7. Electrical Parts List

7-1 WS32Z68PSGXXEC

Level	Loc. No.	Code No.	Description ; Specification	Remark
			ASSY CHASSIS	
1	*	AA91-05665C	ASSY CHASSIS;WS32Z68PSGXXEC,K55A	S.N.A
..2	C-BLOC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
..2	D-FOCU	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
..2	MP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
..2	PCB	AA61-00706B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
..2	TBA+HC	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2	WP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
..2		AA94-12048A	ASSY PCB MISC-MICOM BOARD(TOP);32Z6,K55A	
...3	CNM01	3711-000775	CONNECTOR-HEADER;BOX,26P,2R,2.54mm,STRAI	
...3	CNM01A	AA39-00334A	LEAD CONNECTOR;K55A/WS32Z68P,UL2651#28,U	
...3	CNM02	3711-000775	CONNECTOR-HEADER;BOX,26P,2R,2.54mm,STRAI	
...3	CNM02A	AA39-00334A	LEAD CONNECTOR;K55A/WS32Z68P,UL2651#28,U	
...3	CNM03	3711-002645	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH	
...3	ICM02	1102-001133	IC-EPROM;M27W201-80B6,256KX8BIT,DIP,32P,	
...3	ICM04	1203-001943	IC-VOL. DETECTOR;7025,TO-92,3P,-,PLASTIC	
...3	MB+HC	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
...3	XM01	2801-004071	CRYSTAL-UNIT;6MHZ,30PPM,28-AAM,20PF,400H	
...3		AA97-12147B	ASSY SMD-MICOM BOARD;32Z6,K55A,PAL(EUROP	S.N.A
....4	CM01	2203-001628	C-CERAMIC,CHIP;0.03nF,5%,50V,NP0,TP,1608	
....4	CM02	2203-001628	C-CERAMIC,CHIP;0.03nF,5%,50V,NP0,TP,1608	
....4	CM03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	CM04	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	CM05	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	CM06	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	CM07	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	CM08	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	CM09	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	CM10	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	CM11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	CM12	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	CM13	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	CM14	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	CM15	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
....4	CM16	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
....4	CM17	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
....4	CM18	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
....4	CM19	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
....4	CM20	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	CM21	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	ICM01	1204-001912	IC-DECODER;SDA5550M,P-MQFP,100P,-,PLASTI	
....4	ICM03	1106-001367	IC-SRAM;K6R4008C1C-J12,512KX8BIT,SOJ,36P	
....4	LM01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
....4	LM02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
....4	LM03	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
....4	LM04	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
....4	LM05	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
....4	LM06	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
....4	LM07	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
....4	LM08	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
....4	PCB	AA41-00669A	PCB-MICOM;CW29Z4,FR-4,2L,A,1.6T,180X245,	S.N.A
....4	RM01	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4	RM02	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4	RM03	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
....4	RM04	2007-000121	R-CHIP;820ohm,5%,1/16W,DA,TP,1608	
....4	ZM01	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
....4	ZM02	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
....4	ZM03	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
..2		AA94-12051A	ASSY PCB MISC-CRT;32Z6,K55A	
...3	C522	2201-002117	C-CERAMIC,DISC;4.7nF,20%,3kV,Y5U,TP,16x6	
...3	C523	2301-001192	C-FILM,MPPF;820nF,5%,400V,TP,29x18.5x25.	
...3	CNC01	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	CNC01A	AA39-00088A	LEAD CONNECTOR-ASSY;HERCULES,UL1007/1185	
...3	CNC02	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3	CNC02A	AA39-00127A	LEAD CONNECTOR-ASSY;,8P,35155-0800,S,400	
...3	GT501A	AA39-00341A	LEAD CONNECTOR;K55A(WT-32Z4HD),UL1015#18	
⚠ ...3	GT503S	AA39-20010B	LEAD CONNECTOR-ASSY;,1P,YFH800-01,S,500,	
...3	IC501	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
....4		1201-001131	IC-VIDEO AMP;6111,SIP,9P,-,SINGLE,-,PLAS	
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3	IC502	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC503	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC504	BH99-00038E	ASSY HEAT/SINK;TDA2030,AMP,HERCULES,BH62	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	1201-000010	IC-OP AMP;2030,PENTAWATT,5P,-,SINGLE,-,C	
....4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
....4	CIS	BH62-00041A	HEAT SINK-TR;PN17LT,A1050S,T1.0,50,23,-,	S.N.A
...3	QF09	AA96-00243M	ASSY H/S;-,AMP,AA62-000450A,2SA1011,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000131	TR-POWER;2SA1011-D,PNP,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	QF10	AA96-00243L	ASSY H/S;-,CRT,AA62-000450A,2SC2344,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000153	TR-POWER;2SC2344-D,NPN,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	R529	2008-000264	R-FUSIBLE(S);1ohm,5%,1W,AF,TP,3.9x10mm	
...3	SC01	3722-001503	JACK-PIN;1P,1PI,NI,RED,SCR-JACK	
⚠ ...3	V999S	3704-001032	SOCKET-CRT;8P,29PI,35.5PI,AU30U	
...3		AA97-13361B	ASSY AUTO-CRT;32Z7,S57A	S.N.A
....4	C501	2201-000193	C-CERAMIC,DISC;0.01NF,0.25PF,50V,C0G,TP,	
....4	C504	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C505	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C506	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C507	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C508	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C509	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C510	2201-000291	C-CERAMIC,DISC;1nF,10%,500V,Y5P,TP,7.5x3	
....4	C511	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C512	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C513	2201-000600	C-CERAMIC,DISC;0.56nF,10%,50V,Y5P,TP,5x3	
....4	C514	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
....4	C515	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
....4	C520	2401-000703	C-AL;2200uF,20%,25V,GP,-,12.5x25mm,	
....4	C526	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C528	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C531	2401-002264	C-AL;10uF,20%,350V,GP,TP,10x20mm,5m	
....4	C532	2401-001563	C-AL;47uF,20%,400V,GP,TP,16x25,7.5	
....4	C533	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C534	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C535	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	CF01	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4	CF02	2201-000292	C-CERAMIC,DISC;1nF,10%,50V,Y5P,TP,5x3.5,	
....4	CF03	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF04	2201-000516	C-CERAMIC,DISC;4.7nF,+100-0%,500V,Y5U,TP	
....4	CF05	2301-000261	C-FILM,PEF;4.7nF,5%,100V,TP,10.5x12.5x6.	
....4	CF06	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF07	2201-000604	C-CERAMIC,DISC;0.056nF,+100-0%,500V,SL,T	
....4	CF71	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	CF73	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
....4	CF74	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	CF75	2401-000045	C-AL;10uF,20%,160V,GP,TP,10x16,5	
....4	D501	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D502	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D509	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D510	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D511	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D512	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D513	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D514	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	DF01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF05	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF06	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF07	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DF08	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DZ501	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ502	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ504	0403-000698	DIODE-ZENER;TZP12A,12V,11.4-12.6V,1W,DO-	
....4	DZ510	0403-000734	DIODE-ZENER;TZP15B,15V,14.7-16.5V,1W,DO-	
....4	DZF01	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
....4	DZF02	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
....4	DZF03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	EL100	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL80	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL81	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL82	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL83	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL84	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL85	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL86	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL87	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL88	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL89	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL92	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL94	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL95	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL96	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL97	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL98	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL99	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	FN1	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
....4	FV1	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
....4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT503	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT504	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	L502	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
....4	LF01	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF02	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF03	2701-000112	INDUCTOR-AXIAL;100uH,10%,3x7mm	
....4	LF04	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF06	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF08	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF09	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF11	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	PCB	AA41-00578D	PCB-CRT;CT-29Z7HR,FR-1,1L,D,1.6T,330X245	S.N.A
....4	Q501	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q502	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q503	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q504	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	QF02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	QF03	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	QF04	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	QF05	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	R501	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R502	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R503	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R504	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R505	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R506	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R507	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R508	2001-000995	R-CARBON;8200HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R509	2008-001047	R-FUSIBLE(S);68ohm,5%,2W,AF,TP,3.9x10mm	
....4	R510	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R511	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R512	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R513	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R514	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R515	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R516	2001-001153	R-CARBON(S);470HM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R518	2001-001095	R-CARBON(S);2.2MOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R519	2001-000356	R-CARBON;150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R520	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R522	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R523	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R525	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7	
....4	R527	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R528	2003-000458	R-METAL OXIDE(S);100ohm,5%,2W,AF,TP,4x12	
....4	R530	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R531	2001-000539	R-CARBON;24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R540	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R541	2008-001053	R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
....4	R554	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R555	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R556	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R560	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R561	2001-001126	R-CARBON(S);300OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R562	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R563	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R564	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R565	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R566	2001-001040	R-CARBON(S);0.68OHM,5%,1/2W,AA,TP,2.4X6.	
....4	RF13	2008-001053	R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
....4	RF14	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF15	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF16	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF17	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF18	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF19	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF20	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF21	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF22	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF23	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF24	2003-001018	R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
....4	RF25	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF26	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF27	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF28	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF29	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF30	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF31	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF32	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	RF33	2001-001053	R-CARBON(S);1.5OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF34	2001-001100	R-CARBON(S);2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF35	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	RF36	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA94-12054B	ASSY PCB MISC-CONTROL;32Z6,K55A,CIS	
...3	CNY01	AA39-00100E	LEAD CONNECTOR-ASSY;,4P,YBNH250-04,35155	
...3	CPC+CC	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
...3	SWY01	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY02	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY03	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY04	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY05	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY06	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-12449A	ASSY AUTO-CONTROL;29Z6,K55A,PAL	S.N.A
....4	DZY03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZY04	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	LY01	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	PCB	AA41-00651A	PCB-CONTROL;CS29Z7HF,FR-1,1L,A,1.6T,330X	S.N.A
....4	RY02	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY03	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY04	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY05	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY06	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3		AA96-00936C	ASSY COVER P-COVER CONTROL;32Z6,CIS,HIPS	S.N.A
....4	KC+CC	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
....4		AA63-60001R	SPACER-FELT;-,FELT,-,-,-,-,T0.35,-,200X1	S.N.A
....4		AA64-02662A	KNOB-CONTROL;Z7,ABS,HB,G3676,S104M+W971	
....4		AA63-00557B	COVER-CONTROL;32Z6,HIPS,HB,G4309,DGN-118	S.N.A
..2		AA96-00908J	ASSY COVER P-TERMINAL BOARD;32Z6,HIPS VO	
...3		AA64-02823B	INLAY-T/BOARD;Z7,PS SHEET,T0.5,GUJU	S.N.A
...3		AA65-00025A	TERMINAL-BOARD,ANT;,HIPS V0,BLK	S.N.A
⚠ ..2		AA96-20130H	ASSY POWER CORD;-,CP2/NO(4.0R),H/S 500MM	S.N.A
...3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3		AA39-10003B	CBF POWER CORD;-,KJP-140,KLCE-2F,2.4m,HO	
...3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A
..2		AA95-03086A	ASSY SUB-PCB MICOM BOARD(BOTTO;32Z6,K55A	
...3	CN01	3711-005091	CONNECTOR-HEADER;NOWALL,26P,1R,1.778MM,S	

Level	Loc. No.	Code No.	Description ; Specification	Remark
...3	CN02	3711-005091	CONNECTOR-HEADER;NOWALL,26P,1R,1.778MM,S	
...3	CNM01	3711-000775	CONNECTOR-HEADER;BOX,26P,2R,2.54mm,STRAI	
...3	CNM02	3711-000775	CONNECTOR-HEADER;BOX,26P,2R,2.54mm,STRAI	
...3	PCB	AA41-00670A	PCB-MICOM BODY;CW29Z4,FR-4,2L,A,1.6T,245	S.N.A
..2		AA65-00011B	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
..2		AA61-01190A	HOLDER-CHASSIS;Z7,HIPS V0,G4309	S.N.A
..2		AA94-07792A	ASSY PCB MISC-DYNAMIC FOCUS;CT-29Z7HR,K5	
...3	LH01	AA26-90002C	TRANS-DUMMY;-,-,-,-,-,-,-,-,-,-,EER2	
...3	LH02	AA27-40003L	COIL HORIZ. WIDTH;-,1.0mH,DR14x20,2UEW0.	
...3	RH28	2008-001113	R-FUSIBLE(S);0.22ohm,10%,2W,AG,TP3.9x12	
...3	WIRE3	AA39-20061C	LEAD CONNECTOR-ASSY;,3P,YFH800-03,S,200,	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-07229L	ASSY AUTO-DYNAMIC FOCUS;CT-29Z7HR,K55A	S.N.A
....4	EY01	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
....4	EY02	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
....4	EY03	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
....4	EY04	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
....4	EY05	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
....4	EY06	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
....4	EY07	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
....4	EY08	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
....4	EY09	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
....4	GTH01	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTH02	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTH03	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	PCB	AA41-00152C	PCB-DOUBLE FOCUS;CW29A6VN8X/XEF,FR-1,1L,	S.N.A
..2		AA94-11730A	ASSY PCB MISC-MASTER;Z6,Z7Z9,K55A,S57A,P	
...3	GTAY01	AA39-20179C	LEAD CONNECTOR-ASSY;,3(2)P,YFH800-150,S,	
...3	HP+PCB	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
...3	MPP+LP	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
⚠ ...3	SW811S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
...3		AA97-05539A	ASSY AUTO-MASTER;WS36Z48D,KS4A,PAL	S.N.A
....4	EY01	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
....4	EY02	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
....4	EY03	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
....4	EY04	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
....4	GTY05	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY06	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY07	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY08	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY09	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY10	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	PCB	AA41-00521A	PCB-MASTER S/W;CS32Z4,FR-1,1L,A,1.6T,245	S.N.A
...3		AA61-00719B	HOLDER-MASTER;T6,W3,HIPS V0,BLK,J52A	S.N.A
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA94-11731A	ASSY PCB MISC-LED;CS29Z6HPJX/BWT,K55A	
...3	CN01	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,YBNH025-05,67096	
...3	CY01	2401-002291	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	
...3	LD01	0601-001381	LED;ROUND,RED/GRN,5.0MM,650/563NM	
...3	RM01	AA32-00012A	MODULE REMOCON;ORC-50HF2,38KHZ,940NM,MES	
...3		AA97-12478A	ASSY AUTO-LED;CS29Z6,K55A	S.N.A
....4	DC01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DC02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	PCB	AA41-00702A	PCB-LED;WS32Z6HF,FR-1,1L,A,1.6T,245X245,	S.N.A
....4	RY01	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
..2		AA94-11750C	ASSY PCB MISC-A/V SIDE;32Z6,K55A,PAL	
...3	AV+CV	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
...3	CN701	AA39-00317B	LEAD CONNECTOR-ASSY;K55A/WT-32Z4HD,UL100	
...3	CN703	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,YBNH025-05,67096	
...3	CN704	AA39-00070B	LEAD CONNECTOR-ASSY;,4P,YBNH250-04,35184	
...3	JA701	3722-001164	JACK-PIN;3P,3.4mm,SN,WH:YE:RE,#16-22	
...3	JK04	3722-000544	JACK-VHS;4P,11.5mm,AG,BLK,N	
...3	JKH701	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	
...3		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
...3		AA96-00939C	ASSY COVER P-COVER AV;32Z6,CIS,HIPS HB,G	S.N.A
....4		AA63-60001R	SPACER-FELT;-,FELT,-,-,-,-,T0.35,-,200X1	S.N.A
....4		AA64-02667B	INLAY-AV;Z7,PS SHEET,T0.3,DGN-K189,K55A	S.N.A
....4		AA63-00558A	COVER-A/V;32Z6,HIPS,HB,G4309,DGN-1189	S.N.A
...3		AA97-12697A	ASSY AUTO-A/V SIDE;,K55A,PAL,29Z6	S.N.A
....4	C701	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C702	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C707	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
....4	C708	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
....4	DZ701	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500m	
....4	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L705	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L706	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L707	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L708	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	PCB	AA41-00620B	PCB-A/V SIDE(Z7);CT-29Z7HR,FR-1,1L,B,1.6	S.N.A
....4	R701	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R702	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
..2		AA94-12047A	ASSY PCB MAIN;WS32Z68PGX/XEC,K55A,PAL	
...3	C-BLOC	AA26-00069A	TRANS FBT;FUJ-29C002C(S),DREAM3,4,-,-,-,	
...3	C806	2306-000112	C-FILM,MPPF;100nF,20%,250V,BK,-,15mm	
...3	C820	2401-003419	C-AL;2200uF,20%,50V,WT,TP,16X35.5mm	
...3	CABLE	AA39-30007B	CBF IF;-,T,150mm,1365#26	
...3	CN502	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3	CN702	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	CN702A	AA39-00114C	LEAD CONNECTOR-ASSY;,12P,35155-1200,S,50	
...3	D801S	AA96-00276C	ASSY H/S;-,BRIDGE ,AA62-00052A,GSIB660,K	S.N.A
....4		AA62-00052A	HEAT SINK-PS;-,-,-,SILVER,HOLE 18.5mm, 2	S.N.A
....4		AA60-30003A	WASHER;T1.5,SBHG-1	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		0402-001399	DIODE-BRIDGE;GSIB660,600V,6A,SIP-4,BK	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	GT804S	AA39-20010C	LEAD CONNECTOR-ASSY;,1P,YFH800-01,S,600,	
...3	HC401	BP96-00159A	ASSY HEAT SINK P;H/S,SCREW,FJL6920,FMP-3	S.N.A
....4	CIS	AA60-30001A	WASHER-PLATE;M3,ID3.5,15X8.5,T1.0,SBHG	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	BP62-00015A	HEAT SINK-PS;WT-36Z4HR,A1050S,T2.0,86,80	S.N.A
....4	CIS	BH73-00028B	SILICON/RUBBER-HS;TV ALL,SILICON,26*30*T	S.N.A
....4	CIS	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
....4	CIS	0502-001230	TR-POWER;FJL6920YDTU,N,200000MW,TO-264 F	
....4	CIS	0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	
...3	HC801	AA96-00475A	ASSY H/S;-,REGULATOR,AA62-00066B,FML-G12	S.N.A
....4		AA62-00066B	HEAT SINK;D2,D3,AL ,T1.0,89,70,-,AA62-00	S.N.A
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
....4		0402-001230	DIODE-RECTIFIER;FMG-G2CS,1000V,3A,TO-220	
....4		0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	IC301	AA96-50381A	ASSY H/S;-,-,AA62-30180B,LA7845,-	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1204-000517	IC-VERTICAL DEF.;LA7845,SIP,7P,-,PLASTIC	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
....4		AA62-30180B	HEAT SINK-ES;-,A6063 EXTR.,2,WHT,70MM,-,	S.N.A
⚠ ...3	IC401	1202-000103	IC-VOLTAGE COMP.;393,DIP,8P,300MIL,DUAL,	
...3	IC602	AA96-50369D	ASSY H/S;-,SOUND,AA62-30181F,TDA7269,HER	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1201-001385	IC-POWER AMP;7269A,ZIP,11,19.6,DUAL,13,P	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
....4		AA62-30181F	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
⚠ ...3	IC801S	AA96-50371H	ASSY H/S;-,SMPS,AA62-30181H,5Q1565RF,HER	S.N.A
....4		AA61-11028A	BRACKET;-,SECC,T1.0,-,-,-,-	S.N.A
....4		AA62-30181H	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
....4		1203-002512	IC-PWM CONTROLLER;KA5Q1565RF-YDTU,TO-3PF	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	IC805	AA96-00243K	ASSY H/S;-,REGULATOR,AA62-000450A,KA78R0	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
....4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
...3	JA701	3722-001884	JACK-SCART;42P,-,SNPB,BLK,-	
...3	JA702	3722-001767	JACK-PIN;2P(9P),-,NI,WHI/RED,-	
⚠ ...3	LR402S	AA27-10004F	COIL CHOKE;-,56uH,K,-,2.5A,BK,-,DR12x15,	
⚠ ...3	LR403S	AA27-30003F	COIL LINEARITY;-,7.6uH,DR15x18,USTC 0.12	
⚠ ...3	LR404S	AA27-00031A	COIL HORIZ. WIDTH;-,140UH,AR 8X20,0.8MM,	
⚠ ...3	PFC01S	AA27-00269A	COIL CHOKE-PFC;35MH,CPTTV,35MH,10%,2.0OH	
...3	Q402	0505-001116	FET-SILICON;BUZ73A,N,200V,22A,0.6ohm,40W	
...3	Q804	BH99-00007S	ASSY HEAT/SINK;KSC2073,MICOM,HERCULES,BH	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	0502-001007	TR-POWER;KSC2073-H2,NPN,25W,TO-220,ST,6	
....4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
....4	CIS	BH62-00007A	HEAT SINK-TR;-,T1.0,L20*H30,CDA	S.N.A
⚠ ...3	RL801S	3501-001053	RELAY-POWER;5Vdc,530mW,10A,1FormA,15mS,5	
...3	T401	AA26-50001S	TRANS-HORIZ.DRIVE;-,-,-,6.0mH,-,-,44uH,-	
⚠ ...3	T444S	AA26-00187A	TRANS FBT;FUJ34H003F,CPTTV,2.3MH,FERRITE	
⚠ ...3	T801S	AA26-00178A	TRANS SWITCHING;EER5345,K55A,PAL,CIS,160	
⚠ ...3	TU02S	AA40-00051A	TUNER;TCPW3001PC18B(S),TCPW3001PC18B(S),	
...3		AA95-03091A	ASSY SUB-PCB,FEATURE BOX;,K55A, ,PAL	
....4	BR01	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	BR02	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4	CN01	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4	CN02	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4	CN03	3711-003601	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,ANGLE,	
....4	DC41	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
....4	DC51	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	DX01	2802-001177	RESONATOR-CERAMIC;2.696MHZ,0.4%,BK,10X4.	
....4	EC48	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	EC49	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	EX01	2801-004019	CRYSTAL-UNIT;20.25MHz,30ppm,28-AAM,13pF,	
....4	IC06	1203-002000	IC-VOL. DETECTOR;7027,TO-92,3P,-,PLASTIC	
....4		AA97-12148A	ASSY SMD;,K55A PAL	S.N.A
.....5	DC01	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5	DC02	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5	DC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC04	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC05	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC06	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....5	DC07	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5	DC08	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC09	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,	
.....5	DC10	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC12	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC13	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC14	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC17	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC19	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC20	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC21	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC22	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC23	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....5	DC24	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC25	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC26	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC27	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC28	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC29	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC30	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC31	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC32	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	DC33	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC34	2203-000896	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
.....5	DC35	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	DC36	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5	DC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC39	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	DC40	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5	DC43	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC45	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	DC49	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	DC52	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	DD01	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD02	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD03	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD04	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD05	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD06	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD07	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD08	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD09	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD10	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD11	0403-000746	DIODE-ZENER;RLZ3.9B,3.9V,3.89-4.16V,400m	
.....5	DD13	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD14	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD15	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD16	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD17	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD18	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD19	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD20	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
.....5	DL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	DL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	DL03	2703-001070	INDUCTOR-SMD;100uH,10%,4.5x3.2x3.2mm	
.....5	DQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ02	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ03	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ04	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ05	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ07	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ08	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ09	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
.....5	DQ10	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ11	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR05	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR06	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR08	2007-000691	R-CHIP;3.3Mohm,5%,1/16W,DA,TP,1608	
.....5	DR09	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR10	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR13	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5	DR14	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5	DR15	2007-000869	R-CHIP;4.7Kohm,1%,1/16W,DA,TP,1608	
.....5	DR16	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR17	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR18	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR19	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR23	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP,1608	
.....5	DR24	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
.....5	DR25	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5	DR26	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR27	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....5	DR28	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....5	DR29	2007-000118	R-CHIP;390ohm,5%,1/16W,DA,TP,1608	
.....5	DR30	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR31	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR32	2007-000081	R-CHIP;2.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR33	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5	DR34	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR36	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR37	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR38	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR39	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR40	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....5	DR41	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....5	DR42	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR43	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR44	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR45	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR46	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR47	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR49	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR50	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR51	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR52	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR53	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR54	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR55	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR56	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR57	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR58	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR59	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR60	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR61	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR62	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR63	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR64	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR65	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	DR66	2007-000088	R-CHIP;7.5Kohm,5%,1/16W,DA,TP,1608	
.....5	DR68	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR69	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR70	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR80	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR81	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
.....5	DR82	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
.....5	DR86	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR87	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR88	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	EC01	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC02	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC04	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	EC08	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC09	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC10	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC12	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC13	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC14	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC15	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC17	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC18	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC19	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC20	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC21	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC22	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC23	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC24	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	EC29	2203-000681	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,160	
.....5	EC30	2203-000681	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,160	
.....5	EC31	2203-000681	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,160	
.....5	EC32	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC33	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC34	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,160	
.....5	EC35	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,160	
.....5	EC36	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC39	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC40	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC41	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC42	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC43	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC44	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC45	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC46	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC47	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	EC51	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	EC52	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC53	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC54	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC55	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC56	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC57	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	EC58	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	EC59	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC60	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC62	2203-000681	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,160	
.....5	EC63	2203-000681	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,160	
.....5	EC64	2203-000681	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,160	
.....5	EC65	2203-000681	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,160	
.....5	EL04	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5	EL05	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EL06	3301-001324	CORE-FERRITE BEAD;AB,15OHM,2X1.25X0.9MM,	
.....5	EL07	3301-001324	CORE-FERRITE BEAD;AB,15OHM,2X1.25X0.9MM,	
.....5	EL08	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EL09	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EL13	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EQ04	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....5	EQ05	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....5	EQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	ER01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER02	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	ER06	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5	ER07	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5	ER09	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	ER13	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER16	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER19	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	ER21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	ER22	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER24	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER25	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER26	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER29	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	ER30	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	ER31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	ER32	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	ER33	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	ER34	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	ER35	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	ER36	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	IC01	1204-001938	IC-DECODER;VSP9407B-B11,MQFP,80P,14X14MM	
.....5	IC04	1204-001989	IC-VIDEO PROCESS;CXA2165Q,QFP,64P,20X14M	
.....5	IC05	1203-002186	IC-POSI.FIXED REG.;18,DPAK,3P,240MIL,PLA	
.....5	IC10	1001-001177	IC-VIDEO SWITCH;TEA6425D,VIDEO SWITCH ,S	
.....5	IC11	0801-000662	IC-CMOS LOGIC;74HC123,MULTIVIBATOR,SOP,1	
.....5	PCB	AA41-00644B	PCB-PAL FERTURE BOX;CS29Z6,FR-4,4L,B,1.6	S.N.A
.....5	SC29	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SC31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SC33	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SC43	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	SC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	SC47	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5	SC48	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5	SC49	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	SL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	SR09	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	SR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	SR11	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	SR30	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR32	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR33	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR34	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	SR36	2007-000259	R-CHIP;1.6Kohm,5%,1/16W,DA,TP,1608	
.....5	SR37	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5	TC01	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC02	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC03	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC04	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC05	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC06	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC07	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	TC08	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	TD01	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	TL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	TQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	TQ02	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	TR01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	TR03	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	TR05	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR07	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	TR08	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR09	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	TR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3		AA97-12041B	ASSY ROBOT-MAIN;32 ,K55A,EUROPE	S.N.A
....4	C423	2301-001192	C-FILM,MPPF;820nF,5%,400V,TP,29x18.5x25.	
....4	C426	2306-001004	C-FILM,MPPF;300nF,5%,400V,TP,26x14x21mm,	
....4	C803	2401-002227	C-AL;330uF,20%,450V,GP,BK,35x45,10	
....4	C815	2401-003024	C-AL;220uF,20%,200V,WT,TP,22x35,10	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	CN902	3711-003043	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
⚠ 4	CR405S	2301-001343	C-FILM,MPPF;3.9nF,5%,2kV,TP,29x9.5x16mm,	
⚠ 4	CR406S	2301-001525	C-FILM,PPF;4.7NF,+-5%,1.6KV,TP,28.5*16.0	
⚠ 4	CR407S	2301-001398	C-FILM,MPPF;3.3nF,5%,2kV,TP,29x8.5x1.5mm	
⚠ 4	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ 4	CY802S	2201-000446	C-CERAMIC,DISC;3.3nF,20%,400V,Y5U,TP,15x	
⚠ 4	FP801S	3601-000297	FUSE-CARTRIDGE;250V,5A,TIME-LAG,GLASS,5.	
....4	IC601	1204-001971	IC-SOUND PROCESSOR;MSP3411G-P0-B11,DIP,5	
....4	IC803	1203-001225	IC-POSI.FIXED REG.;78R09,TO-220,4P,-,PLA	
....4	IC902	1103-001177	IC-EEPROM;24WC16,2048x8Bit,DIP,8P,-,-,2.	
....4	L808	AA27-00098A	COIL CHOKE;-,-,24uH,10%,-,0.1,3.0A,DR10X	
⚠ 4	LR405S	AA27-00057A	COIL HORIZ. WIDTH;-,10mH,YL-9N 15x27.5 C	
⚠ 4	LX801S	AA29-30002N	FILTER LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ 4	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ 4	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
⚠ 4	PT801S	1404-001026	THERMISTOR-PTC;7ohm,20%,-,290V,25A,-,ST	
⚠ 4	TU01S	AA40-00050A	TUNER;TCLW3101PD18A(S),TCLW3101PD18A(S),	
....4		AA97-12044B	ASSY AUTO-MAIN;32,K55A,EUROPE	S.N.A
.....5	C101	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C102	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C104	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
.....5	C105	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C106	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C107	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C108	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
.....5	C109	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
.....5	C110	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
.....5	C111	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C112	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C113	2202-000216	C-CERAMIC,MLC-AXIAL;0.027NF,5%,50V,SL,TP	
.....5	C116	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C117	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
.....5	C118	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
.....5	C119	2401-002009	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
.....5	C120	2401-002009	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
.....5	C201	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C202	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
.....5	C206	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C207	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C239	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C240	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C302	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
.....5	C303	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C304	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
.....5	C305	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
.....5	C306	2301-000160	C-FILM,PEF;12nF,5%,50V,TP,11.0x6.0x9.0mm	
.....5	C307	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
.....5	C308	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
.....5	C401	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
.....5	C402	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
.....5	C403	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
.....5	C404	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
.....5	C406	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.	
.....5	C408	2301-001143	C-FILM,PPF;56nF,5%,400V,TP,20x10x17,7.5	
.....5	C409	2303-001001	C-FILM,PPF;22nF,5%,630V,TP,18x14.5x8.5mm	
.....5	C411	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C412	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
.....5	C413	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
.....5	C414	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
.....5	C416	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C417	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C418	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
.....5	C420	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
.....5	C421	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
.....5	C422	2401-001527	C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
.....5	C425	2301-001259	C-FILM,MPPF;100nF,5%,400V,TP,19x8x16,7.5	
.....5	C432	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C601	2201-000558	C-CERAMIC,DISC;0.47nF,10%,50V,Y5P,TP,5x3	
.....5	C602	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
.....5	C603	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C604	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
.....5	C605	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C606	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C607	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C608	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C610	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C611	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C612	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
.....5	C613	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
.....5	C614	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C615	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C619	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C620	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C621	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C622	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C623	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C624	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C625	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C626	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C627	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C628	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C629	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C630	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C631	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C632	2201-000370	C-CERAMIC,DISC;0.22nF,10%,50V,Y5P,TP,4x3	
.....5	C633	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C634	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
.....5	C635	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C636	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C637	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C638	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C639	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C640	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C641	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C642	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C643	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C644	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
.....5	C645	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C646	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C647	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
.....5	C648	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
.....5	C649	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm	
.....5	C650	2401-001176	C-AL;33uF,20%,25V,GP,TP,5x11,5	
.....5	C651	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C652	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C653	2401-002216	C-AL;2200uF,20%,35V,GP,TP,16x25,7.5	
.....5	C654	2201-000611	C-CERAMIC,DISC;0.056NF,5%,50V,C0G,TP,7X3	
.....5	C655	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
.....5	C656	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
.....5	C657	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
.....5	C658	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C659	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C660	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C701	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
.....5	C801	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
.....5	C802	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
.....5	C804	2201-000332	C-CERAMIC,DISC;2.2nF,20%,250V,Y5U,TP,9x4	
.....5	C805	2201-000332	C-CERAMIC,DISC;2.2nF,20%,250V,Y5U,TP,9x4	
.....5	C807	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.	
.....5	C808	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
.....5	C809	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
.....5	C810	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
.....5	C811	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
.....5	C812	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C814	2201-002028	C-CERAMIC,DISC;0.47nF,10%,2kV,Y5P,TP,7.5	
.....5	C816	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
.....5	C817	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C818	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
.....5	C819	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C821	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
.....5	C822	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C823	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
.....5	C824	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
.....5	C825	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C826	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
.....5	C827	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
.....5	C828	2201-000374	C-CERAMIC,DISC;0.22NF,5%,50V,C0G,TP,10.5	
.....5	C830	2201-000984	C-CERAMIC,DISC;0.68nF,10%,2kV,Y5P,TP,9x5	
.....5	C831	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C832	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
.....5	C833	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	C834	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
.....5	C835	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
.....5	C836	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C837	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C838	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
.....5	C840	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
.....5	C841	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
.....5	C843	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C844	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C901	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C902	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C903	2202-000719	C-CERAMIC,MLC-AXIAL;6.8nF,20%,16V,Y5R,TP	
.....5	C904	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C905	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C906	2202-000791	C-CERAMIC,MLC-AXIAL;150pF,10%,50V,Y5P,TP	
.....5	C912	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C917	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C918	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
.....5	C919	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C920	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C921	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C922	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C923	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C924	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
.....5	C925	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C927	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
.....5	CN601	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
.....5	CN901	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
.....5	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D202	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D207	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 5	D401	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 5	D402	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 5	D403	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 5	D404	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 5	D405	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D406	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 5	D408	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 5	D409	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
⚠ 5	D410	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D411	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
.....5	D603	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D607	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 5	D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 5	D804	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 5	D805	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D808	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 5	D812	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D816	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
.....5	D901	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D902	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D903	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D904	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D907	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
.....5	DZ302	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
.....5	DZ303	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
.....5	DZ304	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
.....5	DZ305	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
.....5	DZ306	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
.....5	DZ307	0403-001118	DIODE-ZENER;MTZ30A,32V,26.99-28.39V,500m	
.....5	DZ401	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
.....5	DZ402	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	DZ404	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ601	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ602	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
.....5	DZ603	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ604	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ605	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ606	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ607	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
.....5	DZ608	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
.....5	DZ801	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
.....5	DZ802	0403-000716	DIODE-ZENER;MTZJ4.7B,4.7V,4.55-4.8V,500m	
.....5	DZ803	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
.....5	DZ804	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
.....5	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
.....5	DZ807	0403-001330	DIODE-ZENER;MTZJ30A,26.99-28.39V,500mW,D	
.....5	DZ808	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ902	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ906	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ907	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ908	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ909	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ910	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ911	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ912	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	EL201	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL202	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL203	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL204	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL401	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL402	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL407	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL408	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL805	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL806	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL807	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL808	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY302	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY303	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY403	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY404	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY405	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY406	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY407	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY408	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY409	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY410	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY411	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY412	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY413	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY414	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY415	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY417	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY418	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY419	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY420	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY421	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY422	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY423	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY424	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY425	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY426	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY429	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY430	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY431	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY432	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY433	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY434	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY435	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY436	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY437	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY439	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY441	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY446	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY447	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY603	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY604	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY701	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY702	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY703	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY704	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY705	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY706	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY801	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY802	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY803	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY804	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	EY805	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY806	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY809	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY810	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY811	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY812	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY813	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY814	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY815	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY816	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY817	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY820	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY824	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY825	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY828	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY829	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY830	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY831	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY832	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY833	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY835	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY836	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY837	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY838	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY839	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY840	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY841	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY842	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY844	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY845	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY846	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY848	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY850	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY851	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY853	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY854	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY855	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY856	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY857	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY858	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY859	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY860	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY861	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY862	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY864	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY865	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY871	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	EY872	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	S.N.A
.....5	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
.....5	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
.....5	FA801S	3601-000120	FUSE-AXIAL LEAD;125V,2.5A,FAST-ACTING,GL	
.....5	FA802S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
.....5	FA803S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
.....5	GT102	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT301	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT302	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT401	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT402	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT404	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT405	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT406	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT409	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT410	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT411	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT412	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	HIC401	AA13-00094A	IC HYBRID;-,DDRI001A,SIP,5P,-,TP	
.....5	IC202	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
.....5	IC402	1203-000243	IC-POSI.FIXED REG.;7812A,TO-220,3P,-,PLA	
.....5	IC804	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
.....5	IC903	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	J709	2001-000376	R-CARBON;15OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	L101	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
.....5	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
.....5	L103	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
.....5	L104	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
.....5	L106	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
.....5	L201	2701-000200	INDUCTOR-AXIAL;5.6uH,10%,4.2x9.8mm	
.....5	L203	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L402	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
.....5	L403	2701-001040	INDUCTOR-AXIAL;10uH,10%,4.5x14mm	
.....5	L404	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L407	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L409	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L410	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
.....5	L601	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
.....5	L602	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
.....5	L603	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L604	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L605	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L606	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L607	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L608	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L609	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L610	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L612	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L613	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L614	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L703	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L704	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L705	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L706	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L801	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L802	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L803	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L804	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L805	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L806	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L807	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
.....5	L809	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L811	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
.....5	L902	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
.....5	L903	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
.....5	L904	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
.....5	L906	2701-000215	INDUCTOR-AXIAL;8.2uH,10%,2.5x3.4mm	
.....5	L907	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L908	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
.....5	L909	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
.....5	PCB	AA41-00707B	PCB-MAIN;CS29Z6HP,FR-1,1L,B,1.6T,330X245	S.N.A
.....5	Q404	0505-000156	FET-SILICON;IRF620,N,200V,5A,0.8ohm,50W,	
.....5	Q601	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q603	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q801	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q802	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
.....5	Q803	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q901	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q906	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q907	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q908	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q909	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
.....5	Q910	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
.....5	Q912	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q913	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	R101	2001-000938	R-CARBON;680HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R102	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R103	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R104	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R105	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R106	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R107	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R108	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R203	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R204	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R301	2001-001163	R-CARBON(S);560OHM,5%,1/2W,AA,TP,2.4X6.4	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	R302	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5	R303	2001-000016	R-CARBON(S);10HM,5%,1/2W,AA,TP,2.4X6.4MM	
.....5	R304	2008-001087	R-FUSIBLE(S);1.8ohm,5%,2W,AG,TP,3.9x12mm	
.....5	R305	2003-002205	R-METAL OXIDE(S);330ohm,5%,2W,AG,TP,3.9X	
.....5	R306	2003-002205	R-METAL OXIDE(S);330ohm,5%,2W,AG,TP,3.9X	
.....5	R307	2008-001087	R-FUSIBLE(S);1.8ohm,5%,2W,AG,TP,3.9x12mm	
.....5	R308	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5	R309	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R310	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R314	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R315	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R316	2001-001129	R-CARBON(S);330KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R317	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R401	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
.....5	R402	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
.....5	R403	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
.....5	R405	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
.....5	R409	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
.....5	R410	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
.....5	R411	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R412	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
.....5	R413	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
.....5	R414	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
.....5	R415	2004-000698	R-METAL;3.3Kohm,1%,1/4W,AA,TP,2.4x6.4m	
.....5	R416	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
.....5	R418	2004-004045	R-METAL(S);390ohm,1%,1/2W,AA,TP,2.5x6.5m	
.....5	R419	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R420	2004-001397	R-METAL(S);4.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5	R421	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R422	2008-000251	R-FUSIBLE(S);0.27ohm,5%,2W,AF,TP,3.9x10m	
.....5	R423	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
.....5	R424	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
.....5	R425	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
.....5	R426	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
.....5	R428	2004-000698	R-METAL;3.3Kohm,1%,1/4W,AA,TP,2.4x6.4m	
.....5	R430	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
.....5	R431	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
.....5	R432	2001-001164	R-CARBON(S);56KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R433	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
.....5	R434	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
.....5	R435	2003-001042	R-METAL OXIDE(S);5.6Kohm,5%,2W,AF,TP,3.9	
.....5	R440	2004-001893	R-METAL(S);22Kohm,1%,1/2W,AA,TP,2.5x6.5m	
.....5	R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R602	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R603	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R604	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R605	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R606	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R607	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R608	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R609	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R612	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R613	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R614	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R615	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R616	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R617	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R618	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R623	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R624	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R626	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R627	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R628	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R629	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R630	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R631	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R632	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R633	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R634	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R635	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R636	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R637	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R638	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R639	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R704	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R710	2001-000376	R-CARBON;15OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R715	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R716	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R717	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R718	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R723	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R801	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R802	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
.....5	R803	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
.....5	R804	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
.....5	R805	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R806	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R807	2001-001103	R-CARBON(S);20KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R808	2001-001197	R-CARBON(S);910OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R809	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R810	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R811	2001-001155	R-CARBON(S);5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R812	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R813	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R815	2008-000284	R-FUSIBLE(S);0.10HM,10%,2W,AF,TP,3.9X10M	
.....5	R816	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R817	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R818	2001-001131	R-CARBON(S);33KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R819	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
.....5	R820	2001-001096	R-CARBON(S);2.2OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R821	2004-002015	R-METAL(S);140Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5	R822	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R823	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R824	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R827	2008-000284	R-FUSIBLE(S);0.10HM,10%,2W,AF,TP,3.9X10M	
.....5	R828	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm	
.....5	R829	2008-001148	R-FUSIBLE;3.3OHM,5%,1W,AG,TP,3.9X12MM	
.....5	R830	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
.....5	R833	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R835	2003-002181	R-METAL OXIDE(S);68Kohm,5%,2W,AG,TP,3.9x	
.....5	R838	2001-001050	R-CARBON(S);1.5KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R840	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R841	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R842	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R901	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R902	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R903	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R904	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R905	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R906	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R908	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R909	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R910	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R911	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R912	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R913	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R914	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R915	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R916	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R917	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R919	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R920	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R921	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R922	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R923	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R926	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R927	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R928	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R935	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R936	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R937	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R938	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R939	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R940	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R941	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R942	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R945	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R946	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R947	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R948	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R951	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R952	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	R953	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R954	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R955	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R958	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R960	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R961	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R962	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R963	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R966	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R967	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R968	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R972	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R973	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R974	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R981	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R982	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R983	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R984	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R988	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 5	RR430S	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
⚠ 5	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 5	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 5	VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ 5	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
.....5	X601	2801-003903	CRYSTAL-UNIT;18.432MHz,25ppm,28-AAM,12pF	
...3		AA61-00707B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
...3		AA39-20536G	LEAD CONNECTOR-ASSY;,1P,F,F,60MM,1617#22	

ASSY COVER REAR

1	*	AA90-03249D	ASSY COVER REAR;WS32Z68PSGXXEC	S.N.A
..2		AA64-02747C	CABINET-BACK;32Z6,ABS,V0,G5433,SVM2012	
..2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A

ASSY COVER FRONT

1	*	AA90-03246G	ASSY COVER FRONT;WS32Z68PSGXXEC	S.N.A
..2	CA+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	CB+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CB+TBA	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CC+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	CRT+CF	AA60-10050V	SCREW-ASSY;-,SWRCH18A,M6,L30,HH,+,WC,-,Z	S.N.A
..2	PP+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	SPK+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2	TBA+RJ	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2		AA73-00017A	RUBBER-CAP;29Z7,SILICONE RUBBER,WHT	S.N.A
..2		AA73-00005B	RUBBER-CAP;FLAT,PRJ,SILICONE RUBBER,WHIT	
..2		AA96-00933E	ASSY COVER P-CAINET FRONT;WS32Z68PS,ABS	
...3	DP+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
...3	KNOPOW	AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A
...3		AA64-02753A	INDICATOR LED;29Z6,ACRYL,HB,CLEAR	S.N.A
...3		AA64-02752A	WINDOW-RMC;29Z6,PC,V0,VIOLET	S.N.A
...3		AA64-70117B	BADGE-BRAND;-,AL,-,-,L65,R2000,SILVER,SS	S.N.A
...3		AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA60-00091C	SPACER-FELT;-,FELT,230X10,-,-,BLK,T1.0,-	S.N.A
...3		AA60-00091G	SPACER-FELT;-,FELT,200X10,-,-,BLK,T0.5,-	S.N.A
...3		AA64-02746E	CABINET-FRONT;WS32Z68PS,ABS,HB0690M,G430	S.N.A
...3		AA64-02750A	DECORATION-POWER;29Z6,ABS,HB,GRAY,AL	
...3		AA64-02751B	KNOB-POWER;29Z6,PC,V0,VIOLET,MASTER	
..2		AA91-00507A	ASSY HOLDER SPK;-,-,8OHM/15W,-,ASSY HOLD	
..2		AA63-60004K	SPACER-GUM,CRT;-,NTR RUBBER,-,-,-,BLK,T2	S.N.A
..2		AA61-00997A	HOLDER-D,COIL;32Z5,NYLON 66	S.N.A

ASSY ACCESSORY

1	*	AA92-06868A	ASSY ACCESSORY;WS32Z68PSDXXEC,SPAIN,K55A	S.N.A
..2	1	6801-001014	CARD-REGISTRATION;XEU,ENG,MOJO100,L150,W	S.N.A
..2	1	6801-001015	CARD-REGISTRATION;XEG,GERMAN,MOJO100,L15	S.N.A
..2	1	6801-001016	CARD-REGISTRATION;XEF,FRENCH,MOJO100,L15	S.N.A
..2	1	6801-001020	CARD-REGISTRATION;XEP,PORTUGAL,MOJO100,L	S.N.A
..2	1	6801-001019	CARD-REGISTRATION;XEN,DUTCH,MOJO100,L150	S.N.A
..2	1	6801-001018	CARD-REGISTRATION;XET,ITALY,MOJO100,L150	S.N.A
..2	1	6801-001017	CARD-REGISTRATION;XEC,SPANISH,MOJO100,L1	S.N.A
..2		AA68-02538A	MANUAL USERS;CW29Z6,NO,W/P100G,K55A,PIP(	
..2		AA68-02539A	MANUAL USERS;CW29Z6,PL,W/P100G,K55A,PIP(	
..2		AA68-02542A	MANUAL USERS;CW29Z6,SV,W/P100G,K55A,PIP(	
..2		AA68-02543A	MANUAL USERS;CW29Z6,EL,W/P100G,K55A,PIP(	
..2		AA68-02537A	MANUAL USERS;CW29Z6,IT,W/P100G,K55A,PIP(	
..2		AA69-00862A	BAG PE;-,HDPE PE FOAM,T0.03,W400,H240,-,	S.N.A
..2		AA68-02541A	MANUAL USERS;CW29Z6,ES,W/P100G,K55A,PIP(	
..2		AA68-02540A	MANUAL USERS;CW29Z6,PI,W/P100G,K55A,PIP(	
..2		AA59-00266A	REMOCON;TM63,SAMSUNG,51PX,45,SAMSUNG,2.4	
..2		AA68-02451A	MANUAL USERS;CS29Z7HP,ENG,K55A,NON-PIP,T	
..2		AA68-02536A	MANUAL USERS;CW29Z6,HU,W/P100G,K55A,PIP(	
..2		AA68-02535A	MANUAL USERS;CW29Z6,DE,W/P100G,K55A,PIP(	
..2		AA68-02534A	MANUAL USERS;CW29Z6,FR,W/P100G,K55A,PIP(	
..2		AA68-02533A	MANUAL USERS;CW29Z6,FI,W/P100G,K55A,PIP(	
..2		AA68-02532A	MANUAL USERS;CW29Z6,NL,W/P100G,K55A,PIP(	

ASSY P/MATERIAL

1	*	AA92-05372A	ASSY P/MATERIAL;WT-32Z6HR	S.N.A
..2		AA69-00306A	BAG AIR;LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A
..2		AA69-00744F	BAG-SHEET;-,HDPE PE FOAM,T0.015,W1400,H1	S.N.A
..2		AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,	S.N.A
..2		AA63-10007C	BAND-PP;W18,CLEA,1G	S.N.A
..2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A

ASSY BOX

1	*	AA92-05369E	ASSY BOX;WS32Z68PSGXXEC	S.N.A

ASSY CPT

1	*	AA91-05676A	ASSY CPT;WS32Z68PSGXXEC	S.N.A
..2		AA39-00135B	LEAD CONNECTOR-ASSY;,3(2)P,67096-003,HRP	
..2		AA39-20519A	LEAD CONNECTOR-ASSY;,6(4)P,YFH806-06,500	
..2		AA98-70011G	ASSY TBC WIRE(P);-,32inch,NTSC,2PWH,KS4A	S.N.A
..2		AA27-00019A	COIL DEGAUSSING;-,32,14.5ohm,65T,L3800,	
⚠ ..2		AA03-00348A	CRT COLOR;W76ERF042X044,+400MG,0.32MH,7.	

7-2 CS29Z7HRGX/XHK

ASSY CHASSIS

Level	Loc. No.	Code No.	Description ; Specification	Remark
1	*	AA91-05825E	ASSY CHASSIS;CS29Z7HRGX/XHK,HONG KONG,K5	S.N.A
..2	C-BLOC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
..2	D-FOCU	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
..2	MP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
..2	PCB	AA61-00706B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
..2	TBA+HC	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2	WP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
..2		AA94-12376A	ASSY PCB CRT;-Z6,K55A,1080I 50HZ	
...3	C522	2201-002117	C-CERAMIC,DISC;4.7nF,20%,3kV,Y5U,TP,16x6	
...3	C523	2306-000272	C-FILM,MPPF;820nF,5%,400V,BK,29x25.5x18.	
...3	CNC01	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	CNC01A	AA39-00088A	LEAD CONNECTOR-ASSY;HERCULES,UL1007/1185	
...3	CNC02	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3	CNC02A	AA39-00127A	LEAD CONNECTOR-ASSY;,8P,400MM,35155-0800	
...3	GT501A	AA39-00341A	LEAD CONNECTOR;K55A(WT-32Z4HD),UL1015#18	
⚠ ...3	GT503S	AA39-20010B	LEAD CONNECTOR-ASSY;,1P500,YFH800-01,S,	
...3	IC501	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC502	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC503	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
....4		1201-001131	IC-VIDEO AMP;6111,SIP,9P,-,SINGLE,-,PLAS	
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3	IC504	BH99-00038E	ASSY HEAT/SINK;TDA2030,AMP,HERCULES,BH62	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	1201-000010	IC-OP AMP;2030,PENTAWATT,5P,-,SINGLE,-,C	
....4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
....4	CIS	BH62-00041A	HEAT SINK-TR;PN17LT,A1050S,T1.0,50,23,-,	S.N.A
...3	QF09	AA96-00243M	ASSY H/S;-,AMP,AA62-000450A,2SA1011,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000131	TR-POWER;2SA1011-D,PNP,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	QF10	AA96-00243L	ASSY H/S;-,CRT,AA62-000450A,2SC2344,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000153	TR-POWER;2SC2344-D,NPN,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	SC01	3722-001503	JACK-PIN;1P,1PI,NI,RED,SCR-JACK	
⚠ ...3	V999S	3704-001032	SOCKET-CRT;8P,29PI,35.5PI,AU30U	
...3		AA97-12820A	ASSY AUTO-CRT;29Z6,K55A,1080I 50HZ	S.N.A
....4	C501	2201-000193	C-CERAMIC,DISC;0.01NF,0.25PF,50V,C0G,TP,	
....4	C504	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C505	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C506	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C507	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C508	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C509	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C510	2201-000291	C-CERAMIC,DISC;1NF,10%,500V,Y5P,TP,7.5X3	
....4	C511	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C512	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C513	2201-000600	C-CERAMIC,DISC;0.56NF,10%,50V,Y5P,TP,5X3	
....4	C514	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C515	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C520	2401-000703	C-AL;2200uF,20%,25V,GP,-,12.5x25mm,	
....4	C526	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C528	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C531	2401-002264	C-AL;10uF,20%,350V,GP,TP,10x20mm,5m	
....4	C532	2401-001563	C-AL;47uF,20%,400V,GP,TP,16x25,7.5	
....4	C533	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C534	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C535	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	CF01	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4	CF02	2201-000017	C-CERAMIC,DISC;1NF,10%,50V,Y5P,TP,5X3.5M	
....4	CF03	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF04	2201-000516	C-CERAMIC,DISC;4.7NF,+100-0%,500V,Y5U,TP	
....4	CF05	2301-000261	C-FILM,PEF;4.7nF,5%,100V,TP,10.5x12.5x6.	
....4	CF06	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF07	2201-000604	C-CERAMIC,DISC;0.056NF,+100-0%,500V,SL,T	
....4	CF71	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	CF73	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
....4	CF74	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	CF75	2401-000045	C-AL;10uF,20%,160V,GP,TP,10x16,5	
....4	D501	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D502	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D509	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D510	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D511	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D512	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D513	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D514	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DF01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF05	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF06	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF07	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DF08	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DZ501	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ502	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ504	0403-000698	DIODE-ZENER;TZP12A,12V,11.4-12.6V,1W,DO-	
....4	DZ510	0403-000734	DIODE-ZENER;TZP15B,15V,14.7-16.5V,1W,DO-	
....4	DZF01	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
....4	DZF02	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
....4	DZF03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	EL100	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL80	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL81	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL82	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL83	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL84	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL85	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL86	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL87	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL88	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL89	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL92	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL94	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL95	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL96	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL97	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL98	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL99	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	FN1	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
....4	FV1	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
....4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT503	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT504	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	L502	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
....4	LF01	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF02	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF03	2701-000112	INDUCTOR-AXIAL;100uH,10%,3x7mm	
....4	LF04	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF06	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF08	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF09	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF11	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	PCB	AA41-00578D	PCB-CRT;CT-29Z7HR,FR-1,1L,D,1.6T,330X245	S.N.A
....4	Q501	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q502	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q503	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q504	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	QF02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	QF03	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	QF04	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	QF05	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	R501	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R502	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R503	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R504	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R505	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R506	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R507	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	R508	2001-000995	R-CARBON;8200HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R509	2008-001047	R-FUSIBLE(S);68ohm,5%,2W,AF,TP,3.9x10mm	
....4	R510	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R511	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R512	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R513	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R514	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R515	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R516	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R518	2001-001095	R-CARBON(S);2.2MOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R519	2001-000356	R-CARBON;150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R520	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R522	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R523	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R525	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7	
....4	R527	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R528	2003-000458	R-METAL OXIDE(S);100ohm,5%,2W,AF,TP,4x12	
....4	R529	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
....4	R530	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R531	2001-000539	R-CARBON;24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R540	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R541	2008-001053	R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
....4	R554	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R555	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R556	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R560	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R561	2001-001126	R-CARBON(S);300OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R562	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R563	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R564	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R565	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R566	2001-001040	R-CARBON(S);0.68OHM,5%,1/2W,AA,TP,2.4X6.	
....4	RF13	2008-001053	R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
....4	RF14	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF15	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF16	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF17	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF18	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF19	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF20	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF21	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF22	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF23	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF24	2003-001018	R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
....4	RF25	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF26	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF27	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF28	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF29	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF30	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF31	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF32	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	RF33	2001-001053	R-CARBON(S);1.5OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF34	2001-001100	R-CARBON(S);2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF35	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	RF36	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA94-12261B	ASSY PCB MISC-A/V SIDE;29Z7,K55A,PAL,HON	
...3	AV+CV	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
...3	CN701	AA39-00317B	LEAD CONNECTOR-ASSY;K55A/WT-32Z4HD,UL100	
...3	CN703	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,500,YBNH025-05,6	
...3	CN704	AA39-00070B	LEAD CONNECTOR-ASSY;,4P,500MM,YBNH250-04	
...3	JA701	3722-001164	JACK-PIN;3P,3.4mm,SN,WH:YE:RE,#16-22	
...3	JK04	3722-000544	JACK-VHS;4P,11.5mm,AG,BLK,N	
...3	JKH701	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	
...3		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
...3		AA96-00909F	ASSY COVER P-COVER A/V;29Z7,CS29Z7HRG,HI	
....4		AA63-00556A	COVER-AV;29Z7,HIPS,HB,G4309,DGN-1189	S.N.A
....4		AA64-02667B	INLAY-AV;Z7,PS SHEET,T0.3,DGN-K189,K55A	S.N.A
...3		AA97-12697A	ASSY AUTO-A/V SIDE;,K55A,PAL,29Z6	S.N.A
....4	C701	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C702	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C707	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C708	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	DZ701	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500m	
....4	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L705	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L706	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L707	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L708	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	PCB	AA41-00620B	PCB-A/V SIDE(Z7);CT-29Z7HR,FR-1,1L,B,1.6	S.N.A
....4	R701	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R702	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
..2		AA94-12260B	ASSY PCB MISC-CONTROL;29Z7,K55A,PAL,HONG	
...3	CNY01	AA39-00100E	LEAD CONNECTOR-ASSY;,4P,600MM,YBNH250-04	
...3	CPC+CC	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
...3	SWY01	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY02	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY03	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY04	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY05	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY06	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3		AA97-12449A	ASSY AUTO-CONTROL;29Z6,K55A,PAL	S.N.A
....4	DZY03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZY04	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	LY01	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	PCB	AA41-00651A	PCB-CONTROL;CS29Z7HF,FR-1,1L,A,1.6T,330X	S.N.A
....4	RY02	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY03	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY04	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY05	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY06	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3		AA96-00910D	ASSY COVER P-COVER CONTROL;29Z7,CT-29Z7P	
....4	KC+CC	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
....4		AA63-00555E	COVER-CONTROL;29Z7,HIPS,HB,G4309,DGN-118	S.N.A
....4		AA64-02662A	KNOB-CONTROL;Z7,ABS,HB,G3676,S104M+W971	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
⚠ ..2		AA96-20126D	ASSY POWER CORD;-,EP3/YES,N(H/C500MM),MP	S.N.A
...3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,V0,KE-002	S.N.A
...3		AA39-10007X	CBF POWER CORD;-,EP3/YES(HK),H03VVH2-F,2	
..2		AA65-00011B	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
..2		AA96-00908N	ASSY COVER P-TERMINAL BOARD;29Z7,HIPS V0	
...3	PCB	AA41-00641A	PCB-WOOFER JACK;CT-29Z7HR,FR-1,1L,A,1.6T	S.N.A
...3	WB01	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
...3	WB02	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
...3	WCN01	AA39-20005D	LEAD CONNECTOR-ASSY;,3P,200MM,YBNH250-03	
...3	WJ01	3722-001813	JACK-PIN;1P(3P),8.3MM,AU,BLK,-	
...3	WP+TBA	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
...3		AA64-02822H	INLAY-T/BOARD;Z7,PS SHEET,T0.5,K55A WOOF	S.N.A
...3		AA65-00025A	TERMINAL-BOARD,ANT;,HIPS V0,BLK	S.N.A
..2		AA94-12169A	ASSY PCB MISC-LED;34Z7,K55A,PAL	
...3	CN01	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,500,YBNH025-05,6	
...3	LD01	0601-001381	LED;ROUND,RED/GRN,5.0MM,650/563NM	
...3	RM01	AA32-00012A	MODULE REMOCON;ORC-50HF2,38KHZ,940NM,MES	
...3		AA97-13408A	ASSY AUTO-LED;,PAL	S.N.A
....4	CY01	2401-002291	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	
....4	DC01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DC02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	RY01	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4		AA41-00653A	PCB-LED;CS29Z7HF,FR-1,1L,A,1.6T,245X245,	S.N.A
..2		AA61-01190A	HOLDER-CHASSIS;Z7,HIPS V0,G4309	S.N.A
..2		AA94-07792A	ASSY PCB MISC-DYNAMIC FOCUS;CT-29Z7HR,K5	
...3	LH01	AA26-90002C	TRANS-DUMMY;-,-,-,-,-,-,-,-,-,-,-,EER2	
...3	LH02	AA27-40003L	COIL HORIZ. WIDTH;-,1.0mH,DR14x20,2UEW0.	
...3	RH28	2008-001113	R-FUSIBLE(S);0.22ohm,10%,2W,AG,TP,3.9x12	
...3	WIRE3	AA39-20061C	LEAD CONNECTOR-ASSY;,3P,200,YFH800-03,S,	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-07229L	ASSY AUTO-DYNAMIC FOCUS;CT-29Z7HR,K55A	S.N.A
....4	EY01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY03	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY04	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY05	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY06	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY07	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY08	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY09	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	GTH01	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTH02	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTH03	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	PCB	AA41-00152C	PCB-DOUBLE FOCUS;CW29A6VN8X/XEF,FR-1,1L,	S.N.A
..2		AA94-07798A	ASSY PCB MISC-WOOFER;CT-29Z7HR,K55A,KORE	
...3	CNW01	AA39-20055A	LEAD CONNECTOR-ASSY;,6P,200,YBNH025-06,6	
...3	ICW01	AA96-50367D	ASSY H/S;-,POWER,AA62-30181D,TDA7269,ZES	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1201-001385	IC-POWER AMP;7269A,ZIP,11,19.6,DUAL,13,P	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
....4		AA62-30181D	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,70MM,-	S.N.A
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-07229F	ASSY AUTO-WOOFER;CT-29Z7HR,K55A	S.N.A
....4	CNW02	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
....4	CW01	2401-002216	C-AL;2200uF,20%,35V,GP,TP,16x25,7.5	
....4	CW02	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	CW04	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	CW05	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	CW06	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
....4	CW07	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	CW09	2301-000289	C-FILM,PEF;5.6nF,5%,50V,TP,7x6x3,5	
....4	CW10	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	CW12	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	EYW01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EYW02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	PCB	AA41-00588A	PCB-WOOFER;CT-29M8HR,FR-1,1L,A,1.6T,330X	S.N.A
....4	RW01	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RW02	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RW05	2001-001050	R-CARBON(S);1.5KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	RW06	2001-000085	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	RW07	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RW08	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RW09	2001-000085	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	RW10	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RW11	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
..2		AA94-11730A	ASSY PCB MISC-MASTER;Z6,Z7Z9,K55A,S57A,P	
...3	GTAY01	AA39-20179C	LEAD CONNECTOR-ASSY;,3(2)P,YFH800-150,S,	
...3	HP+PCB	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
...3	MPP+LP	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
⚠ ...3	SW811S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
...3		AA97-05539A	ASSY AUTO-MASTER;WS36Z48D,KS4A,PAL	S.N.A
....4	EY01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY03	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY04	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	GTY05	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY06	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY07	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY08	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY09	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY10	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	PCB	AA41-00521A	PCB-MASTER S/W;CS32Z4,FR-1,1L,A,1.6T,245	S.N.A
...3		AA61-00719B	HOLDER-MASTER;T6,W3,HIPS V0,BLK,J52A	S.N.A
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA94-11990G	ASSY PCB MAIN;CS29Z7HRGX/XHK,K55A,HONG K	S.N.A
...3	C-BLOC	AA26-00069A	TRANS FBT;FUJ-29C002C(S),DREAM3,4,-,-,-,	
...3	C423	2306-000272	C-FILM,MPPF;820nF,5%,400V,BK,29x25.5x18.	
...3	C426	2306-000195	C-FILM,MPPF;360nF,5%,400V,TP,26x19x11.5,	
...3	C803	2401-001426	C-AL;470uF,20%,400V,GP,-,35x45mm,10	
...3	C806	2306-000112	C-FILM,MPPF;100nF,20%,250V,BK,-,15mm	
...3	C815	2401-003024	C-AL;220uF,20%,200V,WT,TP,22x35,10	
...3	C820	2401-003419	C-AL;2200uF,20%,50V,WT,TP,16X35.5mm	
...3	CABLE	AA39-30007B	CBF IF;-,T,150mm,1365#26	
...3	CN502	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3	CN702	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	CN702A	AA39-00114C	LEAD CONNECTOR-ASSY;,12P,500MM,35155-120	
...3	CN902	3711-003043	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
⚠ ...3	CR405S	2301-001343	C-FILM,MPPF;3.9nF,5%,2kV,TP,29x9.5x16mm,	
⚠ ...3	CR406S	2301-001343	C-FILM,MPPF;3.9nF,5%,2kV,TP,29x9.5x16mm,	
⚠ ...3	CR407S	2301-001398	C-FILM,MPPF;3.3nF,5%,2kV,TP,29x8.5x1.5mm	
⚠ ...3	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ ...3	CX802S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ ...3	CY802S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
⚠ ...3	D801S	AA96-00276C	ASSY H/S;-,BRIDGE ,AA62-00052A,GSIB660,K	S.N.A
....4		AA62-00052A	HEAT SINK-PS;-,-,-,SILVER,HOLE 18.5mm, 2	S.N.A
....4		AA60-30003A	WASHER;T1.5,SBHG-1	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		0402-001399	DIODE-BRIDGE;GSIB660,600V,6A,SIP-4,BK	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
⚠ ...3	FP801S	3601-000297	FUSE-CARTRIDGE;250V,5A,TIME-LAG,GLASS,5.	

Level	Loc. No.	Code No.	Description ; Specification	Remark
⚠ ...3	GT804S	AA39-20010C	LEAD CONNECTOR-ASSY;,1P,YFH800-01,S,600,	
...3	HC401	BP96-00159A	ASSY HEAT SINK P;H/S,SCREW,FJL6920,FMP-3	S.N.A
....4	CIS	AA60-30001A	WASHER-PLATE;M3,ID3.5,15X8.5,T1.0,SBHG	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	BP62-00015A	HEAT SINK-PS;WT-36Z4HR,A1050S,T2.0,86,80	S.N.A
....4	CIS	BH73-00028B	SILICON/RUBBER-HS;TV ALL,SILICON,26*30*T	S.N.A
....4	CIS	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
....4	CIS	0502-001230	TR-POWER;FJL6920YDTU,N,200000MW,TO-264 F	
....4	CIS	0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	
...3	HC801	AA96-00475A	ASSY H/S;-,REGULATOR,AA62-00066B,FML-G12	S.N.A
....4		AA62-00066B	HEAT SINK;D2,D3,AL ,T1.0,89,70,-,AA62-00	S.N.A
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
....4		0402-001230	DIODE-RECTIFIER;FMG-G2CS,1000V,3A,TO-220	
....4		0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	IC301	AA96-50381A	ASSY H/S;-,-,AA62-30180B,LA7845,-	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1204-000517	IC-VERTICAL DEF.;LA7845,SIP,7P,-,PLASTIC	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
....4		AA62-30180B	HEAT SINK-ES;-,A6063 EXTR.,2,WHT,70MM,-,	S.N.A
⚠ ...3	IC401	1202-000103	IC-VOLTAGE COMP;393,DIP,8P,300MIL,DUAL,	
...3	IC601	1204-001971	IC-SOUND PROCESSOR;MSP3411G-P0-B11,DIP,5	
...3	IC602	AA96-50369D	ASSY H/S;-,SOUND,AA62-30181F,TDA7269,HER	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1201-001385	IC-POWER AMP;7269A,ZIP,11,19.6,DUAL,13,P	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
....4		AA62-30181F	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
...3	IC801S	AA96-50371H	ASSY H/S;-,SMPS,AA62-30181H,5Q1565RF,HER	S.N.A
....4		AA61-11028A	BRACKET;-,SECC,T1.0,-,-,-,-	S.N.A
....4		AA62-30181H	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
....4		1203-002512	IC-PWM CONTROLLER;KA5Q1565RF-YDTU,TO-3PF	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	IC803	1203-001225	IC-POSI.FIXED REG.;78R09,TO-220,4P,-,PLA	
...3	IC805	AA96-00243K	ASSY H/S;-,REGULATOR,AA62-000450A,KA78R0	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
....4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
...3	IC901	AA09-00041A	IC MICOM;,SDA555X-OTP,3.3V,-,128K,SDIP,-	S.N.A
...3	IC902	1103-001177	IC-EEPROM;24WC16,2048x8Bit,DIP,8P,-,-,2.	
...3	JA701	3722-001765	JACK-PIN;9P(9P),-,NI,YEL/GRN/WHT/BLU/RED	
...3	JA702	3722-001766	JACK-PIN;7P(9P),-,NI,GN/WH/WH/BL/RD/RD/R	
...3	L808	AA27-00098A	COIL CHOKE;-,-,24uH,10%,-,0.1,3.0A,DR10X	
⚠ ...3	LR402S	AA27-10004F	COIL CHOKE;-,56uH,K,-,2.5A,BK,-,DR12x15,	
⚠ ...3	LR403S	AA27-00070A	COIL LINEARITY;-,7uH,YL81 DR1518,11mm,17	
⚠ ...3	LR404S	AA27-40001S	COIL HORIZ. WIDTH;-,110uH,SB-5S8202.6,PI	
⚠ ...3	LR405S	AA27-00057A	COIL HORIZ. WIDTH;-,10mH,YL-9N 15x27.5 C	
⚠ ...3	LX801S	AA29-00011A	FILTER LINE NOISE;CZ32W8,-,0.20MAX,1.5KV	
⚠ ...3	LX802S	AA29-00012A	FILTER LINE NOISE;CS29A6PF8X/HAC,-,0.1MA	
⚠ ...3	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ ...3	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
⚠ ...3	PT801S	1404-001026	THERMISTOR-PTC;7ohm,20%,-,290V,25A,-,ST	
...3	Q402	0505-001116	FET-SILICON;BUZ73A,N,200V,22A,0.6ohm,40W	
...3	Q804	BH99-00007S	ASSY HEAT/SINK;KSC2073,MICOM,HERCULES,BH	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	0502-001007	TR-POWER;KSC2073-H2,NPN,25W,TO-220,ST,6	
....4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
....4	CIS	BH62-00007A	HEAT SINK-TR;-,T1.0,L20*H30,CDA	S.N.A
⚠ ...3	RL801S	3501-001053	RELAY-POWER;5Vdc,530mW,10A,1FormA,15mS,5	
...3	T401	AA26-50001S	TRANS-HORIZ.DRIVE;-,-,-,6.0mH,-,-,44uH,-	
⚠ ...3	T444S	AA26-00170A	TRANS FBT;FUJ-29H002F,29F,1.95MH,FERRIT	
⚠ ...3	T801S	AA26-00010A	TRANS SWITCHING;EER5345,HERCULES,90~264V	
⚠ ...3	TU01S	AA40-00083A	TUNER;TCLS3101PD16A(S),PAL B/G,D/K,I,M,1	
⚠ ...3	TU02S	AA40-00084A	TUNER;TCPS3000PC16B(S),PAL ,181CH,38.9MH	
...3	X601	2801-004020	CRYSTAL-UNIT;18.432MHz,30ppm,28-AAM,12pF	
...3		AA39-20536G	LEAD CONNECTOR-ASSY;,1P,F,60MM,1617#22	
...3		AA97-13373H	ASSY AUTO-MAIN;CS29Z7HRGX/XHK,K55A,HONG	S.N.A
....4	C101	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C102	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C104	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
....4	C105	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C106	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C107	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C108	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	C109	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C110	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C111	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C112	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C113	2202-000216	C-CERAMIC,MLC-AXIAL;0.027NF,5%,50V,SL,TP	
....4	C116	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C201	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C202	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	C206	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C207	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C239	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C240	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C302	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
....4	C303	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
....4	C304	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
....4	C305	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
....4	C306	2301-000160	C-FILM,PEF;12nF,5%,50V,TP,11.0x6.0x9.0mm	
....4	C307	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
....4	C308	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
....4	C401	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C402	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
....4	C403	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C404	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
....4	C408	2301-001143	C-FILM,PPF;56nF,5%,400V,TP,20x10x17,7.5	
....4	C409	2301-001385	C-FILM,PPF;30nF,5%,630V,TP,20x15.5x10.5,	
....4	C411	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
....4	C412	2301-000254	C-FILM,PEF;39nF,5%,50V,TP,7.5x3.5x6.5mm,	
....4	C413	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
....4	C414	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
....4	C415	2301-000203	C-FILM,PEF;2.7nF,5%,100V,TP,7x3.0x6.5mm,	
....4	C416	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
....4	C417	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C418	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
....4	C420	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
....4	C421	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C422	2401-001527	C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
....4	C424	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
....4	C425	2301-001259	C-FILM,MPPF;100nF,5%,400V,TP,19x8x16,7.5	
....4	C432	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C601	2201-000558	C-CERAMIC,DISC;0.47NF,10%,50V,Y5P,TP,5X3	
....4	C602	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
....4	C603	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C604	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	C605	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C606	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C607	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C608	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C610	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C611	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C612	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	C613	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
....4	C614	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C615	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C619	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C620	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C621	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C622	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C623	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C624	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C625	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C626	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C627	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C628	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C629	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C630	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C631	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C632	2201-000370	C-CERAMIC,DISC;0.22NF,10%,50V,Y5P,TP,4X3	
....4	C633	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C634	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	C635	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C636	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C637	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C638	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C639	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C640	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C641	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C642	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C643	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C644	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
....4	C645	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C646	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C647	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
....4	C648	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
....4	C649	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm	
....4	C650	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
....4	C651	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C652	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C653	2401-002216	C-AL;2200uF,20%,35V,GP,TP,16x25,7.5	
....4	C654	2201-000611	C-CERAMIC,DISC;0.056NF,5%,50V,C0G,TP,7X3	
....4	C655	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C656	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
....4	C657	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
....4	C658	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C659	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C660	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	C701	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
....4	C801	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
....4	C802	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
....4	C804	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
....4	C805	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
....4	C807	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.	
....4	C808	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
....4	C809	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	C810	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	C811	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	C812	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C814	2201-002028	C-CERAMIC,DISC;0.47NF,10%,2KV,Y5P,TP,7.5	
....4	C816	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
....4	C817	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C818	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4	C819	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C821	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	C822	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C823	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	C824	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
....4	C825	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C826	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
....4	C827	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4	C828	2201-000374	C-CERAMIC,DISC;0.22NF,5%,50V,C0G,TP,10.5	
....4	C830	2201-000984	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
....4	C831	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C832	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
....4	C833	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4	C834	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
....4	C835	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4	C836	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C837	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C838	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
....4	C840	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
....4	C841	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
....4	C843	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C844	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C901	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C902	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C903	2202-000719	C-CERAMIC,MLC-AXIAL;6.8nF,20%,16V,Y5R,TP	
....4	C904	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C905	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C906	2202-000791	C-CERAMIC,MLC-AXIAL;150pF,10%,50V,Y5P,TP	
....4	C907	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
....4	C909	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
....4	C910	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
....4	C911	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
....4	C912	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C913	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C914	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C915	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C916	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C917	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C918	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
....4	C919	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C920	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C921	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	C922	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C923	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C924	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C925	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C927	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	CN601	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
....4	CN602	3711-002645	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH	
....4	CN901	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
....4	CW901	2503-000156	C-NETWORK;100pFx4,20%,50V	
....4	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D202	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D207	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4	D401	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 4	D402	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4	D403	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D404	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4	D405	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D406	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D408	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4	D409	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
⚠ 4	D410	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D411	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
....4	D603	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D607	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4	D804	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4	D805	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D808	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D812	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D816	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D901	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D902	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D903	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D904	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D907	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4	DZ302	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ303	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ304	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
....4	DZ305	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ306	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ307	0403-001118	DIODE-ZENER;MTZ30A,32V,26.99-28.39V,500m	
....4	DZ401	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
....4	DZ402	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DZ404	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ601	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ602	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ603	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ604	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ605	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ606	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ607	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	DZ608	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	DZ801	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ802	0403-000716	DIODE-ZENER;MTZJ4.7B,4.7V,4.55-4.8V,500m	
....4	DZ803	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
....4	DZ804	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
....4	DZ807	0403-001330	DIODE-ZENER;MTZJ30A,26.99-28.39V,500mW,D	
....4	DZ808	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ902	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ906	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ907	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ908	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ909	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ910	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ911	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ912	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	EL201	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL202	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL203	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL204	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL401	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL402	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	EL407	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL408	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL805	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL806	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL807	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL808	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY302	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY303	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY403	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY404	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY405	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY406	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY407	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY408	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY409	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY410	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY411	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY412	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY413	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY414	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY415	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY417	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY418	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY419	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY420	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY421	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY422	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY423	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY424	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY425	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY426	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY429	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY430	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY431	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY432	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY433	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY434	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY435	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY436	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY437	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY439	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY441	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY446	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY447	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY603	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY604	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY701	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY702	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY703	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY704	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY705	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY706	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY801	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY802	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY803	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY804	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY805	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY806	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY809	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY810	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY811	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY812	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY813	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY814	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY815	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY816	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY817	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY820	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY824	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY825	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY828	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY829	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY830	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY831	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY832	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	EY833	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY835	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY836	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY837	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY838	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY839	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY840	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY841	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY842	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY844	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY845	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY846	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY848	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY850	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY851	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY853	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY854	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY855	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY856	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY857	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY858	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY859	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY860	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY861	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY862	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY864	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY865	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY871	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY872	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
⚠ 4	FA801S	3601-000120	FUSE-AXIAL LEAD;125V,2.5A,FAST-ACTING,GL	
⚠ 4	FA802S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
⚠ 4	FA803S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
....4	GT102	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT301	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT302	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT401	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT402	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT404	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT405	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT406	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT409	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT410	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT411	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT412	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	HIC401	AA13-00094A	IC HYBRID;-,DDRI001A,SIP,5P,-,TP	
....4	IC202	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
⚠ 4	IC402	1203-000243	IC-POSI.FIXED REG.;7812A,TO-220,3P,-,PLA	
....4	IC804	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
....4	IC903	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
....4	IC904	1203-001943	IC-VOL. DETECTOR;7025,TO-92,3P,-,PLASTIC	
....4	J709	2001-000527	R-CARBON;22OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	L101	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
....4	L103	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	L104	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
....4	L106	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	L201	2701-000200	INDUCTOR-AXIAL;5.6uH,10%,4.2x9.8mm	
....4	L203	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L402	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
⚠ 4	L403	2701-001040	INDUCTOR-AXIAL;10uH,10%,4.5x14mm	
....4	L404	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L407	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L409	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L410	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4	L601	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L602	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
....4	L603	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L604	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L605	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L606	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L607	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L608	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L609	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L610	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L612	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L613	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L614	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L615	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L703	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L704	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L705	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L706	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L801	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L802	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L803	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L804	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L805	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L806	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L807	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4	L809	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L811	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
....4	L901	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L902	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
....4	L903	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L904	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L906	2701-000215	INDUCTOR-AXIAL;8.2uH,10%,2.5x3.4mm	
....4	L907	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L908	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
....4	L909	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
....4	PCB	AA41-00707B	PCB-MAIN;CS29Z6HP,FR-1,1L,B,1.6T,330X245	S.N.A
....4	Q404	0505-000156	FET-SILICON;IRF620,N,200V,5A,0.8ohm,50W,	
....4	Q601	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q603	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q801	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q802	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
....4	Q803	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q901	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q906	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q907	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q908	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q909	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4	Q910	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4	Q912	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q913	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q914	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	R101	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R102	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R103	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R104	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R105	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R106	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R107	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R108	2001-000969	R-CARBON;750HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R203	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R204	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R301	2001-001163	R-CARBON(S);560OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R302	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R303	2001-000016	R-CARBON(S);10HM,5%,1/2W,AA,TP,2.4X6.4MM	
....4	R304	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm	
....4	R305	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
....4	R306	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
....4	R307	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm	
....4	R308	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R309	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R310	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R314	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R315	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R316	2001-001129	R-CARBON(S);330KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R317	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R401	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R402	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	R403	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
....4	R405	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
....4	R409	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
....4	R410	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
....4	R411	2001-000028	R-CARBON(S);1000HM,5%,1/2W,AA,TP,2.4X6.4	
....4	R412	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
....4	R413	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
....4	R414	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
....4	R415	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R416	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R418	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R419	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R420	2004-001987	R-METAL(S);4.3Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R421	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R422	2008-000251	R-FUSIBLE(S);0.27ohm,5%,2W,AF,TP,3.9x10m	
....4	R423	2001-001055	R-CARBON(S);1.8KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R424	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
....4	R425	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
....4	R426	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
....4	R428	2004-000698	R-METAL;3.3Kohm,1%,1/4W,AA,TP,2.4x6.4m	
....4	R430	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
....4	R431	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
....4	R432	2001-001164	R-CARBON(S);56KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R433	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
....4	R434	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
....4	R435	2003-001042	R-METAL OXIDE(S);5.6Kohm,5%,2W,AF,TP,3.9	
....4	R440	2004-001893	R-METAL(S);22Kohm,1%,1/2W,AA,TP,2.5x6.5m	
....4	R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R602	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R603	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R604	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R605	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R606	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R607	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R608	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R609	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R612	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R613	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R614	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R615	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R616	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R617	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R618	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R623	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R624	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R626	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R627	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R628	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R629	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R630	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R631	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R632	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R633	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R634	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R635	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R636	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R637	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R638	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R639	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R704	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R710	2001-000376	R-CARBON;15OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R715	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R716	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R717	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R718	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R723	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R801	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R802	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4	R803	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4	R804	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4	R805	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R806	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R808	2001-001197	R-CARBON(S);910OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R809	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R810	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R811	2001-001188	R-CARBON(S);8.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R812	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R813	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R815	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
....4	R816	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R817	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R818	2001-001131	R-CARBON(S);33KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R819	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R820	2001-001096	R-CARBON(S);2.2OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R821	2004-001891	R-METAL(S);133Kohm,1%,1/2W,AA,TP,2.5x6.5	
....4	R822	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R823	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R824	2001-000305	R-CARBON;110KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R827	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
....4	R828	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm	
....4	R829	2008-001148	R-FUSIBLE;3.3OHM,5%,1W,AG,TP,3.9X12MM	
....4	R830	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
....4	R833	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R835	2003-002181	R-METAL OXIDE(S);68Kohm,5%,2W,AG,TP,3.9x	
....4	R838	2001-001050	R-CARBON(S);1.5KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R840	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R841	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R842	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R901	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R902	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R903	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R904	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R905	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R906	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R907	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R908	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R909	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R910	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R911	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R912	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R913	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R914	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R915	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R916	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R917	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R919	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R920	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R921	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R922	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R923	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R924	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R925	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R926	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R927	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R928	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R935	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R936	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R937	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R938	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R940	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R941	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R942	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R945	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R946	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R947	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R948	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R951	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R952	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R953	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R954	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R955	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R958	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R960	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R961	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R962	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R963	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R965	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R966	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R967	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R968	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R972	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R973	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	R974	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R981	2001-000515	R-CARBON;2200HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R982	2001-000515	R-CARBON;2200HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R983	2001-000515	R-CARBON;2200HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R984	2001-000515	R-CARBON;2200HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R988	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RR430S	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
....4	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
....4	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
....4	VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
....4	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
....4	X901	2801-003728	CRYSTAL-UNIT;6MHz,30ppm,28-AAM,20pF,40oh	
...3		AA61-00707B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
...3		AA95-03092A	ASSY SUB-PCB,FEATURE BOX:,K55A,ASIA	
....4	BR01	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4	BR02	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4	CN01	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4	CN02	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4	CN03	3711-003601	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,ANGLE,	
....4	DC41	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
....4	DC51	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	DX01	2802-001177	RESONATOR-CERAMIC;2.696MHZ,0.4%,BK,10X4.	
....4	EC48	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	EC49	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	EX01	2801-004019	CRYSTAL-UNIT;20.25MHz,30ppm,28-AAM,13pF,	
....4	IC06	1203-002000	IC-VOL. DETECTOR;7027,TO-92,3P,-,PLASTIC	
....4	SX01	2802-001179	RESONATOR-CERAMIC;4MHZ,0.5%,BK,8X3X5.5MM	
....4		AA97-13003A	ASSY AUTO-FEATURE BOX;K55A	S.N.A
.....5		AA97-12982A	ASSY SMD-FEATURE BOX:,K55A,PAL	S.N.A
.....6	DC01	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....6	DC02	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....6	DC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC04	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC05	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC06	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....6	DC07	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....6	DC08	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	DC09	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,	
.....6	DC10	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC12	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC13	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC14	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC17	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC19	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC20	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	DC21	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC22	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	DC23	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....6	DC24	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC25	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC26	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC27	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC28	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC29	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC30	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC31	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	DC32	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	DC33	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	DC34	2203-000896	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
.....6	DC35	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	DC36	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	DC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC39	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	DC40	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....6	DC43	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC45	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	DC49	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	DC52	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	DD01	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD02	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD03	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....6	DD04	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....6	DD05	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....6	DD06	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....6	DD07	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....6	DD08	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD09	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD10	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD11	0403-000746	DIODE-ZENER;RLZ3.9B,3.9V,3.89-4.16V,400m	
.....6	DD13	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD14	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD15	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD16	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD17	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD18	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD19	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD20	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
.....6	DL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	DL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	DL03	2703-001070	INDUCTOR-SMD;100uH,10%,4.5x3.2x3.2mm	
.....6	DQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	DQ02	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	DQ03	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	DQ04	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	DQ05	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	DQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	DQ07	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	DQ08	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	DQ09	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
.....6	DQ10	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	DQ11	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	DR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR05	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR06	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	DR08	2007-000691	R-CHIP;3.3Mohm,5%,1/16W,DA,TP,1608	
.....6	DR09	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR10	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR13	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....6	DR14	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....6	DR15	2007-000869	R-CHIP;4.7Kohm,1%,1/16W,DA,TP,1608	
.....6	DR16	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR17	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR18	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR19	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR23	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP,1608	
.....6	DR24	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
.....6	DR25	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6	DR26	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR27	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....6	DR28	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....6	DR29	2007-000118	R-CHIP;390ohm,5%,1/16W,DA,TP,1608	
.....6	DR30	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR31	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....6	DR32	2007-000081	R-CHIP;2.7Kohm,5%,1/16W,DA,TP,1608	
.....6	DR33	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....6	DR34	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....6	DR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR36	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR37	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....6	DR38	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....6	DR39	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....6	DR40	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....6	DR41	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....6	DR42	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR43	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR44	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR45	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR46	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR47	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....6	DR49	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR50	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR51	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR52	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR53	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR54	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR55	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR56	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR57	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR58	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR59	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR60	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR61	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6	DR62	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6	DR63	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....6	DR64	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6	DR65	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR66	2007-000088	R-CHIP;7.5Kohm,5%,1/16W,DA,TP,1608	
.....6	DR68	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	DR69	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	DR70	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	DR80	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6	DR81	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
.....6	DR82	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
.....6	DR86	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....6	DR87	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....6	DR88	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	EC01	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC02	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC04	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	EC08	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	EC09	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	EC10	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	EC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC12	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC13	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	EC14	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	EC15	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	EC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC17	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC18	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC19	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC20	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC21	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC22	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC23	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC24	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	EC29	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EC30	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EC31	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EC32	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC33	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC34	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
.....6	EC35	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
.....6	EC36	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC39	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC40	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC41	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC42	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	EC43	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC44	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	EC45	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC46	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC47	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	EC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	EC51	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	EC52	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC53	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC54	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC55	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC56	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC57	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	EC58	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	EC59	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	EC60	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC62	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EC63	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EC64	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EC65	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EL04	3301-001082	CORE-FERRITE BEAD;AB,600HM,3.2X2.5X1.3MM	
.....6	EL05	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	EL06	3301-001324	CORE-FERRITE BEAD;AB,150HM,2X1.25X0.9MM,	
.....6	EL07	3301-001324	CORE-FERRITE BEAD;AB,150HM,2X1.25X0.9MM,	
.....6	EL08	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	EL09	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	EL13	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	EQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	EQ02	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	EQ03	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	EQ04	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....6	EQ05	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....6	EQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	ER01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER02	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	ER06	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....6	ER07	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....6	ER09	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6	ER11	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	ER12	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6	ER13	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER14	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	ER15	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6	ER16	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER17	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	ER18	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6	ER19	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	ER21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	ER22	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER24	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER25	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER26	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER32	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....6	ER33	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....6	ER34	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....6	ER35	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....6	ER36	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....6	IC01	1204-001938	IC-DECODER;VSP9407B-B11,MQFP,80P,14X14MM	
.....6	IC02	1204-001814	IC-SELECTOR;CXA2151Q,QFP,48P,144MIL,PLAS	
.....6	IC03	1001-001082	IC-VIDEO SWITCH;BA7657F,-,SOP,24P,300MIL	
.....6	IC04	1204-001989	IC-VIDEO PROCESS;CXA2165Q,QFP,64P,20X14M	
.....6	IC05	1203-002186	IC-POSI.FIXED REG.;18,DPAK,3P,240MIL,PLA	
.....6	IC10	1001-001177	IC-VIDEO SWITCH;TEA6425D,VIDEO SWITCH ,S	
.....6	IC11	0801-000662	IC-CMOS LOGIC;74HC123,MULTIVIBATOR,SOP,1	
.....6	PCB	AA41-00644B	PCB-PAL FERTURE BOX;CS29Z6,FR-4,4L,B,1.6	S.N.A
.....6	SC01	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC02	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC03	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC04	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC05	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC06	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC12	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC13	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC14	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	SC16	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC17	2203-005809	C-CERAMIC,CHIP;1000nF,10%,16V,X7R,TP,201	
.....6	SC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	SC19	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC20	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	SC21	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC22	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	SC23	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC24	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC25	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC26	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC27	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....6	SC28	2203-001656	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,1608	
.....6	SC29	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC30	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC31	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC32	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC33	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC34	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC35	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC36	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC37	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC38	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC39	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC40	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC41	2203-000998	C-CERAMIC,CHIP;0.047NF,5%,50V,C0G,TP,160	
.....6	SC42	2203-000998	C-CERAMIC,CHIP;0.047NF,5%,50V,C0G,TP,160	
.....6	SC43	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	SC45	2203-000998	C-CERAMIC,CHIP;0.047NF,5%,50V,C0G,TP,160	
.....6	SC46	2203-000998	C-CERAMIC,CHIP;0.047NF,5%,50V,C0G,TP,160	
.....6	SC47	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....6	SC48	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....6	SC49	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	SL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	SL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	SQ01	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	SR01	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR04	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	SR05	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	SR06	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	SR07	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR08	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR09	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	SR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	SR11	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	SR12	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR13	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR14	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR25	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	SR26	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP,1608	
.....6	SR27	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....6	SR28	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6	SR29	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR36	2007-000259	R-CHIP;1.6Kohm,5%,1/16W,DA,TP,1608	
.....6	SR37	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6	TC01	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	TC02	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	TC03	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	TC04	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	TC05	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	TC06	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	TC07	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	TC08	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	TD01	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....6	TL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	TQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	TQ02	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	TR01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	TR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	TR03	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	TR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	TR05	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	TR07	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	TR08	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	TR09	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	TR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	TR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	

ASSY CPT

1	*	AA91-05635A	ASSY CPT;CS29Z7HRGX/XTT,CHINA,+380MG,SDI	S.N.A
..2		AA27-00128A	COIL DEGAUSSING;-,-,-,-,50T,7,-,29inch,2	
..2		AA91-02173S	ASSY CPT;A68QCP891X004(C),29,+380MG,ITC	S.N.A
⚠ ...3		AA03-00076A	CRT COLOR;A68QCP891X004(C),+380mG,0.315m	
..2		AA98-70011D	ASSY TBC WIRE(P);-,29',NTSC,PAL,2P-WH,-	S.N.A

ASSY COVER REAR

1	*	AA90-03192C	ASSY COVER REAR;CS29Z7HF9X/BWT	S.N.A
..2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A
..2		AA64-02651D	CABINET BACK;29Z7,ABS,VO,G4309,SVM2012	S.N.A
..2		AA63-00563A	COVER-BACK,R;29Z7,ABS,HB,G4309,DGM2188	S.N.A
..2		AA63-00562A	COVER-BACK,L;29Z7,ABS,HB,G4309,DGM2188	S.N.A
..2		AA60-00091J	SPACER-FELT;-,FELT,330X10,-,-,BLK,T0.5,-	S.N.A

ASSY COVER FRONT

1	*	AA90-03189N	ASSY COVER FRONT;CS29Z7HRGX/XHK	S.N.A
..2	BRK+CF	6002-000522	SCREW-TAPPING;TH,+,2,M4,L15,ZPC(BLK),SWR	S.N.A
..2	CA+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	CB+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CB+TBA	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CC+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	CRT+CF	AA60-10050V	SCREW-ASSY;-,SWRCH18A,M6,L30,HH,+,WC,-,Z	S.N.A
..2	CV+CB	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CV+CB+	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	D-COIL	AA65-30017A	CLAMPER CORE-D,COIL;-,NYLON-66,V0,-,NTR,	S.N.A
..2	PP+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	TBA+RJ	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	WOO+CB	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2		AA73-00017A	RUBBER-CAP;29Z7,SILICONE RUBBER,WHT	S.N.A
..2		AA91-03960A	ASSY HOLDER SPK;-,-,8OHM/25W,-,WOOFER SP	
..2		AA96-00905F	ASSY COVER P-CABINET FRONT;29Z7,CS29Z7HR	
...3	GS+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
...3	KNOPOW	AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A
...3	LED+GS	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
...3	SPK+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
...3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA64-02666A	INDICATOR LED;Z7,ACRYL,CLR	
...3		AA91-03959A	ASSY HOLDER SPK;-,-,8OHM/10W,-,FRONT SPE	
...3		AA60-00091C	SPACER-FELT;-,FELT,230X10,-,-,BLK,T1.0,-	S.N.A
...3		AA64-02665A	WINDOW-RMC;Z7,PC,VIOLET	
...3		AA64-01062B	BADGE-BRAND;32Z5,AL FORGING,-,-,L65,-,SI	S.N.A
...3		AA64-02650G	CABINET-FRONT;CS29Z7HRG,ABS,HB0690M,G430	
...3		AA64-02656D	GRILLE-SPEAKER;29Z7,ABS,HB,G4309,DGM2188	S.N.A
...3		AA64-02663B	KNOB-POWER;Z7,PC,VIOLET,MASTER	
...3		AA64-02664A	DECORATION-POWER;Z7,ABS,HB,NTR	
..2		AA73-00005B	RUBBER-CAP;FLAT,PRJ,SILICONE RUBBER,WHIT	
..2		AA65-00019A	CLAMPER CORE-D,COIL;25-34,NYLON 66,V2,N	S.N.A
..2		AA63-60004Y	SPACER-GUM,CRT;ALL MODEL,NTR RUBBER,-,-,	S.N.A
..2		AA61-10054A	BRACKET-CRATER;6277,STS304,T0.5,-,-,-,-	S.N.A

ASSY ACCESSORY

1	*	AA92-07347A	ASSY ACCESSORY;CS34Z7HRGX/XHK,HONG KONG,	S.N.A
..2		AA59-00266A	REMOCON;TM63,SAMSUNG,51PX,45,SAMSUNG,2.4	
..2		AA68-02452A	MANUAL USERS;CS29Z7HR,ENG,PIP,TTX	
..2		AA69-00862A	BAG PE;-,HDPE PE FOAM,T0.03,W400,H240,-,	S.N.A

ASSY P/MATERIAL

1	*	AA92-05176A	ASSY P/MATERIAL;CT-29Z7HR	S.N.A
..2		AA69-00306A	BAG AIR;LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A
..2		AA69-00744F	BAG-SHEET;-,HDPE PE FOAM,T0.015,W1400,H1	S.N.A
..2		AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,	S.N.A
..2		AA63-10007C	BAND-PP;W18,CLEA,1G	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
..2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A

ASSY BOX

Level	Loc. No.	Code No.	Description ; Specification	Remark
1	*	AA92-05171M	ASSY BOX;CS29Z7HRGX/XHK	S.N.A

7-3 CS34Z7HRGX/XHK

ASSY CHASSIS

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA91-05825D	ASSY CHASSIS;CS34Z7HRGX/XHK,HONG KONG,K5	S.N.A
..2	C-BLOC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2	D-FOCU	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2	MP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2	PCB	AA61-00706B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
..2	TBA+HC	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2	WP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2		AA94-12244B	ASSY PCB MISC-CONTROL;34Z7,K55A,PAL,HONG	
...3	CNY01	AA39-00100E	LEAD CONNECTOR-ASSY;,4P,600MM,YBNH250-04	
...3	CPC+CC	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
...3	SWY01	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY02	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY03	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY04	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY05	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY06	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3		AA96-00920F	ASSY COVER P-COVER CONTROL;34Z7,CT-34Z7P	S.N.A
....4	KC+CC	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
....4		AA63-00559G	COVER-CONTROL;34Z7,HIPS,HB,G4309,DGN-118	S.N.A
....4		AA64-02662A	KNOB-CONTROL;Z7,ABS,HB,G3676,S104M+W971	
...3		AA97-12449A	ASSY AUTO-CONTROL;29Z6,K55A,PAL	S.N.A
....4	DZY03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZY04	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	LY01	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	PCB	AA41-00651A	PCB-CONTROL;CS29Z7HF,FR-1,1L,A,1.6T,330X	S.N.A
....4	RY02	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY03	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY04	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY05	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY06	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA94-12243B	ASSY PCB MISC-A/V SIDE;34Z7,K55A,PAL,HON	
...3	AV+CV	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
...3	CN701	AA39-00317B	LEAD CONNECTOR-ASSY;K55A/WT-32Z4HD,UL100	
...3	CN703	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,500,YBNH025-05,6	
...3	CN704	AA39-00070B	LEAD CONNECTOR-ASSY;,4P,500MM,YBNH250-04	
...3	JA701	3722-001164	JACK-PIN;3P,3.4mm,SN,WH:YE:RE,#16-22	
...3	JK04	3722-000544	JACK-VHS;4P,11.5mm,AG,BLK,N	
...3	JKH701	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	
...3		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
...3		AA96-00918F	ASSY COVER P-COVER A/V;34Z7,CS29Z7HRG,HI	
....4		AA63-00560A	COVER-A/V;34Z7,HIPS,HB,G4309,DGN-1189	S.N.A
....4		AA64-02667B	INLAY-AV;Z7,PS SHEET,T0.3,DGN-K189,K55A	S.N.A
...3		AA97-12697A	ASSY AUTO-A/V SIDE;,K55A,PAL,29Z6	S.N.A
....4	C701	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C702	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C707	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C708	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	DZ701	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500m	
....4	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L705	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L706	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L707	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L708	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	PCB	AA41-00620B	PCB-A/V SIDE(Z7);CT-29Z7HR,FR-1,1L,B,1.6	S.N.A
....4	R701	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R702	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
..2		AA94-12169A	ASSY PCB MISC-LED;34Z7,K55A,PAL	
...3	CN01	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,500,YBNH025-05,6	
...3	LD01	0601-001381	LED;ROUND,RED/GRN,5.0MM,650/563NM	
...3	RM01	AA32-00012A	MODULE REMOCON;ORC-50HF2,38KHZ,940NM,MES	
...3		AA97-13408A	ASSY AUTO-LED;,PAL	S.N.A
....4	CY01	2401-002291	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	
....4	DC01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DC02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	RY01	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4		AA41-00653A	PCB-LED;CS29Z7HF,FR-1,1L,A,1.6T,245X245,	S.N.A
⚠ ..2		AA96-20126D	ASSY POWER CORD;-,EP3/YES,N(H/C500MM),MP	S.N.A
...3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A
...3		AA39-10007X	CBF POWER CORD;-,EP3/YES(HK),H03VVH2-F,2	
..2		AA65-00011B	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
..2		AA96-00908N	ASSY COVER P-TERMINAL BOARD;29Z7,HIPS VO	
...3	PCB	AA41-00641A	PCB-WOOFER JACK;CT-29Z7HR,FR-1,1L,A,1.6T	S.N.A
...3	WB01	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
...3	WB02	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
...3	WCN01	AA39-20005D	LEAD CONNECTOR-ASSY;,3P,200MM,YBNH250-03	
...3	WJ01	3722-001813	JACK-PIN;1P(3P),8.3MM,AU,BLK,-	
...3	WP+TBA	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
...3		AA64-02822H	INLAY-T/BOARD;Z7,PS SHEET,T0.5,K55A WOOF	S.N.A
...3		AA65-00025A	TERMINAL-BOARD,ANT;,HIPS V0,BLK	S.N.A
..2		AA94-12053A	ASSY PCB MISC-CRT;34Z6,K55A	
...3	C522	2201-002117	C-CERAMIC,DISC;4.7nF,20%,3kV,Y5U,TP,16x6	
...3	CNC01	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	CNC01A	AA39-00088A	LEAD CONNECTOR-ASSY;HERCULES,UL1007/1185	
...3	CNC02	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3	CNC02A	AA39-00127A	LEAD CONNECTOR-ASSY;,8P,400MM,35155-0800	
...3	GT501A	AA39-00341A	LEAD CONNECTOR;K55A(WT-32Z4HD),UL1015#18	
⚠ ...3	GT503S	AA39-20010B	LEAD CONNECTOR-ASSY;,1P,500,YFH800-01,S,	
...3	IC501	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
....4		1201-001131	IC-VIDEO AMP;6111,SIP9P-,SINGLE,-,PLAS	
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3	IC502	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC503	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC504	BH99-00038E	ASSY HEAT/SINK;TDA2030,AMP,HERCULES,BH62	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	1201-000010	IC-OP AMP;2030,PENTAWATT,5P,-,SINGLE,-,C	
....4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
....4	CIS	BH62-00041A	HEAT SINK-TR;PN17LT,A1050S,T1.0,50,23,-,	S.N.A
...3	QF09	AA96-00243M	ASSY H/S;-,AMP,AA62-000450A,2SA1011,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000131	TR-POWER;2SA1011-D,PNP,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	QF10	AA96-00243L	ASSY H/S;-,CRT,AA62-000450A,2SC2344,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000153	TR-POWER;2SC2344-D,NPN,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	SC01	3722-001503	JACK-PIN;1P,1PI,NI,RED,SCR-JACK	
⚠ ...3	V999S	3704-000114	SOCKET-CRT;14P,29.1,35.5,SN,ISH09S/BK	
...3		2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
...3		AA97-13361A	ASSY AUTO-CRT;34Z6,K55A,RUSSIA	S.N.A
....4	C501	2201-000247	C-CERAMIC,DISC;0.015NF,5%,50V,C0G,TP,5X3	
....4	C502	2201-002031	C-CERAMIC,DISC;0.005NF,0.5PF,50V,C0G,TP,	
....4	C503	2201-000662	C-CERAMIC,DISC;0.007NF,0.25PF,50V,C0G,TP	
....4	C504	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C505	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C506	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C507	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C508	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C509	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C511	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C512	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C513	2201-000600	C-CERAMIC,DISC;0.56NF,10%,50V,Y5P,TP,5X3	
....4	C514	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C515	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C520	2401-000703	C-AL;2200uF,20%,25V,GP,-,12.5x25mm,	
....4	C526	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C528	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C531	2401-002264	C-AL;10uF,20%,350V,GP,TP,10x20mm,5m	
....4	C532	2401-001563	C-AL;47uF,20%,400V,GP,TP,16x25,7.5	
....4	C533	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C534	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C535	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	C536	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C537	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C538	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C539	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CF01	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	CF02	2201-000017	C-CERAMIC,DISC;1NF,10%,50V,Y5P,TP,5X3.5M	
....4	CF03	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF04	2201-000516	C-CERAMIC,DISC;4.7NF,+100-0%,500V,Y5U,TP	
....4	CF05	2301-000261	C-FILM,PEF;4.7nF,5%,100V,TP,10.5x12.5x6.	
....4	CF06	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF07	2201-000604	C-CERAMIC,DISC;0.056NF,+100-0%,500V,SL,T	
....4	CF71	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	CF73	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
....4	CF74	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	CF75	2401-000045	C-AL;10uF,20%,160V,GP,TP,10x16,5	
....4	D501	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D502	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D509	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D510	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D511	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D512	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D513	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D514	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DF01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF05	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF06	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF07	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DF08	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DZ501	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ502	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ504	0403-000698	DIODE-ZENER;TZP12A,12V,11.4-12.6V,1W,DO-	
....4	DZ510	0403-000734	DIODE-ZENER;TZP15B,15V,14.7-16.5V,1W,DO-	
....4	DZF01	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
....4	DZF02	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
....4	DZF03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	EL100	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL80	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL81	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL82	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL83	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL84	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL85	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL86	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL87	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL88	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL89	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL92	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL94	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL95	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL96	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL97	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL98	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL99	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	FN1	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
....4	FV1	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
....4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT503	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT504	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	L502	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
....4	LF01	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF02	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF03	2701-000112	INDUCTOR-AXIAL;100uH,10%,3x7mm	
....4	LF04	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF06	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF08	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF09	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF11	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	PCB	AA41-00578D	PCB-CRT;CT-29Z7HR,FR-1,1L,D,1.6T,330X245	S.N.A
....4	Q501	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q502	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q503	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q504	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	QF02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	QF03	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	QF04	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	QF05	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	R501	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R502	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R504	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R505	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R506	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R507	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R508	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R509	2008-000205	R-FUSIBLE(S);10ohm,5%,1/2W,AF,TP,2.5x6.5	
....4	R510	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R511	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R512	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R513	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R514	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R515	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R518	2001-001095	R-CARBON(S);2.2MOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R519	2001-000356	R-CARBON;150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R520	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R522	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R523	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R524	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
....4	R525	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7	
....4	R527	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R528	2003-000458	R-METAL OXIDE(S);100ohm,5%,2W,AF,TP,4x12	
....4	R529	2008-000264	R-FUSIBLE(S);1ohm,5%,1W,AF,TP,3.9x10mm	
....4	R530	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R531	2001-000539	R-CARBON;24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R540	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R541	2008-001053	R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
....4	R554	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R555	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R556	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R560	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R561	2001-001126	R-CARBON(S);300OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R562	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R563	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R564	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R565	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R566	2001-001040	R-CARBON(S);0.68OHM,5%,1/2W,AA,TP,2.4X6.	
....4	RF13	2008-001014	R-FUSIBLE(S);22ohm,5%,1W,AF,TP,3.2x10mm	
....4	RF14	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF15	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF16	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF17	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF18	2001-001079	R-CARBON(S);150HM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF19	2001-001079	R-CARBON(S);150HM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF20	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF21	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF22	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF23	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF24	2003-001018	R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
....4	RF25	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF26	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF27	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF28	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF29	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF30	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF31	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF32	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	RF33	2001-001053	R-CARBON(S);1.5OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF34	2001-001100	R-CARBON(S);2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF35	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	RF36	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
..2		AA61-01190A	HOLDER-CHASSIS;Z7,HIPS V0,G4309	S.N.A
..2		AA94-07792A	ASSY PCB MISC-DYNAMIC FOCUS;CT-29Z7HR,K5	
...3	LH01	AA26-90002C	TRANS-DUMMY;-,-,-,-,-,-,-,-,-,-,-,EER2	
...3	LH02	AA27-40003L	COIL HORIZ. WIDTH;-,1.0mH,DR14x20,2UEW0.	
...3	RH28	2008-001113	R-FUSIBLE(S);0.22ohm,10%,2W,AG,TP,3.9x12	
...3	WIRE3	AA39-20061C	LEAD CONNECTOR-ASSY;,3P,200,YFH800-03,S,	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-07229L	ASSY AUTO-DYNAMIC FOCUS;CT-29Z7HR,K55A	S.N.A
....4	EY01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY03	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY04	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY05	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY06	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY07	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY08	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY09	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	GTH01	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTH02	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	GTH03	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	PCB	AA41-00152C	PCB-DOUBLE FOCUS;CW29A6VN8X/XEF,FR-1,1L,	S.N.A
..2		AA94-07798A	ASSY PCB MISC-WOOFER;CT-29Z7HR,K55A,KORE	
...3	CNW01	AA39-20055A	LEAD CONNECTOR-ASSY;,6P,200,YBNH025-06,6	
...3	ICW01	AA96-50367D	ASSY H/S;-,POWER,AA62-30181D,TDA7269,ZES	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1201-001385	IC-POWER AMP;7269A,ZIP,11,19.6,DUAL,13,P	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30181D	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,70MM,-	S.N.A
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-07229F	ASSY AUTO-WOOFER;CT-29Z7HR,K55A	S.N.A
....4	CNW02	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
....4	CW01	2401-002216	C-AL;2200uF,20%,35V,GP,TP,16x25,7.5	
....4	CW02	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	CW04	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	CW05	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	CW06	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
....4	CW07	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	CW09	2301-000289	C-FILM,PEF;5.6nF,5%,50V,TP,7x6x3,5	
....4	CW10	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	CW12	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	EYW01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EYW02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	PCB	AA41-00588A	PCB-WOOFER;CT-29M8HR,FR-1,1L,A,1.6T,330X	S.N.A
....4	RW01	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RW02	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RW05	2001-001050	R-CARBON(S);1.5KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	RW06	2001-000085	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	RW07	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RW08	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RW09	2001-000085	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	RW10	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RW11	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
..2		AA94-11730A	ASSY PCB MISC-MASTER;Z6,Z7Z9,K55A,S57A,P	
...3	GTAY01	AA39-20179C	LEAD CONNECTOR-ASSY;,3(2)P,600MM,YFH800-	
...3	HP+PCB	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
...3	MPP+LP	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
⚠ ...3	SW811S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
...3		AA97-05539A	ASSY AUTO-MASTER;WS36Z48D,KS4A,PAL	S.N.A
....4	EY01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY03	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY04	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	GTY05	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY06	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY07	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY08	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY09	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY10	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	PCB	AA41-00521A	PCB-MASTER S/W;CS32Z4,FR-1,1L,A,1.6T,245	S.N.A
...3		AA61-00719B	HOLDER-MASTER;T6,W3,HIPS V0,BLK,J52A	S.N.A
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA94-11990F	ASSY PCB MAIN;CS34Z7HRGX/XHK,K55A,HONG K	
...3	C-BLOC	AA26-00069A	TRANS FBT;FUJ-29C002C(S),DREAM3,4,-,-,-,	
...3	C423	2301-001257	C-FILM,MPPF;640nF,5%,400V,TP,26x14.5x24,	
...3	C426	2306-000205	C-FILM,MPPF;430nF,5%,400V,BK,26x21.5x14.	
...3	C803	2401-001426	C-AL;470uF,20%,400V,GP,-,35x45mm,10	
...3	C806	2306-000112	C-FILM,MPPF;100nF,20%,250V,BK,-,15mm	
...3	C815	2401-003024	C-AL;220uF,20%,200V,WT,TP,22x35,10	
...3	C820	2401-003419	C-AL;2200uF,20%,50V,WT,TP,16X35.5mm	
...3	CABLE	AA39-30007B	CBF IF;-,T,150mm,1365#26	
...3	CN502	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3	CN702	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	CN702A	AA39-00114C	LEAD CONNECTOR-ASSY;,12P,500MM,35155-120	
...3	CN902	3711-003043	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
⚠ ...3	CR405S	2301-001583	C-FILM,PPF;3NF,5%,2KV,TP,25X13X7MM,20	
⚠ ...3	CR406S	2301-001583	C-FILM,PPF;3NF,5%,2KV,TP,25X13X7MM,20	
⚠ ...3	CR407S	2301-001398	C-FILM,MPPF;3.3nF,5%,2kV,TP,29x8.5x1.5mm	
⚠ ...3	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ ...3	CX802S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ ...3	CY802S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
⚠ ...3	D801S	AA96-00276C	ASSY H/S;-,BRIDGE ,AA62-00052A,GSIB660,K	S.N.A
....4		AA62-00052A	HEAT SINK-PS;-,-,-,SILVER,HOLE 18.5mm, 2	S.N.A
....4		AA60-30003A	WASHER;T1.5,SBHG-1	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		0402-001399	DIODE-BRIDGE;GSIB660,600V,6A,SIP-4,BK	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	FP801S	3601-000297	FUSE-CARTRIDGE;250V,5A,TIME-LAG,GLASS,5.	
...3	GT804S	AA39-20010C	LEAD CONNECTOR-ASSY;,1P,600,YFH800-01,S,	
...3	HC401	BP96-00159A	ASSY HEAT SINK P;H/S,SCREW,FJL6920,FMP-3	S.N.A
....4	CIS	AA60-30001A	WASHER-PLATE;M3,ID3.5,15X8.5,T1.0,SBHG	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	BP62-00015A	HEAT SINK-PS;WT-36Z4HR,A1050S,T2.0,86,80	S.N.A
....4	CIS	BH73-00028B	SILICON/RUBBER-HS;TV ALL,SILICON,26*30*T	S.N.A
....4	CIS	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	CIS	0502-001230	TR-POWER;FJL6920YDTU,N,200000MW,TO-264 F	
....4	CIS	0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	
...3	HC801	AA96-00475A	ASSY H/S;-,REGULATOR,AA62-00066B,FML-G12	S.N.A
....4		AA62-00066B	HEAT SINK;D2,D3,AL ,T1.0,89,70,-,AA62-00	S.N.A
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
....4		0402-001230	DIODE-RECTIFIER;FMG-G2CS,1000V,3A,TO-220	
....4		0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	IC301	AA96-50381A	ASSY H/S;-,-,AA62-30180B,LA7845,-	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1204-000517	IC-VERTICAL DEF.;LA7845,SIP,7P,-,PLASTIC	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30180B	HEAT SINK-ES;-,A6063 EXTR.,2,WHT,70MM,-,	S.N.A
...3	IC401	1202-000103	IC-VOLTAGE COMP.;393,DIP,8P,300MIL,DUAL,	
...3	IC601	1204-001971	IC-SOUND PROCESSOR;MSP3411G-P0-B11,DIP,5	
...3	IC602	AA96-50369D	ASSY H/S;-,SOUND,AA62-30181F,TDA7269,HER	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1201-001385	IC-POWER AMP;7269A,ZIP,11,19.6,DUAL,13,P	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30181F	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
...3	IC801S	AA96-50371H	ASSY H/S;-,SMPS,AA62-30181H,5Q1565RF,HER	S.N.A
....4		AA61-11028A	BRACKET;-,SECC,T1.0,-,-,-,-	S.N.A
....4		AA62-30181H	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		1203-002512	IC-PWM CONTROLLER;KA5Q1565RF-YDTU,TO-3PF	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	IC803	1203-001225	IC-POSI.FIXED REG.;78R09,TO-220,4P,-,PLA	
...3	IC805	AA96-00243K	ASSY H/S;-,REGULATOR,AA62-000450A,KA78R0	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-	S.N.A
....4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
...3	IC901	AA09-00041A	IC MICOM;,SDA555X-0TP,3.3V,-,128K,SDIP,-	S.N.A
...3	IC902	1103-001177	IC-EEPROM;24WC16,2048x8Bit,DIP,8P,-,-,2.	
...3	JA701	3722-001765	JACK-PIN;9P(9P),-,NI,YEL/GRN/WHT/BLU/RED	
...3	JA702	3722-001766	JACK-PIN;7P(9P),-,NI,GN/WH/WH/BL/RD/RD/R	
...3	L808	AA27-00098A	COIL CHOKE;-,-,24uH,10%,-,0.1,3.0A,DR10X	
⚠ ...3	LR402S	AA27-10004F	COIL CHOKE;-,56uH,K,-,2.5A,BK,-,DR12x15,	
⚠ ...3	LR403S	AA27-00251A	COIL LINEARITY;10UH,10UH,YL81 DR1518,11M	
⚠ ...3	LR404S	AA27-40003P	COIL HORIZ. WIDTH;-,120uH/180uH,Th8x20,U	
⚠ ...3	LR405S	AA27-00057A	COIL HORIZ. WIDTH;-,10mH,YL-9N 15x27.5 C	
⚠ ...3	LX801S	AA29-00011A	FILTER LINE NOISE;CZ32W8,-,0.20MAX,1.5KV	
⚠ ...3	LX802S	AA29-00012A	FILTER LINE NOISE;CS29A6PF8X/HAC,-,0.1MA	
⚠ ...3	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ ...3	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
⚠ ...3	PT801S	1404-001026	THERMISTOR-PTC;7ohm,20%,-,290V,25A,-,ST	
...3	Q402	0505-001116	FET-SILICON;BUZ73A,N,200V,22A,0.6ohm,40W	
...3	Q804	BH99-00007S	ASSY HEAT/SINK;KSC2073,MICOM,HERCULES,BH	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	0502-001007	TR-POWER;KSC2073-H2,NPN,25W,TO-220,ST,6	
....4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
....4	CIS	BH62-00007A	HEAT SINK-TR;-,T1.0,L20*H30,CDA	S.N.A
⚠ ...3	RL801S	3501-001053	RELAY-POWER;5Vdc,530mW,10A,1FormA,15mS,5	
...3	T401	AA26-50001S	TRANS-HORIZ.DRIVE;-,-,-,6.0mH,-,-,44uH,-	
⚠ ...3	T444S	AA26-00173A	TRANS FBT;FUJ34H001F(S),FUJ34H001F(S),1.	
⚠ ...3	T801S	AA26-00010B	TRANS SWITCHING;EER5345,K55A ,90~264V,PM	
⚠ ...3	TU01S	AA40-00083A	TUNER;TCLS3101PD16A(S),PAL B/G,D/K,I,M,1	
⚠ ...3	TU02S	AA40-00084A	TUNER;TCPS3000PC16B(S),PAL ,181CH,38.9MH	
...3	X601	2801-004020	CRYSTAL-UNIT;18.432MHz,30ppm,28-AAM,12pF	
...3		AA39-20536G	LEAD CONNECTOR-ASSY;,1P,60MM,F,F,1617#22	
...3		AA61-00707B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
...3		AA95-03092A	ASSY SUB-PCB,FEATURE BOX;,K55A,ASIA	
....4	BR01	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4	BR02	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4	CN01	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4	CN02	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	CN03	3711-003601	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,ANGLE,	
....4	DC41	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
....4	DC51	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	DX01	2802-001177	RESONATOR-CERAMIC;2.696MHZ,0.4%,BK,10X4.	
....4	EC48	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	EC49	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	EX01	2801-004019	CRYSTAL-UNIT;20.25MHz,30ppm,28-AAM,13pF,	
....4	IC06	1203-002000	IC-VOL. DETECTOR;7027,TO-92,3P,-,PLASTIC	
....4	SX01	2802-001179	RESONATOR-CERAMIC;4MHZ,0.5%,BK,8X3X5.5MM	
....4		AA97-13003A	ASSY AUTO-FEATURE BOX;K55A	S.N.A
.....5		AA97-12982A	ASSY SMD-FEATURE BOX;,K55A,PAL	S.N.A
.....6	DC01	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....6	DC02	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....6	DC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC04	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC05	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC06	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....6	DC07	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....6	DC08	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	DC09	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,	
.....6	DC10	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC12	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC13	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC14	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC17	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC19	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC20	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	DC21	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC22	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	DC23	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....6	DC24	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC25	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC26	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC27	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC28	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC29	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC30	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC31	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	DC32	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	DC33	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	DC34	2203-000896	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
.....6	DC35	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	DC36	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	DC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC39	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	DC40	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....6	DC43	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	DC45	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	DC49	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	DC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	DC52	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	DD01	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD02	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD03	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....6	DD04	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....6	DD05	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....6	DD06	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....6	DD07	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....6	DD08	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD09	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD10	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD11	0403-000746	DIODE-ZENER;RLZ3.9B,3.89-4.16V,500MW,LL-	
.....6	DD13	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD14	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD15	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD16	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD17	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD18	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD19	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DD20	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
.....6	DL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	DL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	DL03	2703-001070	INDUCTOR-SMD;100uH,10%,4.5x3.2x3.2mm	
.....6	DQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	DQ02	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	DQ03	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	DQ04	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	DQ05	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	DQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	DQ07	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	DQ08	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	DQ09	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
.....6	DQ10	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	DQ11	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	DR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR05	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR06	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	DR08	2007-000691	R-CHIP;3.3Mohm,5%,1/16W,DA,TP,1608	
.....6	DR09	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR10	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR13	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....6	DR14	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....6	DR15	2007-000869	R-CHIP;4.7Kohm,1%,1/16W,DA,TP,1608	
.....6	DR16	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR17	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR18	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR19	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR23	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP,1608	
.....6	DR24	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
.....6	DR25	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6	DR26	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR27	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....6	DR28	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....6	DR29	2007-000118	R-CHIP;390ohm,5%,1/16W,DA,TP,1608	
.....6	DR30	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR31	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....6	DR32	2007-000081	R-CHIP;2.7Kohm,5%,1/16W,DA,TP,1608	
.....6	DR33	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....6	DR34	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....6	DR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR36	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR37	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....6	DR38	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....6	DR39	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....6	DR40	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....6	DR41	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....6	DR42	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR43	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR44	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR45	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR46	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR47	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6	DR49	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR50	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR51	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR52	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR53	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR54	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR55	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR56	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR57	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....6	DR58	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR59	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR60	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR61	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6	DR62	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6	DR63	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....6	DR64	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6	DR65	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	DR66	2007-000088	R-CHIP;7.5Kohm,5%,1/16W,DA,TP,1608	
.....6	DR68	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	DR69	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....6	DR70	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	DR80	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6	DR81	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
.....6	DR82	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
.....6	DR86	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....6	DR87	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....6	DR88	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	EC01	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC02	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC04	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	EC08	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	EC09	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	EC10	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	EC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC12	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC13	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	EC14	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	EC15	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....6	EC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC17	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC18	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC19	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC20	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC21	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC22	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC23	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....6	EC24	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	EC29	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EC30	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EC31	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EC32	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC33	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC34	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
.....6	EC35	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
.....6	EC36	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC39	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC40	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC41	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC42	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	EC43	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC44	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	EC45	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC46	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC47	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	EC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	EC51	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	EC52	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC53	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC54	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC55	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC56	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC57	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	EC58	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	EC59	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	EC60	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	EC62	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EC63	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EC64	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EC65	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....6	EL04	3301-001082	CORE-FERRITE BEAD;AB,600HM,3.2X2.5X1.3MM	
.....6	EL05	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	EL06	3301-001324	CORE-FERRITE BEAD;AB,150HM,2X1.25X0.9MM,	
.....6	EL07	3301-001324	CORE-FERRITE BEAD;AB,150HM,2X1.25X0.9MM,	
.....6	EL08	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	EL09	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	EL13	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	EQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	EQ02	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	EQ03	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	EQ04	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....6	EQ05	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....6	EQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	ER01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER02	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	ER06	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....6	ER07	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....6	ER09	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6	ER11	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	ER12	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6	ER13	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER14	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	ER15	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6	ER16	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER17	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	ER18	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6	ER19	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	ER21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	ER22	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER24	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER25	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER26	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	ER32	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....6	ER33	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....6	ER34	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....6	ER35	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....6	ER36	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....6	IC01	1204-001938	IC-DECODER;VSP9407B-B11,MQFP,80P,14X14MM	
.....6	IC02	1204-001814	IC-SELECTOR;CXA2151Q,QFP,48P,144MIL,PLAS	
.....6	IC03	1001-001082	IC-VIDEO SWITCH;BA7657F,-,SOP,24P,300MIL	
.....6	IC04	1204-001989	IC-VIDEO PROCESS;CXA2165Q,QFP,64P,20X14M	
.....6	IC05	1203-002186	IC-POSI.FIXED REG.;18,DPAK,3P,240MIL,PLA	
.....6	IC10	1001-001177	IC-VIDEO SWITCH;TEA6425D,VIDEO SWITCH ,S	
.....6	IC11	0801-000662	IC-CMOS LOGIC;74HC123,MULTIVIBATOR,SOP,1	
.....6	PCB	AA41-00644B	PCB-PAL FERTURE BOX;CS29Z6,FR-4,4L,B,1.6	S.N.A
.....6	SC01	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC02	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC03	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC04	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC05	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC06	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC12	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC13	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC14	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	SC16	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC17	2203-005809	C-CERAMIC,CHIP;1000nF,10%,16V,X7R,TP,201	
.....6	SC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	SC19	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC20	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	SC21	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC22	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	SC23	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC24	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC25	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC26	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	SC27	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC28	2203-001656	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,1608	
.....6	SC29	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC30	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC31	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC32	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC33	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC34	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC35	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC36	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC37	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC38	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC39	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	SC40	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC41	2203-000998	C-CERAMIC,CHIP;0.047NF,5%,50V,C0G,TP,160	
.....6	SC42	2203-000998	C-CERAMIC,CHIP;0.047NF,5%,50V,C0G,TP,160	
.....6	SC43	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	SC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	SC45	2203-000998	C-CERAMIC,CHIP;0.047NF,5%,50V,C0G,TP,160	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....6	SC46	2203-000998	C-CERAMIC,CHIP;0.047NF,5%,50V,C0G,TP,160	
.....6	SC47	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....6	SC48	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....6	SC49	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	SL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	SL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	SQ01	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	SR01	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR04	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	SR05	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	SR06	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	SR07	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR08	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR09	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	SR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	SR11	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	SR12	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR13	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR14	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR25	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6	SR26	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP,1608	
.....6	SR27	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....6	SR28	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6	SR29	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	SR36	2007-000259	R-CHIP;1.6Kohm,5%,1/16W,DA,TP,1608	
.....6	SR37	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6	TC01	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	TC02	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	TC03	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	TC04	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	TC05	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	TC06	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6	TC07	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	TC08	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6	TD01	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....6	TL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6	TQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	TQ02	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	TR01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	TR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	TR03	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	TR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6	TR05	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	TR07	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	TR08	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	TR09	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6	TR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....6	TR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3		AA97-13373G	ASSY AUTO-MAIN;,K55A	S.N.A
....4	C101	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C102	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C104	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
....4	C105	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C106	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C107	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C108	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
....4	C109	2202-000279	C-CERAMIC,MLC-AXIAL;47pF,5%,50V,SL,TP,3.	
....4	C110	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C111	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C112	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C113	2202-000216	C-CERAMIC,MLC-AXIAL;0.027NF,5%,50V,SL,TP	
....4	C116	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C201	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C202	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	C206	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C207	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C239	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C240	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C302	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
....4	C303	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
....4	C304	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
....4	C305	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
....4	C306	2301-000160	C-FILM,PEF;12nF,5%,50V,TP,11.0x6.0x9.0mm	
....4	C307	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
....4	C308	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
....4	C401	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C402	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
....4	C403	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C404	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
....4	C408	2301-001143	C-FILM,PPF;56nF,5%,400V,TP,20x10x17,7.5	
....4	C409	2303-001001	C-FILM,PPF;22nF,5%,630V,TP,18x14.5x8.5mm	
....4	C411	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
....4	C412	2301-000310	C-FILM,PEF;68nF,5%,50V,TP,8.0X8.5X4.0X5,	
....4	C413	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
....4	C414	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
....4	C415	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,	
....4	C416	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
....4	C417	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C418	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
....4	C420	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
....4	C421	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C422	2401-001527	C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
....4	C424	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
....4	C425	2306-000127	C-FILM,MPPF;120nF,5%,400V,TP,21.5x17mm,5	
....4	C432	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C601	2201-000558	C-CERAMIC,DISC;0.47NF,10%,50V,Y5P,TP,5X3	
....4	C602	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
....4	C603	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C604	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	C605	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C606	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C607	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C608	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C610	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C611	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C612	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	C613	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
....4	C614	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C615	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C619	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C620	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C621	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C622	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C623	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C624	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C625	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C626	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C627	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C628	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C629	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C630	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C631	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C632	2201-000370	C-CERAMIC,DISC;0.22NF,10%,50V,Y5P,TP,4X3	
....4	C633	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C634	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	C635	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C636	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C637	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C638	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C639	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C640	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C641	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C642	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C643	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C644	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
....4	C645	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C646	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C647	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
....4	C648	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
....4	C649	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm	
....4	C650	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
....4	C651	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C652	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C653	2401-002216	C-AL;2200uF,20%,35V,GP,TP,16x25,7.5	
....4	C654	2201-000611	C-CERAMIC,DISC;0.056NF,5%,50V,C0G,TP,7X3	
....4	C655	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C656	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
....4	C657	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
....4	C658	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C659	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	C660	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	C701	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
....4	C801	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
....4	C802	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
....4	C804	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
....4	C805	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
....4	C807	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.	
....4	C808	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
....4	C809	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	C810	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C811	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	C812	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C814	2201-002028	C-CERAMIC,DISC;0.47NF,10%,2KV,Y5P,TP,7.5	
....4	C816	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
....4	C817	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C818	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4	C819	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C821	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	C822	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C823	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	C824	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
....4	C825	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C826	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
....4	C827	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4	C828	2201-000374	C-CERAMIC,DISC;0.22NF,5%,50V,C0G,TP,10.5	
....4	C830	2201-000984	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
....4	C831	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C832	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
....4	C833	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4	C834	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
....4	C835	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4	C836	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C837	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C838	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
....4	C840	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
....4	C841	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
....4	C843	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C844	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C901	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C902	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C903	2202-000719	C-CERAMIC,MLC-AXIAL;6.8nF,20%,16V,Y5R,TP	
....4	C904	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C905	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C906	2202-000791	C-CERAMIC,MLC-AXIAL;150pF,10%,50V,Y5P,TP	
....4	C907	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
....4	C909	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
....4	C910	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
....4	C911	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
....4	C912	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C913	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C914	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C915	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C916	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C917	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C918	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
....4	C919	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C920	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C921	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C922	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C923	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C924	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C925	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C927	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	CN601	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
....4	CN602	3711-002645	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH	
....4	CN901	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
....4	CW901	2503-000156	C-NETWORK;100pFx4,20%,50V	
....4	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D202	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D207	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4	D401	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 4	D402	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4	D403	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D404	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4	D405	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D406	0404-001056	DIODE-SCHOTTKY;RK16,60V,1.5A,DO-204AC,TP	
⚠ 4	D408	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4	D409	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
⚠ 4	D410	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D411	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
....4	D603	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D607	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4	D804	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4	D805	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D808	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D812	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D816	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D901	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D902	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D903	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D904	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D907	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4	DZ302	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ303	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ304	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
....4	DZ305	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ306	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ307	0403-001118	DIODE-ZENER;MTZ30A,32V,26.99-28.39V,500m	
....4	DZ401	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
....4	DZ402	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DZ404	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ601	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ602	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ603	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ604	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ605	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ606	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ607	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	DZ608	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	DZ801	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ802	0403-000716	DIODE-ZENER;MTZJ4.7B,4.7V,4.55-4.8V,500m	
....4	DZ803	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
....4	DZ804	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
....4	DZ807	0403-001330	DIODE-ZENER;MTZJ30A,26.99-28.39V,500mW,D	
....4	DZ808	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ902	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ906	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ907	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ908	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ909	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ910	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ911	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ912	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	EL201	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL202	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL203	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL204	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL401	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL402	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL407	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL408	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL805	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL806	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL807	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL808	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY302	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY303	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY403	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY404	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY405	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY406	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY407	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY408	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY409	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	EY410	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY411	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY412	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY413	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY414	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY415	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY417	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY418	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY419	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY420	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY421	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY422	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY423	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY424	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY425	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY426	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY429	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY430	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY431	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY432	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY433	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY434	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY435	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY436	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY437	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY439	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY441	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY446	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY447	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY603	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY604	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY701	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY702	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY703	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY704	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY705	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY706	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY801	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY802	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY803	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY804	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY805	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY806	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY809	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY810	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY811	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY812	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY813	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY814	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY815	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY816	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY817	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY820	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY824	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY825	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY828	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY829	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY830	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY831	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY832	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY833	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY835	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY836	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY837	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY838	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY839	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY840	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY841	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY842	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY844	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY845	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY846	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY848	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY850	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY851	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY853	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY854	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY855	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY856	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY857	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY858	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY859	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY860	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY861	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY862	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY864	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY865	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY871	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY872	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
⚠ 4	FA801S	3601-000120	FUSE-AXIAL LEAD;125V,2.5A,FAST-ACTING,GL	
⚠ 4	FA802S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
⚠ 4	FA803S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
....4	GT102	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT301	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT302	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT401	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT402	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT404	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT405	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT406	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT409	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT410	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT411	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT412	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	HIC401	AA13-00094A	IC HYBRID;-,DDRI001A,SIP,5P,-,TP	
....4	IC202	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
....4	IC402	1203-000243	IC-POSI.FIXED REG.;7812A,TO-220,3P,-,PLA	
....4	IC804	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
....4	IC903	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
....4	IC904	1203-001943	IC-VOL. DETECTOR;7025,TO-92,3P,-,PLASTIC	
....4	J709	2001-000527	R-CARBON;22OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	L101	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
....4	L103	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	L104	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
....4	L106	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	L201	2701-000200	INDUCTOR-AXIAL;5.6uH,10%,4.2x9.8mm	
....4	L203	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L402	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
⚠ 4	L403	2701-001040	INDUCTOR-AXIAL;10uH,10%,4.5x14mm	
....4	L404	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L407	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L409	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L410	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4	L601	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L602	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
....4	L603	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L604	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L605	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L606	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L607	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L608	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L609	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L610	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L612	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L613	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L614	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L615	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L703	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L704	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L705	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L706	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L801	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	L802	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L803	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L804	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L805	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L806	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L807	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4	L809	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L811	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
....4	L901	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L902	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
....4	L903	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L904	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L906	2701-000215	INDUCTOR-AXIAL;8.2uH,10%,2.5x3.4mm	
....4	L907	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L908	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
....4	L909	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
....4	PCB	AA41-00707B	PCB-MAIN;CS29Z6HP,FR-1,1L,B,1.6T,330X245	S.N.A
....4	Q404	0505-000156	FET-SILICON;IRF620,N,200V,5A,0.8ohm,50W,	
....4	Q601	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q603	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q801	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q802	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
....4	Q803	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q901	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q906	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q907	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q908	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q909	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4	Q910	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4	Q912	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q913	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q914	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	R101	2001-000938	R-CARBON;680HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R102	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R103	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R104	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R105	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R106	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R107	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R108	2001-000969	R-CARBON;750HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R203	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R204	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R301	2001-001163	R-CARBON(S);5600HM,5%,1/2W,AA,TP,2.4X6.4	
....4	R302	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R303	2001-000016	R-CARBON(S);10HM,5%,1/2W,AA,TP,2.4X6.4MM	
....4	R304	2008-001108	R-FUSIBLE(S);1.2ohm,5%,2W,AG,TP,3.9x12mm	
....4	R305	2003-002205	R-METAL OXIDE(S);330ohm,5%,2W,AG,TP,3.9X	
....4	R306	2003-002205	R-METAL OXIDE(S);330ohm,5%,2W,AG,TP,3.9X	
....4	R307	2008-001114	R-FUSIBLE(S);1.5ohm,5%,2W,AG,TP,3.9x12mm	
....4	R308	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R309	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R310	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R314	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R315	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R316	2001-001129	R-CARBON(S);330KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R317	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R401	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R402	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R403	2003-000532	R-METAL OXIDE(S);18ohm,5%,2W,AF,TP,4x12m	
....4	R405	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
....4	R409	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
....4	R410	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
....4	R411	2001-000028	R-CARBON(S);1000HM,5%,1/2W,AA,TP,2.4X6.4	
....4	R412	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
....4	R413	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
....4	R414	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
....4	R415	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R416	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R418	2001-001114	R-CARBON(S);2700HM,5%,1/2W,AA,TP,2.4X6.4	
....4	R419	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R420	2004-001987	R-METAL(S);4.3Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R421	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R422	2008-001149	R-FUSIBLE(S);0.220HM,5%,2W,AF,TP,3.8X11M	
....4	R423	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R424	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
....4	R425	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
....4	R426	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
....4	R428	2004-000698	R-METAL;3.3Kohm,1%,1/4W,AA,TP,2.4x6.4m	
....4	R430	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
....4	R431	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
....4	R432	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R433	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
....4	R434	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	R435	2003-000784	R-METAL OXIDE(S);7.5Kohm,5%,2W,AF,TP,4x1	
....4	R440	2004-002019	R-METAL(S);33Kohm,1%,1/2W,AA,TP,2.5x6.5m	
....4	R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R602	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R603	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R604	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R605	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R606	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R607	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R608	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R609	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R610	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R611	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R612	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R613	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R614	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R615	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R616	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R617	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R618	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R623	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R624	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R626	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R627	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R628	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R629	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R630	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R631	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R632	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R633	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R634	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R635	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R636	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R637	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R638	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R639	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R704	2001-000969	R-CARBON;750HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R710	2001-000376	R-CARBON;150HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R715	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R716	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R717	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R718	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R723	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R801	2001-000019	R-CARBON(S);100HM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R802	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4	R803	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4	R804	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4	R805	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R806	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R808	2001-001197	R-CARBON(S);910OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R809	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R810	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R811	2001-001188	R-CARBON(S);8.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R812	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R813	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R815	2008-000284	R-FUSIBLE(S);0.10HM,10%,2W,AF,TP,3.9X10M	
....4	R816	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R817	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R818	2001-001131	R-CARBON(S);33KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R819	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R820	2001-001096	R-CARBON(S);2.2OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R821	2004-002015	R-METAL(S);140Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R822	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R823	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R824	2001-000305	R-CARBON;110KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R827	2008-000284	R-FUSIBLE(S);0.10HM,10%,2W,AF,TP,3.9X10M	
....4	R828	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm	
....4	R829	2008-001148	R-FUSIBLE;3.3OHM,5%,1W,AG,TP,3.9X12MM	
....4	R830	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	R833	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R835	2003-002181	R-METAL OXIDE(S);68Kohm,5%,2W,AG,TP,3.9x	
....4	R838	2001-001050	R-CARBON(S);1.5KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R840	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R841	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R842	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R901	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R902	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R903	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R904	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R905	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R906	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R907	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R908	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R909	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R910	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R911	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R912	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R913	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R914	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R915	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R916	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R917	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R919	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R920	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R921	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R922	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R923	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R924	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R925	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R926	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R927	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R928	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R935	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R936	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R937	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R938	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R940	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R941	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R942	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R945	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R946	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R947	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R948	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R951	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R952	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R953	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R954	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R955	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R958	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R960	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R961	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R962	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R963	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R965	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R966	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R967	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R968	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R972	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R973	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R974	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R981	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R982	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R983	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R984	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R988	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 4	RR430S	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
⚠ 4	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ 4	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
....4	X901	2801-003728	CRYSTAL-UNIT;6MHz,30ppm,28-AAM,20pF,40oh	

ASSY CPT

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA91-02964A	ASSY CPT;CS34Z4HF9X/BWT	S.N.A
..2		AA91-02176B	ASSY CPT;A80LTM350X98,34,+380MG,ITC,AA0	S.N.A
⚠ ...3		AA03-00232A	CRT COLOR;A80LTM350X98,+380MG,0.35MH,9.9	
..2		AA98-70011F	ASSY TBC WIRE(P);-,34inch,NTSC,2P-WH,KS4	S.N.A
..2		AA27-00060A	COIL DEGAUSSING;-,34,14ohm ,-,L3600,E	

ASSY COVER REAR

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA90-03205C	ASSY COVER REAR;CS34Z7HF9X/BWT	S.N.A
..2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A
..2		AA64-02655D	CABINET BACK;34Z7,ABS,VO,G4309,SVM2012	
..2		AA63-00567A	COVER-BACK,R;34Z7,ABS,HB,G4309,DGM2188	S.N.A
..2		AA63-00566A	COVER-BACK,L;34Z7,ABS,HB,G4309,DGM2188	S.N.A
..2		AA60-00091J	SPACER-FELT;-,FELT,330X10,-,-,BLK,T0.5,-	S.N.A

ASSY COVER FRONT

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA90-03202N	ASSY COVER FRONT;CS34Z7HRGX/XHK	S.N.A
..2	C/F	AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
..2	CA+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	CB+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CB+TBA	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CC+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	CRT+CF	AA60-10050V	SCREW-ASSY;-,SWRCH18A,M6,L30,HH,+,WC,-,Z	S.N.A
..2	CV+CB	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CV+CB+	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	D-COIL	AA65-30113A	CLAMPER CORE-D,COIL;-,NYLON 66,V2,-,BLK,	S.N.A
..2	D-COIL	AA65-30017A	CLAMPER CORE-D,COIL;-,NYLON-66,V0,-,NTR,	S.N.A
..2	PP+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	TBA+RJ	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	WOO+CB	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2		AA73-00017A	RUBBER-CAP;29Z7,SILICONE RUBBER,WHT	S.N.A
..2		AA91-03960A	ASSY HOLDER SPK;-,-,8OHM/25W,-,WOOFER SP	
..2		AA96-00916E	ASSY COVER P-FRONT;34Z7,CS34Z7HRG,ABS HB	
...3	GS+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
...3	KNOPOW	AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A
...3	LED+GS	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
...3	SPK+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
...3		AA64-02666A	INDICATOR LED;Z7,ACRYL,CLR	
...3		AA64-70124C	BADGE-BRAND;-,AL,-,-,L=70,SAMSUNG,SILVER	S.N.A
...3		AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA91-03959A	ASSY HOLDER SPK;-,-,8OHM/10W,-,FRONT SPE	
...3		AA64-02665A	WINDOW-RMC;Z7,PC,VIOLET	
...3		AA64-02654F	CABINET-FRONT;CS34Z7HRGX CHN,ABS,HB0690M	S.N.A
...3		AA64-02657D	GRILLE-SPEAKER;32Z7,ABS,HB,G4309,DGM2188	S.N.A
...3		AA64-02663B	KNOB-POWER;Z7,PC,VIOLET,MASTER	
...3		AA64-02664A	DECORATION-POWER;Z7,ABS,HB,NTR	
..2		AA73-00005B	RUBBER-CAP;FLAT,PRJ,SILICONE RUBBER,WHIT	
..2		AA63-60004Z	SPACER-GUM,CRT;ALL MODEL,NTR RUBBER,-,-,	S.N.A
..2		AA61-01258A	HOLDER-D,COIL;NYLON,34M9,T3.0	S.N.A
..2		AA61-01108A	SUPPORT-CRT;Z7,HIPS	S.N.A

ASSY ACCESSORY

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA92-07347A	ASSY ACCESSORY;CS34Z7HRGX/XHK,HONG KONG,	S.N.A
..2	2	AA68-02452A	MANUAL USERS;CS29Z7HR,ENG,PIP,TTX	
..2		AA69-00862A	BAG PE;-,HDPE PE FOAM,T0.03,W400,H240,-,	S.N.A
..2		AA59-00266E	REMOCON;TM63,SAMSUNG,51PX,45,SAMSUNG,2.4	

ASSY P/MATERIAL

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA92-05219A	ASSY P/MATERIAL;CT-34Z7HR	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
..2		AA69-00306A	BAG AIR;LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A
..2		AA69-00744F	BAG-SHEET;-,HDPE PE FOAM,T0.015,W1400,H1	S.N.A
..2		AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,	S.N.A
..2		AA63-10007C	BAND-PP;W18,CLEA,1G	S.N.A
..2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A

7-4 CS29Z4HNGX/BWT

ASSY CHASSIS

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA91-05665D	ASSY CHASSIS;Z4,K55A,PAL CIS	S.N.A
..2	C-BLOC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2	D-FOCU	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2	MP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2	PCB	AA61-00706B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
..2	TBA+HC	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2	WP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2		AA96-00908E	ASSY COVER P-TERMINAL BOARD;29Z6,CIS,HIP	
...3		AA64-02823A	INLAY-T/BOARD;Z7,PS SHEET,T0.5,PAL	S.N.A
...3		AA65-00025A	TERMINAL-BOARD,ANT;,HIPS V0,BLK	S.N.A
..2		AA94-12358A	ASSY PCB MISC-LED;Z4,K55A,PAL	
...3	CNY01	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,500,YBNH025-05,6	
...3	LDY01	0601-001381	LED;ROUND,RED/GRN,5.0MM,650/563NM	
...3	RMY01	AA32-00005A	MODULE REMOCON;VISHAY,10,700~850,-,-,ST	
...3		AA97-13495A	ASSY AUTO-LED;Z4,K55A,PAL	S.N.A
....4	CY01	2401-002291	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	
....4	DZY01	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZY02	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	PCB	AA41-00520B	PCB-LED;CS32Z4/29Z4,FR-1,1L,B,1.6T,245X2	S.N.A
....4	RY01	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA94-12357A	ASSY PCB MISC-CONTROL;Z4,K55A,PAL	
...3	CNY01	AA39-00100D	LEAD CONNECTOR-ASSY;,4P,700MM,YBNH250-04	
...3	PCB+KC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
...3	SWY01	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY02	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY03	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY04	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY05	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY06	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-13519A	ASSY AUTO-CONTROL;Z4,K55A,PAL	S.N.A
....4	DZY03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZY04	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	LY01	2701-000136	INDUCTOR-AXIAL;18uH,10%,2.5x3.4mm	
....4	LY02	2701-000136	INDUCTOR-AXIAL;18uH,10%,2.5x3.4mm	
....4	PCB	AA41-00522A	PCB-CONTROL;CS32Z4,FR-1,1L,A,1.6T,245X24	S.N.A
....4	RY02	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY03	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY04	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY05	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY06	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
...3		AA64-03209A	KNOB-CONTROL;Z4,ABS,HB,WHT,SVM3012	S.N.A
⚠ ..2		AA96-20130H	ASSY POWER CORD;-,CP2/NO(4.0R),H/S 500MM	S.N.A
...3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3		AA39-10003B	CBF POWER CORD;-,KJP-140,KLCE-2F,2.4m,HO	
...3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A
..2		AA95-01863A	ASSY SUB-PCB-MASTER;WS36Z48D,KS4A,PAL,AA	
...3	CN811	AA39-20179C	LEAD CONNECTOR-ASSY;,3(2)P,600MM,YFH800-	
...3	HP+PCB	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
...3	MPP+LP	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
⚠ ...3	SW811S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
...3		AA97-05539A	ASSY AUTO-MASTER;WS36Z48D,KS4A,PAL	S.N.A
....4	EY01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY03	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY04	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	GTY05	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY06	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY07	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY08	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY09	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY10	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	PCB	AA41-00521A	PCB-MASTER S/W;CS32Z4,FR-1,1L,A,1.6T,245	S.N.A
...3		AA61-00450B	HOLDER-POWER;32Z5,ABS,-,-,-,GRAY,HB	S.N.A
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA65-00011B	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
..2		AA61-01190A	HOLDER-CHASSIS;Z7,HIPS V0,G4309	S.N.A
..2		AA94-07792A	ASSY PCB MISC-DYNAMIC FOCUS;CT-29Z7HR,K5	
...3	LH01	AA26-90002C	TRANS-DUMMY;-,-,-,-,-,-,-,-,-,-,-,EER2	
...3	LH02	AA27-40003L	COIL HORIZ. WIDTH;-,1.0mH,DR14x20,2UEW0.	
...3	RH28	2008-001113	R-FUSIBLE(S);0.22ohm,10%,2W,AG,TP,3.9x12	
...3	WIRE3	AA39-20061C	LEAD CONNECTOR-ASSY;,3P,200,YFH800-03,S,	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-07229L	ASSY AUTO-DYNAMIC FOCUS;CT-29Z7HR,K55A	S.N.A
....4	EY01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY03	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY04	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY05	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY06	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY07	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY08	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY09	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	GTH01	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTH02	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTH03	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	PCB	AA41-00152C	PCB-DOUBLE FOCUS;CW29A6VN8X/XEF,FR-1,1L,	S.N.A
..2		AA94-08584P	ASSY PCB MISC-CRT;29Z6,K55A,100HZ	
...3	C522	2201-002117	C-CERAMIC,DISC;4.7nF,20%,3kV,Y5U,TP,16x6	
...3	C523	2306-000272	C-FILM,MPPF;820nF,5%,400V,BK,29x25.5x18.	
...3	CNC01	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	CNC01A	AA39-00088A	LEAD CONNECTOR-ASSY;HERCULES,UL1007/1185	
...3	CNC02	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3	CNC02A	AA39-00127A	LEAD CONNECTOR-ASSY;,8P,400MM,35155-0800	
...3	GT501A	AA39-00341A	LEAD CONNECTOR;K55A(WT-32Z4HD),UL1015#18	
⚠ ...3	GT503S	AA39-20010B	LEAD CONNECTOR-ASSY;,1P,500,YFH800-01,S,	
...3	IC501	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC502	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC503	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
....4		1201-001131	IC-VIDEO AMP;6111,SIP,9P,-,SINGLE,-,PLAS	
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3	IC504	BH99-00038E	ASSY HEAT/SINK;TDA2030,AMP,HERCULES,BH62	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	1201-000010	IC-OP AMP;2030,PENTAWATT,5P,-,SINGLE,-,C	
....4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
....4	CIS	BH62-00041A	HEAT SINK-TR;PN17LT,A1050S,T1.0,50,23,-,	S.N.A
...3	QF09	AA96-00243M	ASSY H/S;-,AMP,AA62-000450A,2SA1011,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000131	TR-POWER;2SA1011-D,PNP,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	QF10	AA96-00243L	ASSY H/S;-,CRT,AA62-000450A,2SC2344,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000153	TR-POWER;2SC2344-D,NPN,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	SC01	3722-001503	JACK-PIN;1P,1PI,NI,RED,SCR-JACK	
⚠ ...3	V999S	3704-001032	SOCKET-CRT;8P,29PI,35.5PI,AU30U	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-12040A	ASSY AUTO-CRT;CS29Z6HP,K55A	S.N.A
....4	C501	2201-000193	C-CERAMIC,DISC;0.01NF,0.25PF,50V,C0G,TP,	
....4	C504	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C505	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C506	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C507	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C508	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C509	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C510	2201-000291	C-CERAMIC,DISC;1NF,10%,500V,Y5P,TP,7.5X3	
....4	C511	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C512	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C513	2201-000600	C-CERAMIC,DISC;0.56NF,10%,50V,Y5P,TP,5X3	
....4	C514	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C515	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C520	2401-000703	C-AL;2200uF,20%,25V,GP,-,12.5x25mm,	
....4	C526	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C528	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C531	2401-002264	C-AL;10uF,20%,350V,GP,TP,10x20mm,5m	
....4	C532	2401-001563	C-AL;47uF,20%,400V,GP,TP,16x25,7.5	
....4	C533	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C534	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C535	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	CF01	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4	CF02	2201-000017	C-CERAMIC,DISC;1NF,10%,50V,Y5P,TP,5X3.5M	
....4	CF03	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF04	2201-000516	C-CERAMIC,DISC;4.7NF,+100-0%,500V,Y5U,TP	
....4	CF05	2301-000261	C-FILM,PEF;4.7nF,5%,100V,TP,10.5x12.5x6.	
....4	CF06	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF07	2201-000604	C-CERAMIC,DISC;0.056NF,+100-0%,500V,SL,T	
....4	CF71	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	CF73	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
....4	CF74	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	CF75	2401-000045	C-AL;10uF,20%,160V,GP,TP,10x16,5	
....4	D501	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D502	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D509	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D510	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D511	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D512	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D513	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D514	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DF01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF05	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF06	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF07	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DF08	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DZ501	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ502	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ504	0403-000698	DIODE-ZENER;TZP12A,12V,11.4-12.6V,1W,DO-	
....4	DZ510	0403-000734	DIODE-ZENER;TZP15B,15V,14.7-16.5V,1W,DO-	
....4	DZF01	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
....4	DZF02	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
....4	DZF03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	EL100	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL80	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL81	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL82	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL83	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL84	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL85	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL86	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL87	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL88	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL89	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL92	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL94	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL95	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL96	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL97	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL98	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL99	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	FN1	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
....4	FV1	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
....4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT503	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT504	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	L502	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
....4	LF01	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF02	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF03	2701-000112	INDUCTOR-AXIAL;100uH,10%,3x7mm	
....4	LF04	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF06	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF08	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF09	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF11	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	PCB	AA41-00578D	PCB-CRT;CT-29Z7HR,FR-1,1L,D,1.6T,330X245	S.N.A
....4	Q501	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q502	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q503	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q504	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	QF02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	QF03	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	QF04	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	QF05	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	R501	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R502	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R503	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R504	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R505	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R506	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R507	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R508	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R509	2008-001047	R-FUSIBLE(S);68ohm,5%,2W,AF,TP,3.9x10mm	
....4	R510	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R511	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R512	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R513	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R514	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R515	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R516	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R518	2001-001095	R-CARBON(S);2.2MOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R519	2001-000356	R-CARBON;150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R520	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R522	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R523	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R525	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7	
....4	R527	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R528	2003-000458	R-METAL OXIDE(S);100ohm,5%,2W,AF,TP,4x12	
....4	R530	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R531	2001-000539	R-CARBON;24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R540	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R541	2008-001053	R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
....4	R554	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R555	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R556	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R560	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R561	2001-001126	R-CARBON(S);3000HM,5%,1/2W,AA,TP,2.4X6.4	
....4	R562	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R563	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R564	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R565	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R566	2001-001040	R-CARBON(S);0.68OHM,5%,1/2W,AA,TP,2.4X6.	
....4	RF13	2008-001053	R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
....4	RF14	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF15	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF16	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF17	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF18	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF19	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF20	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF21	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF22	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF23	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF24	2003-001018	R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
....4	RF25	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF26	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF27	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF28	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF29	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF30	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF31	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF32	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	RF33	2001-001053	R-CARBON(S);1.5OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF34	2001-001100	R-CARBON(S);2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF35	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	RF36	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
..2		AA94-12047C	ASSY PCB MAIN;WS32Z4HPGX/BWT,K55A	
...3	C-BLOC	AA26-00069A	TRANS FBT;FUJ-29C002C(S),DREAM3,4,-,-,-	
...3	C423	2306-000272	C-FILM,MPPF;820nF,5%,400V,BK,29x25.5x18.	
...3	C426	2306-000195	C-FILM,MPPF;360nF,5%,400V,TP,26x19x11.5,	
...3	C803	2401-002227	C-AL;330uF,20%,450V,GP,BK,35x45,10	
...3	C806	2306-000112	C-FILM,MPPF;100nF,20%,250V,BK,-,15mm	
...3	C815	2401-003024	C-AL;220uF,20%,200V,WT,TP,22x35,10	
...3	C820	2401-003419	C-AL;2200uF,20%,50V,WT,TP,16X35.5mm	
...3	CN502	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3	CN702	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	CN702A	AA39-00114C	LEAD CONNECTOR-ASSY;,12P,500MM,35155-120	
...3	CN902	3711-003043	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
⚠ ...3	CR405S	2301-001343	C-FILM,MPPF;3.9nF,5%,2kV,TP,29x9.5x16mm,	
⚠ ...3	CR406S	2301-001343	C-FILM,MPPF;3.9nF,5%,2kV,TP,29x9.5x16mm,	
⚠ ...3	CR407S	2301-001398	C-FILM,MPPF;3.3nF,5%,2kV,TP,29x8.5x1.5mm	
⚠ ...3	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	

Level	Loc. No.	Code No.	Description ; Specification	Remark
...3	CX802S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
...3	CY802S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
...3	D801S	AA96-00276C	ASSY H/S;-,BRIDGE ,AA62-00052A,GSIB660,K	S.N.A
....4		AA62-00052A	HEAT SINK-PS;-,-,-,SILVER,HOLE 18.5mm, 2	S.N.A
....4		AA60-30003A	WASHER;T1.5,SBHG-1	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		0402-001399	DIODE-BRIDGE;GSIB660,600V,6A,SIP-4,BK	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	FP801S	3601-000297	FUSE-CARTRIDGE;250V,5A,TIME-LAG,GLASS,5.	
...3	GT804S	AA39-20010C	LEAD CONNECTOR-ASSY;,1P600,YFH800-01,S,	
...3	HC401	BP96-00159A	ASSY HEAT SINK P;H/S,SCREW,FJL6920,FMP-3	S.N.A
....4	CIS	AA60-30001A	WASHER-PLATE;M3,ID3.5,15X8.5,T1.0,SBHG	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	BP62-00015A	HEAT SINK-PS;WT-36Z4HR,A1050S,T2.0,86,80	S.N.A
....4	CIS	BH73-00028B	SILICON/RUBBER-HS;TV ALL,SILICON,26*30*T	S.N.A
....4	CIS	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	CIS	0502-001230	TR-POWER;FJL6920YDTU,N,200000MW,TO-264 F	
....4	CIS	0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	
...3	HC801	AA96-00475A	ASSY H/S;-,REGULATOR,AA62-00066B,FML-G12	S.N.A
....4		AA62-00066B	HEAT SINK;D2,D3,AL ,T1.0,89,70,-,AA62-00	S.N.A
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
....4		0402-001230	DIODE-RECTIFIER;FMG-G2CS,1000V,3A,TO-220	
....4		0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	IC301	AA96-50381A	ASSY H/S;-,-,AA62-30180B,LA7845,-	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1204-000517	IC-VERTICAL DEF.;LA7845,SIP,7P,-,PLASTIC	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30180B	HEAT SINK-ES;-,A6063 EXTR.,2,WHT,70MM,-,	S.N.A
...3	IC401	1202-000103	IC-VOLTAGE COMP.;393,DIP,8P,300MIL,DUAL,	
...3	IC601	1204-001971	IC-SOUND PROCESSOR;MSP3411G-P0-B11,DIP,5	
...3	IC602	AA96-50369D	ASSY H/S;-,SOUND,AA62-30181F,TDA7269,HER	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1201-001385	IC-POWER AMP;7269A,ZIP,11,19.6,DUAL,13,P	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30181F	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
...3	IC801S	AA96-50371H	ASSY H/S;-,SMPS,AA62-30181H,5Q1565RF,HER	S.N.A
....4		AA61-11028A	BRACKET;-,SECC,T1.0,-,-,-,-	S.N.A
....4		AA62-30181H	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		1203-002512	IC-PWM CONTROLLER;KA5Q1565RF-YDTU,TO-3PF	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	IC803	1203-001225	IC-POSI.FIXED REG.;78R09,TO-220,4P,-,PLA	
...3	IC805	AA96-00243K	ASSY H/S;-,REGULATOR,AA62-000450A,KA78R0	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
....4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
...3	IC901	AA09-00041A	IC MICOM;,SDA555X-OTP,3.3V,-,128K,SDIP,-	S.N.A
...3	IC902	1103-001177	IC-EEPROM;24WC16,2048x8Bit,DIP,8P,-,-,2.	
...3	JA701	3722-001884	JACK-SCART;42P,-,SNPB,BLK,-	
...3	JA702	3722-001767	JACK-PIN;2P(9P),-,NI,WHI/RED,-	
...3	L808	AA27-00098A	COIL CHOKE;-,-,24uH,10%,-,0.1,3.0A,DR10X	
...3	LR402S	AA27-10004F	COIL CHOKE;-,56uH,K,-,2.5A,BK,-,DR12x15,	
...3	LR403S	AA27-00070A	COIL LINEARITY;-,7uH,YL81 DR1518,11mm,17	
...3	LR404S	AA27-40001S	COIL HORIZ. WIDTH;-,110uH,SB-5S8202.6,PI	
...3	LR405S	AA27-00057A	COIL HORIZ. WIDTH;-,10mH,YL-9N 15x27.5 C	
...3	LX801S	AA29-30002N	FILTER LINE NOISE;-,16MH,1.5A,AC100~260V	
...3	LX802S	AA29-30002N	FILTER LINE NOISE;-,16MH,1.5A,AC100~260V	
...3	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
...3	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
...3	PT801S	1404-001026	THERMISTOR-PTC;7ohm,20%,-,290V,25A,-,ST	
...3	Q402	0505-001116	FET-SILICON;BUZ73A,N,200V,22A,0.6ohm,40W	
...3	Q804	BH99-00007S	ASSY HEAT/SINK;KSC2073,MICOM,HERCULES,BH	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	0502-001007	TR-POWER;KSC2073-H2,NPN,25W,TO-220,ST,6	
....4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
....4	CIS	BH62-00007A	HEAT SINK-TR;-,T1.0,L20*H30,CDA	S.N.A
...3	RL801S	3501-001053	RELAY-POWER;5Vdc,530mW,10A,1FormA,15mS,5	
...3	T401	AA26-50001S	TRANS-HORIZ.DRIVE;-,-,-,6.0mH,-,-,44uH,-	
...3	T444S	AA26-00170A	TRANS FBT;FUJ-29H002F,29F,1.95MH,FERRIT	
...3	T801S	AA26-00178A	TRANS SWITCHING;EER5345,K55A,PAL,CIS,160	
...3	TU01S	AA40-00096A	TUNER;TCLS3101PD16A(N),PAL,181CH,38.9MHZ	
...3	X601	2801-004020	CRYSTAL-UNIT;18.432MHz,30ppm,28-AAM,12pF	
...3		AA95-03091B	ASSY SUB-PCB,FEATURE BOX;,K55A, ,PAL	
....4	BR01	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4	BR02	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4	CN01	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4	CN02	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4	CN03	3711-003601	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,ANGLE,	
....4	DC41	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
....4	DC51	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	DX01	2802-001177	RESONATOR-CERAMIC;2.696MHZ,0.4%,BK,10X4.	
....4	EC48	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	EC49	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	EX01	2801-004019	CRYSTAL-UNIT;20.25MHz,30ppm,28-AAM,13pF,	
....4	IC06	1203-002000	IC-VOL. DETECTOR;7027,TO-92,3P,-,PLASTIC	
....4		AA97-13629A	ASSY SMD;,K55A, ,PAL,	S.N.A
.....5	DC01	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5	DC02	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5	DC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC04	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC05	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC06	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....5	DC07	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5	DC08	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC09	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,	
.....5	DC10	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC12	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC13	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC14	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC17	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC19	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC20	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC21	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC22	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC23	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....5	DC24	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC25	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC26	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC27	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC28	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC29	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC30	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC31	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC32	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	DC33	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC34	2203-000896	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
.....5	DC35	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	DC36	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5	DC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC39	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	DC40	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5	DC43	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC45	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	DC49	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	DC52	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	DD01	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD02	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD03	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD04	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD05	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD06	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD07	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD08	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD09	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD10	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD11	0403-000746	DIODE-ZENER;RLZ3.9B,3.89-4.16V,500MW,LL-	
.....5	DD13	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD14	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD15	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD16	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD17	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD18	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD19	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD20	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	DL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	DL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	DL03	2703-001070	INDUCTOR-SMD;100uH,10%,4.5x3.2x3.2mm	
.....5	DQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ02	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ03	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ04	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ05	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ07	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ08	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ09	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
.....5	DQ10	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ11	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR05	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR06	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR08	2007-000691	R-CHIP;3.3Mohm,5%,1/16W,DA,TP,1608	
.....5	DR09	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR10	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR13	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5	DR14	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5	DR15	2007-000869	R-CHIP;4.7Kohm,1%,1/16W,DA,TP,1608	
.....5	DR16	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR17	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR18	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR19	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR23	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP,1608	
.....5	DR24	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
.....5	DR25	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5	DR26	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR27	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....5	DR28	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....5	DR29	2007-000118	R-CHIP;390ohm,5%,1/16W,DA,TP,1608	
.....5	DR30	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR31	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR32	2007-000081	R-CHIP;2.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR33	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5	DR34	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR36	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR37	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR38	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR39	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR40	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....5	DR41	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....5	DR42	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR43	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR44	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR45	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR46	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR47	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR49	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR50	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR51	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR52	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR53	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR54	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR55	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR56	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR57	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR58	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR59	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR60	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR61	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR62	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR63	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR64	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR65	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR66	2007-000088	R-CHIP;7.5Kohm,5%,1/16W,DA,TP,1608	
.....5	DR68	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR69	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR70	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR80	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR81	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
.....5	DR82	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
.....5	DR86	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR87	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR88	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	EC01	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC02	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC04	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	EC08	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC09	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC10	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC12	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC13	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC14	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC15	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC17	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC18	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC19	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC20	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC21	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC22	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC23	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC24	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	EC29	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC30	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC31	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC32	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC33	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC34	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
.....5	EC35	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
.....5	EC36	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC39	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC40	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC41	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC42	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC43	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC44	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC45	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC46	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC47	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	EC51	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	EC52	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC53	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC54	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC55	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC56	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC57	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	EC58	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	EC59	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC60	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC62	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC63	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC64	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC65	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EL04	3301-001082	CORE-FERRITE BEAD;AB,600HM,3.2X2.5X1.3MM	
.....5	EL05	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EL06	3301-001324	CORE-FERRITE BEAD;AB,150HM,2X1.25X0.9MM,	
.....5	EL07	3301-001324	CORE-FERRITE BEAD;AB,150HM,2X1.25X0.9MM,	
.....5	EL08	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EL09	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EL13	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EQ04	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....5	EQ05	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....5	EQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	ER01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER02	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	ER06	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5	ER07	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5	ER09	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	ER13	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER16	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER19	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	ER21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	ER22	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER24	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER25	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER26	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER29	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	ER30	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	ER31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	ER32	2007-000293	R-CHIP;1000HM,5%,1/8W,DA,TP,3216	
.....5	ER33	2007-000293	R-CHIP;1000HM,5%,1/8W,DA,TP,3216	
.....5	ER34	2007-000293	R-CHIP;1000HM,5%,1/8W,DA,TP,3216	
.....5	ER35	2007-000293	R-CHIP;1000HM,5%,1/8W,DA,TP,3216	
.....5	ER36	2007-000293	R-CHIP;1000HM,5%,1/8W,DA,TP,3216	
.....5	IC01	1204-001950	IC-VIDEO DECODER;VSP9405B,QFP,80P;-,PLAS	
.....5	IC04	1204-001989	IC-VIDEO PROCESS;CXA2165Q,QFP,64P,20X14M	
.....5	IC05	1203-002186	IC-POSI.FIXED REG.;18,DPAK,3P,240MIL,PLA	
.....5	IC10	1001-001177	IC-VIDEO SWITCH;TEA6425D,VIDEO SWITCH ,S	
.....5	IC11	0801-000662	IC-CMOS LOGIC;74HC123,MULTIVIBATOR,SOP,1	
.....5	PCB	AA41-00644B	PCB-PAL FERTURE BOX;CS29Z6,FR-4,4L,B,1.6	S.N.A
.....5	SC29	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SC31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SC33	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SC43	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	SC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	SC47	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5	SC48	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5	SC49	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	SL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	SR09	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	SR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	SR11	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	SR30	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR32	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR33	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR34	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	SR36	2007-000259	R-CHIP;1.6Kohm,5%,1/16W,DA,TP,1608	
.....5	SR37	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5	TC01	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC02	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC03	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC04	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC05	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC06	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC07	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	TC08	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	TD01	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	TL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	TQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	TQ02	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	TR01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	TR03	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	TR05	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR07	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	TR08	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR09	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	TR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3		AA39-00191A	LEAD CONNECTOR-ASSY;,4P,1100/500MM,35155	
...3		AA97-12467C	ASSY AUTO-MAIN;Z4,K55A,RUSSIA	S.N.A
.....4	C101	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....4	C102	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....4	C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....4	C104	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
.....4	C105	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....4	C106	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....4	C107	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....4	C108	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
.....4	C109	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
.....4	C110	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
.....4	C111	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....4	C112	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....4	C113	2202-000216	C-CERAMIC,MLC-AXIAL;0.027NF,5%,50V,SL,TP	
.....4	C116	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....4	C201	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....4	C202	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
.....4	C203	2202-000106	C-CERAMIC,MLC-AXIAL;1.5nF,20%,16V,Y5P,TP	
.....4	C204	2202-000106	C-CERAMIC,MLC-AXIAL;1.5nF,20%,16V,Y5P,TP	
.....4	C206	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....4	C207	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....4	C239	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....4	C240	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....4	C302	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
.....4	C303	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
.....4	C304	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
.....4	C305	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
.....4	C306	2301-000160	C-FILM,PEF;12nF,5%,50V,TP,11.0x6.0x9.0mm	
.....4	C307	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
.....4	C308	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
.....4	C401	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
.....4	C402	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
.....4	C403	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
.....4	C404	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
.....4	C408	2301-001143	C-FILM,PPF;56nF,5%,400V,TP,20x10x17,7.5	
.....4	C409	2301-001385	C-FILM,PPF;30nF,5%,630V,TP,20x15.5x10.5,	
.....4	C411	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
.....4	C412	2301-000254	C-FILM,PEF;39nF,5%,50V,TP,7.5x3.5x6.5mm,	
.....4	C413	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
.....4	C414	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
.....4	C415	2301-000203	C-FILM,PEF;2.7nF,5%,100V,TP,7x3.0x6.5mm,	
.....4	C416	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....4	C417	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....4	C418	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
.....4	C420	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
.....4	C421	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
.....4	C422	2401-001527	C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
.....4	C424	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
.....4	C425	2301-001259	C-FILM,MPPF;100nF,5%,400V,TP,19x8x16,7.5	
.....4	C432	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....4	C601	2201-000558	C-CERAMIC,DISC;0.47NF,10%,50V,Y5P,TP,5X3	
.....4	C602	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
.....4	C603	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....4	C604	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
.....4	C605	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....4	C606	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....4	C607	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....4	C608	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....4	C610	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....4	C611	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....4	C612	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
.....4	C613	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
.....4	C614	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....4	C615	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....4	C619	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....4	C620	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....4	C621	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....4	C622	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....4	C623	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....4	C624	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....4	C625	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....4	C626	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....4	C627	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....4	C628	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....4	C629	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....4	C630	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....4	C631	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....4	C632	2201-000370	C-CERAMIC,DISC;0.22NF,10%,50V,Y5P,TP,4X3	
.....4	C633	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....4	C634	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
.....4	C635	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	C636	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C637	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C638	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C639	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C640	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C641	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C642	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C643	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C644	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
....4	C645	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C646	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C647	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
....4	C648	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
....4	C649	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm	
....4	C650	2401-001176	C-AL;33uF,20%,25V,GP,TP,5x11,5	
....4	C651	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C652	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C653	2401-002216	C-AL;2200uF,20%,35V,GP,TP,16x25,7.5	
....4	C654	2201-000611	C-CERAMIC,DISC;0.056NF,5%,50V,C0G,TP,7X3	
....4	C655	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	C656	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
....4	C657	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
....4	C658	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C659	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C660	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C701	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
....4	C801	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
....4	C802	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
....4	C804	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
....4	C805	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
....4	C807	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.	
....4	C808	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
....4	C809	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	C810	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C811	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	C812	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C813	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.	
....4	C814	2201-002028	C-CERAMIC,DISC;0.47NF,10%,2KV,Y5P,TP,7.5	
....4	C816	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
....4	C817	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C818	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4	C819	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C821	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	C822	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C823	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	C824	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
....4	C825	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C826	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
....4	C827	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4	C828	2201-000374	C-CERAMIC,DISC;0.22NF,5%,50V,C0G,TP,10.5	
....4	C830	2201-000984	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
....4	C831	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C832	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
....4	C833	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4	C834	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
....4	C835	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4	C836	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C837	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C838	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
....4	C840	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
....4	C841	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
....4	C843	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C844	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C901	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C902	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C903	2202-000719	C-CERAMIC,MLC-AXIAL;6.8nF,20%,16V,Y5R,TP	
....4	C904	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C905	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C906	2202-000791	C-CERAMIC,MLC-AXIAL;150pF,10%,50V,Y5P,TP	
....4	C907	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
....4	C909	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
....4	C910	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
....4	C911	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
....4	C912	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C913	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C914	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C915	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C916	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C917	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C918	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
....4	C919	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C920	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C921	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C922	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C923	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C924	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C925	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C927	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	CN302	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
....4	CN601	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
....4	CN901	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
....4	CW901	2503-000156	C-NETWORK;100pFx4,20%,50V	
....4	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D202	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D207	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4	D401	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 4	D402	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4	D403	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D404	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4	D405	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D406	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D408	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4	D409	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
⚠ 4	D410	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D411	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
....4	D603	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D607	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D801	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 4	D802	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 4	D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4	D804	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4	D805	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D808	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D812	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D816	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D901	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D902	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D903	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D904	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D907	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4	DZ302	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ303	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ304	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
....4	DZ305	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ306	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ307	0403-001118	DIODE-ZENER;MTZ30A,32V,26.99-28.39V,500m	
....4	DZ401	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
....4	DZ402	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DZ404	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ601	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ602	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ603	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ604	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ605	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ606	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ607	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	DZ608	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	DZ801	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ802	0403-000716	DIODE-ZENER;MTZJ4.7B,4.7V,4.55-4.8V,500m	
....4	DZ803	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
....4	DZ804	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
....4	DZ807	0403-001330	DIODE-ZENER;MTZJ30A,26.99-28.39V,500mW,D	
....4	DZ808	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ902	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ906	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ907	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ908	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ909	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	DZ910	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ911	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ912	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	EL201	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL202	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL203	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL204	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL401	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL402	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL407	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL408	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL805	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL806	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL807	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL808	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY302	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY303	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY403	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY404	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY405	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY406	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY407	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY408	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY409	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY410	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY411	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY412	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY413	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY414	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY415	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY417	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY418	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY419	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY420	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY421	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY422	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY423	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY424	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY425	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY426	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY429	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY430	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY431	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY432	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY433	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY434	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY435	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY436	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY437	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY439	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY441	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY446	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY447	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY603	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY604	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY701	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY702	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY703	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY704	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY705	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY706	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY801	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY802	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY803	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY804	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY805	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY806	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY809	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY810	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY811	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY812	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY813	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY814	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY815	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY816	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY817	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY820	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY824	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY825	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY828	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY829	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY830	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY831	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY832	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY833	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY835	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY836	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY837	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY838	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY839	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY840	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY841	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY842	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY844	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY845	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY846	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY848	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY850	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY851	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY853	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY854	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY855	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY856	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY857	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY858	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY859	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY860	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY861	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY862	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY864	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY865	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY871	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY872	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
⚠ 4	FA801S	3601-000120	FUSE-AXIAL LEAD;125V,2.5A,FAST-ACTING,GL	
⚠ 4	FA802S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
⚠ 4	FA803S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
....4	GT102	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT301	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT302	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT401	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT402	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT404	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT405	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT406	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT409	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT410	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT411	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT412	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT807	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	HIC401	AA13-00094A	IC HYBRID:-,DDRI001A,SIP,5P,-,TP	
....4	IC202	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
⚠ 4	IC402	1203-000243	IC-POSI.FIXED REG.;7812A,TO-220,3P,-,PLA	
....4	IC804	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
....4	IC903	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
....4	IC904	1203-001943	IC-VOL. DETECTOR;7025,TO-92,3P,-,PLASTIC	
....4	J709	2001-000376	R-CARBON;150HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	L101	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
....4	L103	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	L104	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
....4	L106	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	L201	2701-000200	INDUCTOR-AXIAL;5.6uH,10%,4.2x9.8mm	
....4	L203	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L402	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
⚠ 4	L403	2701-001040	INDUCTOR-AXIAL;10uH,10%,4.5x14mm	
....4	L404	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L407	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L409	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L410	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4	L601	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L602	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
....4	L603	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L604	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L605	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L606	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L607	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L608	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L609	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L610	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L612	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L613	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L614	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L615	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L703	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L704	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L705	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L706	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L801	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L802	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L803	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L804	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L805	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L806	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L807	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4	L809	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L811	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
....4	L901	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L902	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
....4	L903	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L904	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L906	2701-000215	INDUCTOR-AXIAL;8.2uH,10%,2.5x3.4mm	
....4	L907	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L908	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
....4	L909	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
....4	PCB	AA41-00707B	PCB-MAIN;CS29Z6HP,FR-1,1L,B,1.6T,330X245	S.N.A
....4	Q404	0505-000156	FET-SILICON;IRF620,N,200V,5A,0.8ohm,50W,	
....4	Q601	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q603	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q801	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q802	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
....4	Q803	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q901	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q906	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q907	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q908	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q909	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4	Q910	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4	Q912	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q913	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q914	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	R101	2001-000938	R-CARBON;680HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R102	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R103	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R104	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R105	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R106	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R107	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R108	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R203	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R204	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R301	2001-001163	R-CARBON(S);560OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R302	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R303	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4	R304	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm	
....4	R305	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
....4	R306	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
....4	R307	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm	
....4	R308	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R309	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R310	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R314	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R315	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R316	2001-001129	R-CARBON(S);330KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R317	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R401	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R402	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R403	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
....4	R405	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
....4	R409	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
....4	R410	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
....4	R411	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R412	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
....4	R413	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
....4	R414	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
....4	R415	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R416	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R418	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R419	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R420	2004-001987	R-METAL(S);4.3Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R421	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R422	2008-000251	R-FUSIBLE(S);0.27ohm,5%,2W,AF,TP,3.9x10m	
....4	R423	2001-001055	R-CARBON(S);1.8KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R424	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
....4	R425	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
....4	R426	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
....4	R428	2004-000698	R-METAL;3.3Kohm,1%,1/4W,AA,TP,2.4x6.4m	
....4	R430	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
....4	R431	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
....4	R432	2001-001164	R-CARBON(S);56KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R433	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
....4	R434	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
....4	R435	2003-001042	R-METAL OXIDE(S);5.6Kohm,5%,2W,AF,TP,3.9	
....4	R440	2004-001893	R-METAL(S);22Kohm,1%,1/2W,AA,TP,2.5x6.5m	
....4	R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R602	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R603	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R604	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R605	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R606	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R607	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R608	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R609	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R612	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R613	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R614	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R615	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R616	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R617	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R618	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R623	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R624	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R626	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R627	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R628	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R629	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R630	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R631	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R632	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R633	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R634	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R635	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R636	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R637	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R638	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R639	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R704	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R710	2001-000376	R-CARBON;150HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R715	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R716	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R717	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	R718	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R723	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R801	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R802	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4	R803	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4	R804	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4	R805	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R806	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R807	2001-001103	R-CARBON(S);20KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R808	2001-001197	R-CARBON(S);910OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R809	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R810	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R811	2001-001155	R-CARBON(S);5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R812	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R813	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R815	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
....4	R816	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R817	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R818	2001-001131	R-CARBON(S);33KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R819	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R820	2001-001096	R-CARBON(S);2.2OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R821	2004-001891	R-METAL(S);133Kohm,1%,1/2W,AA,TP,2.5x6.5	
....4	R822	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R823	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R824	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R827	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
....4	R828	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm	
....4	R829	2008-001148	R-FUSIBLE;3.3OHM,5%,1W,AG,TP,3.9X12MM	
....4	R830	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
....4	R833	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R835	2003-002181	R-METAL OXIDE(S);68Kohm,5%,2W,AG,TP,3.9x	
....4	R838	2001-001050	R-CARBON(S);1.5KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R840	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R841	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R842	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R901	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R902	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R903	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R904	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R905	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R906	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R907	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R908	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R909	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R910	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R911	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R912	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R913	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R914	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R915	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R916	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R917	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R919	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R920	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R921	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R922	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R923	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R924	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R925	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R926	2001-000793	R-CARBON;470HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R927	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R928	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R935	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R936	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R937	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R938	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R940	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R941	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R942	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R945	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R946	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R947	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R948	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R951	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R952	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R953	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R954	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R955	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R958	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R960	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R961	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R962	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R963	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R965	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R966	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R967	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R968	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R972	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R973	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R974	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R981	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R982	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R983	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R984	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R988	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 4	RR430S	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
⚠ 4	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ 4	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
....4	X901	2801-003728	CRYSTAL-UNIT;6MHz,30ppm,28-AAM,20pF,40oh	
...3		AA39-20536G	LEAD CONNECTOR-ASSY;,1P,60MM,F,F,1617#22	
...3		AA61-00707B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
..2		AA94-12356A	ASSY PCB MISC-A/V SIDE;Z4,K55A,PAL	
...3	CN701	AA39-00317B	LEAD CONNECTOR-ASSY;K55A/WT-32Z4HD,UL100	
...3	CN703	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,500,YBNH025-05,6	
...3	CN704	AA39-00070A	LEAD CONNECTOR-ASSY;,4P,200MM,YBNH250-04	
...3	JA701	3722-001031	JACK-PIN;3P,3.6mm,#18,AU	
...3	JH701	3722-000143	JACK-PHONE;1P(VER),3.4PI,AG,BLK,NO	
...3	JS701	3722-001163	JACK-VHS;4P,12mm,AU,BLK,N	
...3		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
...3		AA97-13518A	ASSY AUTO-A/V SIDE;Z4,K55A,PAL	S.N.A
....4	C701	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C702	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C707	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C708	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	DZ701	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500m	
....4	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L703	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L705	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L706	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L707	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L708	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	PCB	AA41-00616B	PCB-A/V SIDE(Z4);CT-29Z4HRH,FR-1,1L,B,1.	S.N.A
....4	R701	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R702	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
...3		AA61-60109D	SPRING ETC-DOOR;32W8,SUS304L,-,-,-,-,-,-	S.N.A
...3		AA61-00545A	HOLDER-AV,HOUSING ASSY;32Z5,ABS,-,-,-,GR	S.N.A
....4		6003-001070	SCREW-TAPTITE;BH,+,B,M2,L4,ZPC(BLK),SWRC	S.N.A
....4		AA61-00453B	HOLDER-AV,HOUSING;32Z5,ABS,-,-,-,GRAY,HB	S.N.A
....4		AA61-30001A	LATCH-DOOR;-,-,-,-,-,-,-,KIFUCO LA701	
....4		AA61-80002A	DAMPER-GEAR;-,DP802,-,-,-,-,BLU,DP802	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA61-00451F	HOLDER-AV;32Z5,HIPS,GR503,FV2	S.N.A
...3		AA61-00544G	HOLDER-AV,COVER ASSY;Z4,ABS,GRAY,HB K55A	S.N.A
....4		AA61-00452B	HOLDER-AV,COVER;32Z5,ABS,-,-,-,GRAY,HB	S.N.A
....4		AA64-01204E	INLAY-SIDE,AV;32Z4,PS SHEET,T0.3,KS3A PA	S.N.A

ASSY CPT

1		AA91-03134A	ASSY CPT;CT-29Z4HR	S.N.A
..2		AA91-02173Q	ASSY CPT;A68QCP891X004,29,+380MG,ITC,CT	S.N.A
⚠ ...3		AA03-00076A	CRT COLOR;A68QCP891X004(C),+380mG,0.315m	
..2		AA98-70011D	ASSY TBC WIRE(P);-,29',NTSC,PAL,2P-WH,-	S.N.A
..2		AA27-00128A	COIL DEGAUSSING;-,-,-,-,50T,7,-,29inch,2	

ASSY COVER FRONT

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA90-04193D	ASSY COVER FRONT;CS29Z4HNGX/BWT	S.N.A
..2	BRK+CF	6002-000522	SCREW-TAPPING;TH,+,2,M4,L15,ZPC(BLK),SWR	S.N.A
..2	CB+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CB+TBA	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CRT+CF	AA60-10050V	SCREW-ASSY;-,SWRCH18A,M6,L30,HH,+,WC,-,Z	S.N.A
..2	D-COIL	AA65-00019A	CLAMPER CORE-D,COIL;25-34,NYLON 66,V2,N	S.N.A
..2	DR+CF	6002-000522	SCREW-TAPPING;TH,+,2,M4,L15,ZPC(BLK),SWR	S.N.A
..2	HP+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	KC+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	TB+RCA	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2		AA91-00748P	ASSY CABINET FRONT;,CS29Z4,SV012P K55A C	
...3	SPK+CF	6006-001096	SCREW-ASS'Y TAPT;WP,BH,+,M4.0,L12,BLK,SW	S.N.A
...3	WIN+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
...3		AA64-03210A	KNOB-POWER;Z4,ABS,HB,WHT,SVM3012	
...3		AA64-03211A	WINDOW-REMOCON;Z4,PC,VIOLET	S.N.A
...3		AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA91-00738A	ASSY HOLDER SPK;-,PP,8OHM,10W,-,ZEUS-2 F	
...3		AA64-01973F	CABINET-FRONT;29Z4,HIPS,HB,G4309,SV012P	S.N.A
...3		AA64-01203B	INDICATOR LED;32Z5,ACRYL,-,CLR,-,-,-	
...3		AA64-01062B	BADGE-BRAND;32Z5,AL FORGING,-,-,L65,-,SI	S.N.A
...3		AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A
..2		AA61-01222A	HOLDER-CAP;,DAHC-30 PE	S.N.A
..2		AA65-30017A	CLAMPER CORE-D,COIL;-,NYLON-66,V0,-,NTR,	S.N.A
..2		AA63-60004Y	SPACER-GUM,CRT;ALL MODEL,NTR RUBBER,-,-,	S.N.A
..2		AA61-10054A	BRACKET-CRATER;6277,STS304,T0.5,-,-,-,-	S.N.A

ASSY COVER REAR

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA90-02041T	ASSY COVER REAR;CS29Z4HNGX/BWT	S.N.A
..2	CABBAC	AA60-00091J	SPACER-FELT;-,FELT,330X10,-,-,BLK,T0.5,-	S.N.A
..2		AA63-00463A	COVER-WOOFER;TOOL,34Z4,-,-,-,-,-,-,MOLD	S.N.A
..2		AA64-01976B	CABINET BACK;29Z4,HIPS,FV2,GR503	
...3		AA61-20129C	HOLDER-WIRE;29Z4,NYLON-66,GRAY,DAFC-2500	S.N.A
..2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A

ASSY ACCESSORY

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA92-06199A	ASSY ACCESSORY;29Z6,RUSSIA,K55A	S.N.A
..2	1	AA68-02479A	MANUAL USERS;CS29Z7HP,RUS,K55A,PIP,TTX	
..2		6801-001073	CARD-REGISTRATION;RUS,XEV,RUS,MOJO100,-,	S.N.A
..2		AA59-00266D	REMOCON;TM63,HERCULES,45,SAMSUNG,EX,RUSS	
...3		2802-000194	RESONATOR-CERAMIC;8MHz,1.0%,TP,8.5x4.5x5	
...3		AA09-00275A	IC MICOM;Z86L8808SSC-R51PX,SOP,ST,SZTM-8	
..2		AA68-00952A	CARD-COUPON;-,A/P100(G),AA68-00949A,-,-,	S.N.A
..2		AA69-00862A	BAG PE;-,HDPE PE FOAM,T0.03,W400,H240,-,	S.N.A
..2		AA68-01402A	MANUAL-GOOD WILL LETTER;,CIS,B5,1PAGE,A/	S.N.A
..2		AA68-01120A	MANUAL SERVICE;-,-,CIS,A4,6PAGE(FOLD),W/	S.N.A
..2		AA68-00816B	CARD WARRANTY-01;,RUSSINA,2,W/P 120G,BOT	S.N.A

ASSY P/MATERIAL

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA92-03130A	ASSY P/MATERIAL;CS29Z4HF9X/BOB	S.N.A
..2		AA69-00744F	BAG-SHEET;-,HDPE PE FOAM,T0.015,W1400,H1	S.N.A
..2		AA69-00306A	BAG AIR;LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A
..2		AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,	S.N.A
..2		AA63-10007C	BAND-PP;W18,CLEA,1G	S.N.A
..2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A

7-5 CS34Z4HNGX/BWT

ASSY CHASSIS

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA91-05665F	ASSY CHASSIS;34Z4,K55A,PAL CIS	S.N.A
..2	C-BLOC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2	D-FOCU	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2	MP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2	PCB	AA61-00706B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
..2	TBA+HC	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2	WP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2		AA96-00908E	ASSY COVER P-TERMINAL BOARD;29Z6,CIS,HIP	
...3		AA64-02823A	INLAY-T/BOARD;Z7,PS SHEET,T0.5,PAL	S.N.A
...3		AA65-00025A	TERMINAL-BOARD,ANT;,HIPS V0,BLK	S.N.A
..2		AA94-12358A	ASSY PCB MISC-LED;Z4,K55A,PAL	
...3	CNY01	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,500,YBNH025-05,6	
...3	LDY01	0601-001381	LED;ROUND,RED/GRN,5.0MM,650/563NM	
...3	RMY01	AA32-00005A	MODULE REMOCON;VISHAY,10,700~850,-,-,ST	
...3		AA97-13495A	ASSY AUTO-LED;Z4,K55A,PAL	S.N.A
....4	CY01	2401-002291	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	
....4	DZY01	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZY02	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	PCB	AA41-00520B	PCB-LED;CS32Z4/29Z4,FR-1,1L,B,1.6T,245X2	S.N.A
....4	RY01	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA94-12357A	ASSY PCB MISC-CONTROL;Z4,K55A,PAL	
...3	CNY01	AA39-00100D	LEAD CONNECTOR-ASSY;,4P,700MM,YBNH250-04	
...3	PCB+KC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
...3	SWY01	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY02	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY03	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY04	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY05	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY06	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-13519A	ASSY AUTO-CONTROL;Z4,K55A,PAL	S.N.A
....4	DZY03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZY04	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	LY01	2701-000136	INDUCTOR-AXIAL;18uH,10%,2.5x3.4mm	
....4	LY02	2701-000136	INDUCTOR-AXIAL;18uH,10%,2.5x3.4mm	
....4	PCB	AA41-00522A	PCB-CONTROL;CS32Z4,FR-1,1L,A,1.6T,245X24	S.N.A
....4	RY02	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY03	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY04	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY05	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY06	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3		AA64-03209A	KNOB-CONTROL;Z4,ABS,HB,WHT,SVM3012	S.N.A
⚠ ..2		AA96-20130H	ASSY POWER CORD;-,CP2/NO(4.0R),H/S 500MM	S.N.A
...3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3		AA39-10003B	CBF POWER CORD;-,KJP-140,KLCE-2F,2.4m,HO	
...3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A
..2		AA95-01863A	ASSY SUB-PCB-MASTER;WS36Z48D,KS4A,PAL,AA	
...3	CN811	AA39-20179C	LEAD CONNECTOR-ASSY;,3(2)P,600MM,YFH800-	
...3	HP+PCB	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
...3	MPP+LP	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
⚠ ...3	SW811S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
...3		AA97-05539A	ASSY AUTO-MASTER;WS36Z48D,KS4A,PAL	S.N.A
....4	EY01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY03	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY04	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	GTY05	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY06	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY07	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY08	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY09	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY10	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	PCB	AA41-00521A	PCB-MASTER S/W;CS32Z4,FR-1,1L,A,1.6T,245	S.N.A
...3		AA61-00450B	HOLDER-POWER;32Z5,ABS,-,-,-,GRAY,HB	S.N.A
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA65-00011B	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
..2		AA61-01190A	HOLDER-CHASSIS;Z7,HIPS V0,G4309	S.N.A
..2		AA94-07792A	ASSY PCB MISC-DYNAMIC FOCUS;CT-29Z7HR,K5	
...3	LH01	AA26-90002C	TRANS-DUMMY;-,-,-,-,-,-,-,-,-,-,-,EER2	
...3	LH02	AA27-40003L	COIL HORIZ. WIDTH;-,1.0mH,DR14x20,2UEW0.	
...3	RH28	2008-001113	R-FUSIBLE(S);0.22ohm,10%,2W,AG,TP,3.9x12	
...3	WIRE3	AA39-20061C	LEAD CONNECTOR-ASSY;,3P,200,YFH800-03,S,	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-07229L	ASSY AUTO-DYNAMIC FOCUS;CT-29Z7HR,K55A	S.N.A
....4	EY01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY03	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY04	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY05	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY06	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY07	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY08	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY09	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	GTH01	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTH02	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTH03	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	PCB	AA41-00152C	PCB-DOUBLE FOCUS;CW29A6VN8X/XEF,FR-1,1L,	S.N.A
..2		AA94-12047E	ASSY PCB MAIN;CS34Z4HNGX/BWT,K55A	
...3	C-BLOC	AA26-00069A	TRANS FBT;FUJ-29C002C(S),DREAM3,4,-,-,-	
...3	C423	2301-001193	C-FILM,MPPF;1uF,5%,400V,TP,31x17x25,20	
...3	C425	2306-000273	C-FILM,MPPF;82nF,5%,400V,BK,19x15.5x7,15	
...3	C426	2306-000172	C-FILM,MPPF;270nF,5%,400V,BK,26.5x19mm,2	
...3	C803	2401-002227	C-AL;330uF,20%,450V,GP,BK,35x45,10	
...3	C806	2306-000112	C-FILM,MPPF;100nF,20%,250V,BK,-,15mm	
...3	C815	2401-003024	C-AL;220uF,20%,200V,WT,TP,22x35,10	
...3	C820	2401-003419	C-AL;2200uF,20%,50V,WT,TP,16X35.5mm	
...3	CN502	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3	CN702	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	CN702A	AA39-00114C	LEAD CONNECTOR-ASSY;,12P,500MM,35155-120	
...3	CN902	3711-003043	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
⚠ ...3	CR405S	2301-001583	C-FILM,PPF;3NF,5%,2KV,TP,25X13X7MM,20	
⚠ ...3	CR406S	2301-001583	C-FILM,PPF;3NF,5%,2KV,TP,25X13X7MM,20	
⚠ ...3	CR407S	2301-001398	C-FILM,MPPF;3.3nF,5%,2kV,TP,29x8.5x1.5mm	
⚠ ...3	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ ...3	CX802S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ ...3	CY802S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
⚠ ...3	D801S	AA96-00276C	ASSY H/S;-,BRIDGE ,AA62-00052A,GSIB660,K	S.N.A
....4		AA62-00052A	HEAT SINK-PS;-,-,-,-,SILVER,HOLE 18.5mm, 2	S.N.A
....4		AA60-30003A	WASHER;T1.5,SBHG-1	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		0402-001399	DIODE-BRIDGE;GSIB660,600V,6A,SIP-4,BK	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
⚠ ...3	FP801S	3601-000297	FUSE-CARTRIDGE;250V,5A,TIME-LAG,GLASS,5.	
⚠ ...3	GT804S	AA39-20010C	LEAD CONNECTOR-ASSY;,1P,600,YFH800-01,S,	
...3	HC401	BP96-00159A	ASSY HEAT SINK P;H/S,SCREW,FJL6920,FMP-3	S.N.A
....4	CIS	AA60-30001A	WASHER-PLATE;M3,ID3.5,15X8.5,T1.0,SBHG	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	BP62-00015A	HEAT SINK-PS;WT-36Z4HR,A1050S,T2.0,86,80	S.N.A
....4	CIS	BH73-00028B	SILICON/RUBBER-HS;TV ALL,SILICON,26*30*T	S.N.A
....4	CIS	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	CIS	0502-001230	TR-POWER;FJL6920YDTU,N,200000MW,TO-264 F	
....4	CIS	0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	
...3	HC801	AA96-00475A	ASSY H/S;-,REGULATOR,AA62-00066B,FML-G12	S.N.A
....4		AA62-00066B	HEAT SINK;D2,D3,AL ,T1.0,89,70,-,AA62-00	S.N.A
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
....4		0402-001230	DIODE-RECTIFIER;FMG-G2CS,1000V,3A,TO-220	
....4		0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	IC301	AA96-50381A	ASSY H/S;-,-,AA62-30180B,LA7845,-	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1204-000517	IC-VERTICAL DEF.;LA7845,SIP,7P,-,PLASTIC	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30180B	HEAT SINK-ES;-,A6063 EXTR.,2,WHT,70MM,-,	S.N.A
⚠ ...3	IC401	1202-000103	IC-VOLTAGE COMP;393,DIP,8P,300MIL,DUAL,	
...3	IC601	1204-001971	IC-SOUND PROCESSOR;MSP3411G-P0-B11,DIP,5	
...3	IC602	AA96-50369D	ASSY H/S;-,SOUND,AA62-30181F,TDA7269,HER	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1201-001385	IC-POWER AMP;7269A,ZIP,11,19.6,DUAL,13,P	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30181F	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
⚠ ...3	IC801S	AA96-50371H	ASSY H/S;-,SMPS,AA62-30181H,5Q1565RF,HER	S.N.A
....4		AA61-11028A	BRACKET;-,SECC,T1.0,-,-,-	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4		AA62-30181H	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		1203-002512	IC-PWM CONTROLLER;KA5Q1565RF-YDTU,TO-3PF	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	IC803	1203-001225	IC-POSI.FIXED REG.;78R09,TO-220,4P;-,PLA	
...3	IC805	AA96-00243K	ASSY H/S;-,REGULATOR,AA62-000450A,KA78R0	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-	S.N.A
....4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P;-,	
...3	IC901	AA09-00041A	IC MICOM;,SDA555X-OTP,3.3V,-,128K,SDIP,-	S.N.A
...3	IC902	1103-001177	IC-EEPROM;24WC16,2048x8Bit,DIP,8P,-,-,2.	
...3	JA701	3722-001884	JACK-SCART;42P,-,SNPB,BLK,-	
...3	JA702	3722-001767	JACK-PIN;2P(9P),-,NI,WHI/RED,-	
...3	L808	AA27-00098A	COIL CHOKE;-,-,24uH,10%,-,0.1,3.0A,DR10X	
⚠ ...3	LR402S	AA27-10004F	COIL CHOKE;-,56uH,K,-,2.5A,BK,-,DR12x15,	
⚠ ...3	LR403S	AA27-00251A	COIL LINEARITY;10UH,10UH,YL81 DR1518,11M	
⚠ ...3	LR404S	AA27-40003P	COIL HORIZ. WIDTH;-,120uH/180uH,Th8x20,U	
⚠ ...3	LR405S	AA27-00057A	COIL HORIZ. WIDTH;-,10mH,YL-9N 15x27.5 C	
⚠ ...3	LX801S	AA29-30002N	FILTER LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ ...3	LX802S	AA29-30002N	FILTER LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ ...3	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ ...3	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
⚠ ...3	PT801S	1404-001026	THERMISTOR-PTC;7ohm,20%,-,290V,25A,-,ST	
...3	Q402	0505-001116	FET-SILICON;BUZ73A,N,200V,22A,0.6ohm,40W	
...3	Q804	BH99-00007S	ASSY HEAT/SINK;KSC2073,MICOM,HERCULES,BH	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	0502-001007	TR-POWER;KSC2073-H2,NPN,25W,TO-220,ST,6	
....4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
....4	CIS	BH62-00007A	HEAT SINK-TR;-,T1.0,L20*H30,CDA	S.N.A
⚠ ...3	RL801S	3501-001053	RELAY-POWER;5Vdc,530mW,10A,1FormA,15mS,5	
...3	T401	AA26-50001S	TRANS-HORIZ.DRIVE;-,-,-,6.0mH,-,-,44uH,-	
⚠ ...3	T444S	AA26-00173A	TRANS FBT;FUJ34H001F(S),FUJ34H001F(S),1.	
⚠ ...3	T801S	AA26-00178A	TRANS SWITCHING;EER5345,K55A,PAL,CIS,160	
⚠ ...3	TU01S	AA40-00096A	TUNER;TCLS3101PD16A(N),PAL,181CH,38.9MHZ	
...3	X601	2801-004020	CRYSTAL-UNIT;18.432MHz,30ppm,28-AAM,12pF	
...3		AA95-03091B	ASSY SUB-PCB,FEATURE BOX;,K55A, ,PAL	
....4	BR01	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4	BR02	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4	CN01	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4	CN02	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4	CN03	3711-003601	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,ANGLE,	
....4	DC41	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
....4	DC51	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	DX01	2802-001177	RESONATOR-CERAMIC;2.696MHZ,0.4%,BK,10X4.	
....4	EC48	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	EC49	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	EX01	2801-004019	CRYSTAL-UNIT;20.25MHz,30ppm,28-AAM,13pF,	
....4	IC06	1203-002000	IC-VOL. DETECTOR;7027,TO-92,3P,-,PLASTIC	
....4		AA97-13629A	ASSY SMD;,K55A, ,PAL,	S.N.A
.....5	DC01	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5	DC02	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5	DC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC04	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC05	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC06	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....5	DC07	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5	DC08	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC09	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,	
.....5	DC10	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC12	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC13	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC14	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC17	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC19	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC20	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC21	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC22	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC23	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....5	DC24	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC25	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC26	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	DC27	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC28	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC29	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC30	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC31	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC32	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	DC33	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC34	2203-000896	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
.....5	DC35	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	DC36	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5	DC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC39	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	DC40	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5	DC43	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC45	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	DC49	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	DC52	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	DD01	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD02	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD03	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD04	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD05	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD06	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD07	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD08	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD09	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD10	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD11	0403-000746	DIODE-ZENER;RLZ3.9B,3.89-4.16V,500MW,LL-	
.....5	DD13	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD14	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD15	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD16	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD17	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD18	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD19	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD20	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
.....5	DL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	DL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	DL03	2703-001070	INDUCTOR-SMD;100uH,10%,4.5x3.2x3.2mm	
.....5	DQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ02	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ03	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ04	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ05	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ07	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ08	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ09	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
.....5	DQ10	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ11	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR05	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR06	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR08	2007-000691	R-CHIP;3.3Mohm,5%,1/16W,DA,TP,1608	
.....5	DR09	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR10	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR13	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5	DR14	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5	DR15	2007-000869	R-CHIP;4.7Kohm,1%,1/16W,DA,TP,1608	
.....5	DR16	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR17	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR18	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR19	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR23	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP,1608	
.....5	DR24	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
.....5	DR25	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5	DR26	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	DR27	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....5	DR28	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....5	DR29	2007-000118	R-CHIP;390ohm,5%,1/16W,DA,TP,1608	
.....5	DR30	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR31	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR32	2007-000081	R-CHIP;2.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR33	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5	DR34	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR36	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR37	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR38	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR39	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR40	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....5	DR41	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....5	DR42	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR43	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR44	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR45	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR46	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR47	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR49	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR50	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR51	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR52	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR53	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR54	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR55	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR56	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR57	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR58	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR59	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR60	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR61	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR62	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR63	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR64	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR65	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR66	2007-000088	R-CHIP;7.5Kohm,5%,1/16W,DA,TP,1608	
.....5	DR68	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR69	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR70	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR80	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR81	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
.....5	DR82	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
.....5	DR86	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR87	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR88	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	EC01	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC02	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC04	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	EC08	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC09	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC10	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC12	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC13	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC14	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC15	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC17	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC18	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC19	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC20	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC21	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC22	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC23	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC24	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	EC29	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC30	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC31	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC32	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC33	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC34	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	EC35	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
.....5	EC36	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC39	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC40	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC41	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC42	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC43	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC44	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC45	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC46	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC47	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	EC51	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	EC52	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC53	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC54	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC55	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC56	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC57	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	EC58	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	EC59	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC60	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC62	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC63	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC64	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC65	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EL04	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5	EL05	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EL06	3301-001324	CORE-FERRITE BEAD;AB,15OHM,2X1.25X0.9MM,	
.....5	EL07	3301-001324	CORE-FERRITE BEAD;AB,15OHM,2X1.25X0.9MM,	
.....5	EL08	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EL09	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EL13	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EQ04	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....5	EQ05	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....5	EQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	ER01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER02	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	ER06	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5	ER07	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5	ER09	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	ER13	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER16	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER19	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	ER21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	ER22	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER24	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER25	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER26	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER29	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	ER30	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	ER31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	ER32	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	ER33	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	ER34	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	ER35	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	ER36	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	IC01	1204-001950	IC-VIDEO DECODER;VSP9405B,QFP,80P,-,PLAS	
.....5	IC04	1204-001989	IC-VIDEO PROCESS;CXA2165Q,QFP,64P,20X14M	
.....5	IC05	1203-002186	IC-POSI.FIXED REG.;18,DPAK,3P,240MIL,PLA	
.....5	IC10	1001-001177	IC-VIDEO SWITCH;TEA6425D,VIDEO SWITCH ,S	
.....5	IC11	0801-000662	IC-CMOS LOGIC;74HC123,MULTIVIBATOR,SOP,1	
.....5	PCB	AA41-00644B	PCB-PAL FERTURE BOX;CS29Z6,FR-4,4L,B,1.6	S.N.A
.....5	SC29	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SC31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SC33	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SC43	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	SC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	SC47	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5	SC48	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5	SC49	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	SL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	SR09	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	SR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	SR11	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	SR30	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR32	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR33	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR34	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	SR36	2007-000259	R-CHIP;1.6Kohm,5%,1/16W,DA,TP,1608	
.....5	SR37	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5	TC01	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC02	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC03	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC04	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC05	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC06	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC07	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	TC08	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	TD01	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	TL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	TQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	TQ02	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	TR01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	TR03	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	TR05	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR07	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	TR08	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR09	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	TR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3		AA39-00191A	LEAD CONNECTOR-ASSY;,4P,1100/500MM,35155	
...3		AA97-12467E	ASSY AUTO-MAIN;34Z4,K55A,RUSSIA	S.N.A
....4	C101	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C102	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C104	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
....4	C105	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C106	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C107	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C108	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
....4	C109	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C110	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C111	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C112	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C113	2202-000216	C-CERAMIC,MLC-AXIAL;0.027NF,5%,50V,SL,TP	
....4	C116	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C201	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C202	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	C203	2202-000106	C-CERAMIC,MLC-AXIAL;1.5nF,20%,16V,Y5P,TP	
....4	C204	2202-000106	C-CERAMIC,MLC-AXIAL;1.5nF,20%,16V,Y5P,TP	
....4	C206	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C207	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C239	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C240	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C302	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
....4	C303	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
....4	C304	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
....4	C305	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
....4	C306	2301-000160	C-FILM,PEF;12nF,5%,50V,TP,11.0x6.0x9.0mm	
....4	C307	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
....4	C308	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
....4	C401	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C402	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
....4	C403	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C404	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
....4	C408	2301-001143	C-FILM,PPF;56nF,5%,400V,TP,20x10x17,7.5	
....4	C409	2303-001001	C-FILM,PPF;22nF,5%,630V,TP,18x14.5x8.5mm	
....4	C411	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
....4	C412	2301-000310	C-FILM,PEF;68nF,5%,50V,TP,8.0X8.5X4.0X5,	
....4	C413	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
....4	C414	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
....4	C415	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,	
....4	C416	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
....4	C417	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C418	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
....4	C420	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
....4	C421	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C422	2401-001527	C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
....4	C424	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
....4	C432	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C601	2201-000558	C-CERAMIC,DISC;0.47NF,10%,50V,Y5P,TP,5X3	
....4	C602	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
....4	C603	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C604	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	C605	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C606	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C607	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C608	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C610	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C611	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C612	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	C613	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
....4	C614	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C615	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C619	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C620	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C621	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C622	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C623	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C624	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C625	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C626	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C627	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C628	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C629	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C630	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C631	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C632	2201-000370	C-CERAMIC,DISC;0.22NF,10%,50V,Y5P,TP,4X3	
....4	C633	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C634	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	C635	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C636	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C637	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C638	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C639	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C640	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C641	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C642	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C643	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C644	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
....4	C645	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C646	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C647	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
....4	C648	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
....4	C649	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm	
....4	C650	2401-001176	C-AL;33uF,20%,25V,GP,TP,5x11,5	
....4	C651	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C652	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C653	2401-002216	C-AL;2200uF,20%,35V,GP,TP,16x25,7.5	
....4	C654	2201-000611	C-CERAMIC,DISC;0.056NF,5%,50V,C0G,TP,7X3	
....4	C655	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	C656	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
....4	C657	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
....4	C658	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C659	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C660	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C701	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
....4	C801	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
....4	C802	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
....4	C804	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
....4	C805	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
....4	C807	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.	
....4	C808	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
....4	C809	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	C810	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C811	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	C812	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C813	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.	
....4	C814	2201-002028	C-CERAMIC,DISC;0.47NF,10%,2KV,Y5P,TP,7.5	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	C816	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
....4	C817	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C818	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4	C819	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C821	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	C822	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C823	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	C824	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
....4	C825	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C826	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
....4	C827	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4	C828	2201-000374	C-CERAMIC,DISC;0.22NF,5%,50V,C0G,TP,10.5	
....4	C830	2201-000984	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
....4	C831	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C832	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
....4	C833	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4	C834	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
....4	C835	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4	C836	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C837	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C838	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
....4	C840	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
....4	C841	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
....4	C843	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C844	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C901	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C902	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C903	2202-000719	C-CERAMIC,MLC-AXIAL;6.8nF,20%,16V,Y5R,TP	
....4	C904	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C905	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C906	2202-000791	C-CERAMIC,MLC-AXIAL;150pF,10%,50V,Y5P,TP	
....4	C907	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
....4	C909	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
....4	C910	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
....4	C911	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
....4	C912	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C913	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C914	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C915	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C916	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C917	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C918	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
....4	C919	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C920	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C921	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C922	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C923	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C924	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C925	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C927	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	CN302	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
....4	CN601	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
....4	CN901	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
....4	CW901	2503-000156	C-NETWORK;100pFx4,20%,50V	
....4	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D202	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D207	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4	D401	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 4	D402	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4	D403	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D404	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4	D405	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D406	0404-001056	DIODE-SCHOTTKY;RK16,60V,1.5A,DO-204AC,TP	
⚠ 4	D408	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4	D409	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
⚠ 4	D410	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D411	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
....4	D603	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D607	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D801	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 4	D802	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 4	D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4	D804	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4	D805	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D808	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	

Level	Loc. No.	Code No.	Description ; Specification	Remark
⚠ 4	D812	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D816	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D901	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D902	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D903	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D904	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	D907	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4	DZ302	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ303	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ304	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
....4	DZ305	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ306	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ307	0403-001118	DIODE-ZENER;MTZ30A,32V,26.99-28.39V,500m	
....4	DZ401	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
....4	DZ402	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DZ404	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ601	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ602	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ603	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ604	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ605	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ606	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ607	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	DZ608	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	DZ801	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ802	0403-000716	DIODE-ZENER;MTZJ4.7B,4.7V,4.55-4.8V,500m	
....4	DZ803	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
....4	DZ804	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
....4	DZ807	0403-001330	DIODE-ZENER;MTZJ30A,26.99-28.39V,500mW,D	
....4	DZ808	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ902	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ906	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ907	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ908	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ909	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ910	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ911	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ912	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	EL201	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL202	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL203	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL204	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL401	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL402	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL407	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL408	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL805	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL806	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL807	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL808	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY302	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY303	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY403	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY404	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY405	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY406	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY407	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY408	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY409	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY410	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY411	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY412	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY413	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY414	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY415	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY417	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY418	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY419	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY420	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY421	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY422	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY423	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	EY424	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY425	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY426	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY429	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY430	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY431	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY432	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY433	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY434	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY435	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY436	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY437	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY439	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY441	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY446	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY447	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY603	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY604	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY701	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY702	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY703	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY704	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY705	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY706	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY801	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY802	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY803	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY804	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY805	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY806	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY809	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY810	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY811	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY812	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY813	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY814	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY815	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY816	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY817	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY820	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY824	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY825	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY828	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY829	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY830	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY831	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY832	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY833	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY835	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY836	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY837	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY838	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY839	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY840	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY841	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY842	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY844	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY845	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY846	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY848	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY850	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY851	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY853	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY854	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY855	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY856	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY857	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY858	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY859	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY860	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY861	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY862	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY864	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY865	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY871	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY872	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4	FA801S	3601-000120	FUSE-AXIAL LEAD;125V,2.5A,FAST-ACTING,GL	
....4	FA802S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
....4	FA803S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
....4	GT102	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT301	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT302	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT401	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT402	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT404	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT405	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT406	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT409	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT410	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT411	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT412	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT807	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	HIC401	AA13-00094A	IC HYBRID;-,DDRI001A,SIP,5P,-,TP	
....4	IC202	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
....4	IC402	1203-000243	IC-POSI.FIXED REG.;7812A,TO-220,3P,-,PLA	
....4	IC804	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
....4	IC903	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
....4	IC904	1203-001943	IC-VOL. DETECTOR;7025,TO-92,3P,-,PLASTIC	
....4	J709	2001-000376	R-CARBON;150HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	L101	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
....4	L103	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	L104	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
....4	L106	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	L201	2701-000200	INDUCTOR-AXIAL;5.6uH,10%,4.2x9.8mm	
....4	L203	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L402	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4	L403	2701-001040	INDUCTOR-AXIAL;10uH,10%,4.5x14mm	
....4	L404	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L407	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L409	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L410	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4	L601	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L602	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
....4	L603	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L604	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L605	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L606	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L607	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L608	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L609	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L610	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L612	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L613	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L614	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L615	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L703	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L704	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L705	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L706	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
....4	L801	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L802	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L803	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L804	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L805	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L806	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
....4	L807	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4	L809	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L811	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
....4	L901	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L902	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	L903	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L904	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
....4	L906	2701-000215	INDUCTOR-AXIAL;8.2uH,10%,2.5x3.4mm	
....4	L907	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L908	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
....4	L909	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
....4	PCB	AA41-00707B	PCB-MAIN;CS29Z6HP,FR-1,1L,B,1.6T,330X245	S.N.A
....4	Q404	0505-000156	FET-SILICON;IRF620,N,200V,5A,0.8ohm,50W,	
....4	Q601	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q603	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q801	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q802	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
....4	Q803	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q901	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q906	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q907	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q908	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q909	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4	Q910	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4	Q912	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q913	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q914	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	R101	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R102	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R103	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R104	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R105	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R106	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R107	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R108	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R203	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R204	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R301	2001-001163	R-CARBON(S);560OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R302	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R303	2001-000016	R-CARBON(S);10HM,5%,1/2W,AA,TP,2.4X6.4MM	
....4	R304	2008-001108	R-FUSIBLE(S);1.2ohm,5%,2W,AG,TP,3.9x12mm	
....4	R305	2003-002205	R-METAL OXIDE(S);330ohm,5%,2W,AG,TP,3.9X	
....4	R306	2003-002205	R-METAL OXIDE(S);330ohm,5%,2W,AG,TP,3.9X	
....4	R307	2008-001114	R-FUSIBLE(S);1.5ohm,5%,2W,AG,TP,3.9x12mm	
....4	R308	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R309	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R310	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R314	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R315	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R316	2001-001129	R-CARBON(S);330KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R317	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R401	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R402	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R403	2003-000532	R-METAL OXIDE(S);18ohm,5%,2W,AF,TP,4x12m	
....4	R405	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
....4	R409	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
....4	R410	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
....4	R411	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R412	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
....4	R413	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
....4	R414	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
....4	R415	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R416	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R418	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R419	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R420	2004-001987	R-METAL(S);4.3Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R421	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R422	2008-001149	R-FUSIBLE(S);0.22OHM,5%,2W,AF,TP,3.8X11M	
....4	R423	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R424	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
....4	R425	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
....4	R426	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
....4	R428	2004-000698	R-METAL;3.3Kohm,1%,1/4W,AA,TP,2.4x6.4m	
....4	R430	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
....4	R431	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
....4	R432	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R433	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
....4	R434	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	R435	2003-000784	R-METAL OXIDE(S);7.5Kohm,5%,2W,AF,TP,4x1	
....4	R440	2004-002019	R-METAL(S);33Kohm,1%,1/2W,AA,TP,2.5x6.5m	
....4	R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R602	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R603	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R604	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R605	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R606	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R607	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R608	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R609	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R612	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R613	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R614	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R615	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R616	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R617	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R618	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R623	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R624	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R626	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R627	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R628	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R629	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R630	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R631	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R632	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R633	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R634	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R635	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R636	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R637	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R638	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R639	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R704	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R710	2001-000376	R-CARBON;15OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R715	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R716	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R717	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R718	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R723	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R801	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R802	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4	R803	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4	R804	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4	R805	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R806	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R807	2001-001103	R-CARBON(S);20KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R808	2001-001197	R-CARBON(S);910OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R809	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R810	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R811	2001-001155	R-CARBON(S);5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R812	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R813	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R815	2008-000284	R-FUSIBLE(S);0.10HM,10%,2W,AF,TP,3.9X10M	
....4	R816	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R817	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R818	2001-001131	R-CARBON(S);33KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R819	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R820	2001-001096	R-CARBON(S);2.2OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R821	2004-002015	R-METAL(S);140Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R822	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R823	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R824	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R827	2008-000284	R-FUSIBLE(S);0.10HM,10%,2W,AF,TP,3.9X10M	
....4	R828	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm	
....4	R829	2008-001148	R-FUSIBLE;3.3OHM,5%,1W,AG,TP,3.9X12MM	
....4	R830	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
....4	R833	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R835	2003-002181	R-METAL OXIDE(S);68Kohm,5%,2W,AG,TP,3.9x	
....4	R838	2001-001050	R-CARBON(S);1.5KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R840	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R841	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R842	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R901	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R902	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R903	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R904	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R905	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	R906	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R907	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R908	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R909	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R910	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R911	2001-000628	R-CARBON;3000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R912	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R913	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R914	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R915	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R916	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R917	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R919	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R920	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R921	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R922	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R923	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R924	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R925	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R926	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R927	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R928	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R935	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R936	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R937	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R938	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R940	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R941	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R942	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R945	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R946	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R947	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R948	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R951	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R952	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R953	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R954	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R955	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R958	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R960	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R961	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R962	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R963	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R965	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R966	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R967	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R968	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R972	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R973	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R974	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R981	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R982	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R983	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R984	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R988	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 4	RR430S	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
⚠ 4	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ 4	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
....4	X901	2801-003728	CRYSTAL-UNIT;6MHz,30ppm,28-AAM,20pF,40oh	
...3		AA39-20536G	LEAD CONNECTOR-ASSY;,1P,60MM,F,F,1617#22	
...3		AA61-00707B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
..2		AA94-12053A	ASSY PCB MISC-CRT;34Z6,K55A	
...3	C522	2201-002117	C-CERAMIC,DISC;4.7nF,20%,3kV,Y5U,TP,16x6	
...3	CNC01	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	CNC01A	AA39-00088A	LEAD CONNECTOR-ASSY;HERCULES,UL1007/1185	
...3	CNC02	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3	CNC02A	AA39-00127A	LEAD CONNECTOR-ASSY;,8P,400MM,35155-0800	
...3	GT501A	AA39-00341A	LEAD CONNECTOR;K55A(WT-32Z4HD),UL1015#18	
⚠ ...3	GT503S	AA39-20010B	LEAD CONNECTOR-ASSY;,1P,500,YFH800-01,S,	
...3	IC501	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
....4		1201-001131	IC-VIDEO AMP;6111,SIP,9P,-,SINGLE,-,PLAS	
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3	IC502	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC503	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC504	BH99-00038E	ASSY HEAT/SINK;TDA2030,AMP,HERCULES,BH62	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	1201-000010	IC-OP AMP;2030,PENTAWATT,5P,-,SINGLE,-,C	
....4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
....4	CIS	BH62-00041A	HEAT SINK-TR;PN17LT,A1050S,T1.0,50,23,-,	S.N.A
...3	QF09	AA96-00243M	ASSY H/S;-,AMP,AA62-000450A,2SA1011,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000131	TR-POWER;2SA1011-D,PNP,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	QF10	AA96-00243L	ASSY H/S;-,CRT,AA62-000450A,2SC2344,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000153	TR-POWER;2SC2344-D,NPN,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	SC01	3722-001503	JACK-PIN;1P,1PI,NI,RED,SCR-JACK	
⚠ ...3	V999S	3704-000114	SOCKET-CRT;14P,29.1,35.5,SN,ISH09S/BK	
...3		2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
...3		AA97-13361A	ASSY AUTO-CRT;34Z6,K55A,RUSSIA	S.N.A
....4	C501	2201-000247	C-CERAMIC,DISC;0.015NF,5%,50V,C0G,TP,5X3	
....4	C502	2201-002031	C-CERAMIC,DISC;0.005NF,0.5PF,50V,C0G,TP,	
....4	C503	2201-000662	C-CERAMIC,DISC;0.007NF,0.25PF,50V,C0G,TP	
....4	C504	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C505	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C506	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C507	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C508	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C509	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C511	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C512	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C513	2201-000600	C-CERAMIC,DISC;0.56NF,10%,50V,Y5P,TP,5X3	
....4	C514	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C515	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C520	2401-000703	C-AL;2200uF,20%,25V,GP,-,12.5x25mm,	
....4	C526	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C528	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C531	2401-002264	C-AL;10uF,20%,350V,GP,TP,10x20mm,5m	
....4	C532	2401-001563	C-AL;47uF,20%,400V,GP,TP,16x25,7.5	
....4	C533	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C534	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C535	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	C536	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C537	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C538	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C539	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CF01	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4	CF02	2201-000017	C-CERAMIC,DISC;1NF,10%,50V,Y5P,TP,5X3.5M	
....4	CF03	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF04	2201-000516	C-CERAMIC,DISC;4.7NF,+100-0%,500V,Y5U,TP	
....4	CF05	2301-000261	C-FILM,PEF;4.7nF,5%,100V,TP,10.5x12.5x6.	
....4	CF06	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF07	2201-000604	C-CERAMIC,DISC;0.056NF,+100-0%,500V,SL,T	
....4	CF71	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	CF73	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
....4	CF74	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	CF75	2401-000045	C-AL;10uF,20%,160V,GP,TP,10x16,5	
....4	D501	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D502	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D509	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D510	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D511	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D512	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D513	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D514	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DF01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF05	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF06	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF07	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DF08	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DZ501	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ502	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ504	0403-000698	DIODE-ZENER;TZP12A,12V,11.4-12.6V,1W,DO-	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	DZ510	0403-000734	DIODE-ZENER;TZP15B,15V,14.7-16.5V,1W,DO-	
....4	DZF01	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
....4	DZF02	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
....4	DZF03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	EL100	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL80	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL81	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL82	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL83	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL84	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL85	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL86	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL87	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL88	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL89	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL92	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL94	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL95	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL96	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL97	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL98	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL99	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	FN1	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
....4	FV1	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
....4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT503	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT504	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	L502	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
....4	LF01	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF02	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF03	2701-000112	INDUCTOR-AXIAL;100uH,10%,3x7mm	
....4	LF04	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF06	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF08	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF09	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF11	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	PCB	AA41-00578D	PCB-CRT;CT-29Z7HR,FR-1,1L,D,1.6T,330X245	S.N.A
....4	Q501	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q502	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q503	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q504	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	QF02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	QF03	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	QF04	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	QF05	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	R501	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R502	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R504	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R505	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R506	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R507	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R508	2001-000995	R-CARBON;8200HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R509	2008-000205	R-FUSIBLE(S);10ohm,5%,1/2W,AF,TP,2.5x6.5	
....4	R510	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R511	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R512	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R513	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R514	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R515	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R518	2001-001095	R-CARBON(S);2.2MOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R519	2001-000356	R-CARBON;150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R520	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R522	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R523	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R524	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
....4	R525	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7	
....4	R527	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R528	2003-000458	R-METAL OXIDE(S);100ohm,5%,2W,AF,TP,4x12	
....4	R529	2008-000264	R-FUSIBLE(S);1ohm,5%,1W,AF,TP,3.9x10mm	
....4	R530	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R531	2001-000539	R-CARBON;24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R540	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R541	2008-001053	R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
....4	R554	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R555	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R556	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R560	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R561	2001-001126	R-CARBON(S);300OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R562	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R563	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R564	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R565	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R566	2001-001040	R-CARBON(S);0.68OHM,5%,1/2W,AA,TP,2.4X6.	
....4	RF13	2008-001014	R-FUSIBLE(S);22ohm,5%,1W,AF,TP,3.2x10mm	
....4	RF14	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF15	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF16	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF17	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF18	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF19	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF20	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF21	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF22	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF23	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF24	2003-001018	R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
....4	RF25	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF26	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF27	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF28	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF29	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF30	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF31	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF32	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	RF33	2001-001053	R-CARBON(S);1.5OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF34	2001-001100	R-CARBON(S);2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF35	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	RF36	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
..2		AA94-12356A	ASSY PCB MISC-A/V SIDE;Z4,K55A,PAL	
...3	CN701	AA39-00317B	LEAD CONNECTOR-ASSY;K55A/WT-32Z4HD,UL100	
...3	CN703	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,500,YBNH025-05,6	
...3	CN704	AA39-00070A	LEAD CONNECTOR-ASSY;,4P,200MM,YBNH250-04	
...3	JA701	3722-001031	JACK-PIN;3P,3.6mm,#18,AU	
...3	JH701	3722-000143	JACK-PHONE;1P(VER),3.4PI,AG,BLK,NO	
...3	JS701	3722-001163	JACK-VHS;4P,12mm,AU,BLK,N	
...3		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
...3		AA97-13518A	ASSY AUTO-A/V SIDE;Z4,K55A,PAL	S.N.A
....4	C701	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C702	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C707	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C708	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	DZ701	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500m	
....4	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L703	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L705	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L706	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L707	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L708	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	PCB	AA41-00616B	PCB-A/V SIDE(Z4);CT-29Z4HRH,FR-1,1L,B,1.	S.N.A
....4	R701	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R702	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
...3		AA61-60109D	SPRING ETC-DOOR;32W8,SUS304L,-,-,-,-,-,-	S.N.A
...3		AA61-00545A	HOLDER-AV,HOUSING ASSY;32Z5,ABS,-,-,-,GR	S.N.A
....4		6003-001070	SCREW-TAPTITE;BH,+,B,M2,L4,ZPC(BLK),SWRC	S.N.A
....4		AA61-00453B	HOLDER-AV,HOUSING;32Z5,ABS,-,-,-,GRAY,HB	S.N.A
....4		AA61-30001A	LATCH-DOOR;-,-,-,-,-,-,KIFUCO LA701	
....4		AA61-80002A	DAMPER-GEAR;-,DP802,-,-,-,-,BLU,DP802	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA61-00451F	HOLDER-AV;32Z5,HIPS,GR503,FV2	S.N.A
...3		AA61-00544G	HOLDER-AV,COVER ASSY;Z4,ABS,GRAY,HB K55A	S.N.A
....4		AA61-00452B	HOLDER-AV,COVER;32Z5,ABS,-,-,-,GRAY,HB	S.N.A
....4		AA64-01204E	INLAY-SIDE,AV;32Z4,PS SHEET,T0.3,KS3A PA	S.N.A

ASSY CPT

1		AA91-02964A	ASSY CPT;CS34Z4HF9X/BWT	S.N.A
..2		AA91-02176B	ASSY CPT;A80LTM350X98,34,+380MG,ITC,AA0	S.N.A
⚠ ...3		AA03-00232A	CRT COLOR;A80LTM350X98,+380MG,0.35MH,9.9	
..2		AA98-70011F	ASSY TBC WIRE(P);-,34inch,NTSC,2P-WH,KS4	S.N.A
..2		AA27-00060A	COIL DEGAUSSING;-,34,14ohm ,-,L3600,E	

Level	Loc. No.	Code No.	Description ; Specification	Remark

Level	Loc. No.	Code No.	Description ; Specification	Remark

ASSY COVER REAR

1		AA90-02055L	ASSY COVER REAR;CS34Z4HNGX/BWT	S.N.A
..2	CABBAC	AA60-00091J	SPACER-FELT;-,FELT,330X10,-,-,BLK,T0.5,-	S.N.A
..2		AA63-00463A	COVER-WOOFER;TOOL,34Z4,-,-,-,-,-,-,MOLD	S.N.A
..2		AA64-01977B	CABINET BACK;34Z4,HIPS,FV2,GR503	
...3		AA61-20129C	HOLDER-WIRE;29Z4,NYLON-66,GRAY,DAFC-2500	S.N.A
..2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A

ASSY COVER FRONT

1		AA90-01892V	ASSY COVER FRONT;CS34Z4HNGX/BWT	S.N.A
..2	CB+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CB_TBA	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CRT	AA63-60004L	SPACER-GUM,CRT;-,NTR RUBBER,-,-,-,BLK,T3	S.N.A
..2	CRT+CF	AA60-10050V	SCREW-ASSY;-,SWRCH18A,M6,L30,HH,+,WC,-,Z	S.N.A
..2	DR+CF	6002-000522	SCREW-TAPPING;TH,+,2,M4,L15,ZPC(BLK),SWR	S.N.A
..2	HP+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	KC+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	TB+RCA	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2		AA61-01222A	HOLDER-CAP;,DAHC-30 PE	S.N.A
..2		AA65-00019A	CLAMPER CORE-D,COIL;25-34,NYLON 66,V2,N	S.N.A
..2		AA65-30113A	CLAMPER CORE-D,COIL;-,NYLON 66,V2,-,BLK,	S.N.A
..2		AA91-00764M	ASSY CABINET FRONT;,CS34Z4,SV012P K55A C	
...3	WIN+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
...3		AA64-03211A	WINDOW-REMOCON;Z4,PC,VIOLET	S.N.A
...3		AA91-00738A	ASSY HOLDER SPK;-,PP,8OHM,10W,-,ZEUS-2 F	
...3		AA64-01062B	BADGE-BRAND;32Z5,AL FORGING,-,-,L65,-,SI	S.N.A
...3		AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA64-03210A	KNOB-POWER;Z4,ABS,HB,WHT,SVM3012	
...3		6006-001096	SCREW-ASS'Y TAPT;WP,BH,+,M4.0,L12,BLK,SW	S.N.A
...3		AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A
...3		AA64-01203B	INDICATOR LED;32Z5,ACRYL,-,CLR,-,-,-	
...3		AA64-01974F	CABINET-FRONT;34Z4,HIPS,HB,G4309,SV012P	S.N.A
..2		AA61-00306B	SUPPORT-CRT;34A7,HIPS,-,-,-,NTR,HB	S.N.A

ASSY ACCESSORY

1		AA92-06199A	ASSY ACCESSORY;29Z6,RUSSIA,K55A	S.N.A
..2	1	AA68-02479A	MANUAL USERS;CS29Z7HP,RUS,K55A,PIP,TTX	
..2		6801-001073	CARD-REGISTRATION;RUS,XEV,RUS,MOJO100,-,	S.N.A
..2		AA59-00266D	REMOCON;TM63,HERCULES,45,SAMSUNG,EX,RUSS	
...3		2802-000194	RESONATOR-CERAMIC;8MHz,1.0%,TP,8.5x4.5x5	
...3		AA09-00275A	IC MICOM;Z86L8808SSC-R51PX,SOP,ST,SZTM-8	
..2		AA68-00952A	CARD-COUPON;-,A/P100(G),AA68-00949A,-,-,	S.N.A
..2		AA69-00862A	BAG PE;-,HDPE PE FOAM,T0.03,W400,H240,-,	S.N.A
..2		AA68-01402A	MANUAL-GOOD WILL LETTER;,CIS,B5,1PAGE,A/	S.N.A
..2		AA68-01120A	MANUAL SERVICE;-,-,CIS,A4,6PAGE(FOLD),W/	S.N.A
..2		AA68-00816B	CARD WARRANTY-01;,RUSSINA,2,W/P 120G,BOT	S.N.A

ASSY P/MATERIAL

1		AA92-03144B	ASSY P/MATERIAL;CS34Z4HF9X/SAP	S.N.A
..2		AA69-00744L	BAG-SHEET;-,HDPE PE FOAM,T0.015,W1650,H1	S.N.A
..2		AA69-00306A	BAG AIR;LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A
..2		AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,	S.N.A
..2		AA63-10007C	BAND-PP;W18,CLEA,1G	S.N.A
..2		AA61-20285A	HOLDER-BOX;3456,PP,-,-,-,WHT,VO	S.N.A
..2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A

7-6 CS34Z6HPGX/BWT

ASSY CHASSIS

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA91-05665B	ASSY CHASSIS;,K55A,RUSSIA	S.N.A
..2	C-BLOC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2	D-FOCU	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2	MP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2	PCB	AA61-00706B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
..2	TBA+HC	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2	WP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
..2		AA94-12054A	ASSY PCB MISC-CONTROL;34Z6HP,K55A,100HZ	
...3	CNY01	AA39-00100E	LEAD CONNECTOR-ASSY;,4P,600MM,YBNH250-04	
...3	CPC+CC	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
...3	SWY01	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY02	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY03	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY04	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY05	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWY06	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-12449A	ASSY AUTO-CONTROL;29Z6,K55A,PAL	S.N.A
....4	DZY03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZY04	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	LY01	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	PCB	AA41-00651A	PCB-CONTROL;CS29Z7HF,FR-1,1L,A,1.6T,330X	S.N.A
....4	RY02	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY03	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY04	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY05	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RY06	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
...3		AA96-00937B	ASSY COVER P-COVER CONTROL;CS34Z6HP,HIPS	
....4	KC+CC	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
....4		AA63-60001R	SPACER-FELT;-,FELT,-,-,-,-,T0.35,-,200X1	S.N.A
....4		AA64-02662A	KNOB-CONTROL;Z7,ABS,HB,G3676,S104M+W971	
....4		AA63-00570B	COVER-CONTROL;34Z6,HIPS,HB,G4309,DGN-118	S.N.A
..2		AA94-12053A	ASSY PCB MISC-CRT;34Z6,K55A	
...3	C522	2201-002117	C-CERAMIC,DISC;4.7nF,20%,3kV,Y5U,TP,16x6	
...3	CNC01	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	CNC01A	AA39-00088A	LEAD CONNECTOR-ASSY;HERCULES,UL1007/1185	
...3	CNC02	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3	CNC02A	AA39-00127A	LEAD CONNECTOR-ASSY;,8P,400MM,35155-0800	
...3	GT501A	AA39-00341A	LEAD CONNECTOR;K55A(WT-32Z4HD),UL1015#18	
⚠ ...3	GT503S	AA39-20010B	LEAD CONNECTOR-ASSY;,1P,500,YFH800-01,S,	
...3	IC501	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
....4		1201-001131	IC-VIDEO AMP;6111,SIP,9P,-,SINGLE,-,PLAS	
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3	IC502	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC503	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC504	BH99-00038E	ASSY HEAT/SINK;TDA2030,AMP,HERCULES,BH62	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	1201-000010	IC-OP AMP;2030,PENTAWATT,5P,-,SINGLE,-,C	
....4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
....4	CIS	BH62-00041A	HEAT SINK-TR;PN17LT,A1050S,T1.0,50,23,-,	S.N.A
...3	QF09	AA96-00243M	ASSY H/S;-,AMP,AA62-000450A,2SA1011,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000131	TR-POWER;2SA1011-D,PNP,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	QF10	AA96-00243L	ASSY H/S;-,CRT,AA62-000450A,2SC2344,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000153	TR-POWER;2SC2344-D,NPN,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	SC01	3722-001503	JACK-PIN;1P,1PI,NI,RED,SCR-JACK	
⚠ ...3	V999S	3704-000114	SOCKET-CRT;14P,29.1,35.5,SN,ISH09S/BK	
...3		2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
...3		AA97-13361A	ASSY AUTO-CRT;34Z6,K55A,RUSSIA	S.N.A
....4	C501	2201-000247	C-CERAMIC,DISC;0.015NF,5%,50V,C0G,TP,5X3	
....4	C502	2201-002031	C-CERAMIC,DISC;0.005NF,0.5PF,50V,C0G,TP,	
....4	C503	2201-000662	C-CERAMIC,DISC;0.007NF,0.25PF,50V,C0G,TP	
....4	C504	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C505	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C506	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C507	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C508	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C509	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C511	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C512	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C513	2201-000600	C-CERAMIC,DISC;0.56NF,10%,50V,Y5P,TP,5X3	
....4	C514	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C515	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C520	2401-000703	C-AL;2200uF,20%,25V,GP,-,12.5x25mm,	
....4	C526	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C528	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C531	2401-002264	C-AL;10uF,20%,350V,GP,TP,10x20mm,5m	
....4	C532	2401-001563	C-AL;47uF,20%,400V,GP,TP,16x25,7.5	
....4	C533	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C534	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C535	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	C536	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C537	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C538	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C539	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CF01	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4	CF02	2201-000017	C-CERAMIC,DISC;1NF,10%,50V,Y5P,TP,5X3.5M	
....4	CF03	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF04	2201-000516	C-CERAMIC,DISC;4.7NF,+100-0%,500V,Y5U,TP	
....4	CF05	2301-000261	C-FILM,PEF;4.7nF,5%,100V,TP,10.5x12.5x6.	
....4	CF06	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF07	2201-000604	C-CERAMIC,DISC;0.056NF,+100-0%,500V,SL,T	
....4	CF71	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	CF73	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
....4	CF74	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	CF75	2401-000045	C-AL;10uF,20%,160V,GP,TP,10x16,5	
....4	D501	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D502	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D509	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D510	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D511	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D512	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D513	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D514	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DF01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF05	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF06	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF07	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DF08	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DZ501	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ502	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ504	0403-000698	DIODE-ZENER;TZP12A,12V,11.4-12.6V,1W,DO-	
....4	DZ510	0403-000734	DIODE-ZENER;TZP15B,15V,14.7-16.5V,1W,DO-	
....4	DZF01	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
....4	DZF02	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
....4	DZF03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	EL100	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL80	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL81	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL82	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL83	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL84	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL85	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL86	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL87	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL88	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL89	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL92	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL94	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL95	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL96	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL97	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL98	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	EL99	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
....4	FN1	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	FV1	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
....4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT503	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT504	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	L502	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
....4	LF01	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF02	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF03	2701-000112	INDUCTOR-AXIAL;100uH,10%,3x7mm	
....4	LF04	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF06	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF08	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF09	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	LF11	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	PCB	AA41-00578D	PCB-CRT;CT-29Z7HR,FR-1,1L,D,1.6T,330X245	S.N.A
....4	Q501	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q502	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q503	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q504	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	QF02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	QF03	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	QF04	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	QF05	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	R501	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R502	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R504	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R505	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R506	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R507	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R508	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R509	2008-000205	R-FUSIBLE(S);10ohm,5%,1/2W,AF,TP,2.5x6.5	
....4	R510	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R511	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R512	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R513	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R514	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R515	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R518	2001-001095	R-CARBON(S);2.2MOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R519	2001-000356	R-CARBON;150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R520	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R522	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R523	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R524	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
....4	R525	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7	
....4	R527	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R528	2003-000458	R-METAL OXIDE(S);100ohm,5%,2W,AF,TP,4x12	
....4	R529	2008-000264	R-FUSIBLE(S);1ohm,5%,1W,AF,TP,3.9x10mm	
....4	R530	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R531	2001-000539	R-CARBON;24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R540	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R541	2008-001053	R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
....4	R554	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R555	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R556	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R560	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R561	2001-001126	R-CARBON(S);3000HM,5%,1/2W,AA,TP,2.4X6.4	
....4	R562	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R563	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R564	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R565	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R566	2001-001040	R-CARBON(S);0.68OHM,5%,1/2W,AA,TP,2.4X6.	
....4	RF13	2008-001014	R-FUSIBLE(S);22ohm,5%,1W,AF,TP,3.2x10mm	
....4	RF14	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF15	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF16	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	RF17	2001-000019	R-CARBON(S);100HM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF18	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF19	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	RF20	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF21	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF22	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF23	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF24	2003-001018	R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
....4	RF25	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF26	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF27	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF28	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF29	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF30	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF31	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RF32	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	RF33	2001-001053	R-CARBON(S);1.5OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF34	2001-001100	R-CARBON(S);2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RF35	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	RF36	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
..2		AA94-12050A	ASSY PCB MAIN;,K55A,34CIS	
...3	C-BLOC	AA26-00069A	TRANS FBT;FUJ-29C002C(S),DREAM3,4,-,-,-,	
...3	C425	2306-000273	C-FILM,MPPF;82nF,5%,400V,BK,19x15.5x7,15	
...3	C426	2306-000172	C-FILM,MPPF;270nF,5%,400V,BK,26.5x19mm,2	
...3	C806	2306-000112	C-FILM,MPPF;100nF,20%,250V,BK,-,15mm	
...3	C820	2401-003419	C-AL;2200uF,20%,50V,WT,TP,16X35.5mm	
...3	CABLE	AA39-30007B	CBF IF;-,T,150mm,1365#26	
...3	CN502	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3	CN702	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	CN702A	AA39-00114C	LEAD CONNECTOR-ASSY;,12P,500MM,35155-120	
⚠ ...3	D801S	AA96-00276C	ASSY H/S;-,BRIDGE ,AA62-00052A,GSIB660,K	S.N.A
....4		AA62-00052A	HEAT SINK-PS;-,-,-,SILVER,HOLE 18.5mm, 2	S.N.A
....4		AA60-30003A	WASHER;T1.5,SBHG-1	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		0402-001399	DIODE-BRIDGE;GSIB660,600V,6A,SIP-4,BK	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
⚠ ...3	GT804S	AA39-20010C	LEAD CONNECTOR-ASSY;,1P,600,YFH800-01,S,	
...3	HC401	BP96-00159A	ASSY HEAT SINK P;H/S,SCREW,FJL6920,FMP-3	S.N.A
....4	CIS	AA60-30001A	WASHER-PLATE;M3,ID3.5,15X8.5,T1.0,SBHG	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	BP62-00015A	HEAT SINK-PS;WT-36Z4HR,A1050S,T2.0,86,80	S.N.A
....4	CIS	BH73-00028B	SILICON/RUBBER-HS;TV ALL,SILICON,26*30*T	S.N.A
....4	CIS	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	CIS	0502-001230	TR-POWER;FJL6920YDTU,N,200000MW,TO-264 F	
....4	CIS	0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	
...3	HC801	AA96-00475A	ASSY H/S;-,REGULATOR,AA62-00066B,FML-G12	S.N.A
....4		AA62-00066B	HEAT SINK;D2,D3,AL ,T1.0,89,70,-,AA62-00	S.N.A
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P;-,	
....4		0402-001230	DIODE-RECTIFIER;FMG-G2CS,1000V,3A,TO-220	
....4		0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	IC301	AA96-50381A	ASSY H/S;-,-,AA62-30180B,LA7845,-	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1204-000517	IC-VERTICAL DEF.;LA7845,SIP,7P,-,PLASTIC	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30180B	HEAT SINK-ES;-,A6063 EXTR.,2,WHT,70MM,-,	S.N.A
...3	IC602	AA96-50369D	ASSY H/S;-,SOUND,AA62-30181F,TDA7269,HER	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1201-001385	IC-POWER AMP;7269A,ZIP,11,19.6,DUAL,13,P	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30181F	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
⚠ ...3	IC801S	AA96-50371H	ASSY H/S;-,SMPS,AA62-30181H,5Q1565RF,HER	S.N.A
....4		AA61-11028A	BRACKET;-,SECC,T1.0,-,-,-,-	S.N.A
....4		AA62-30181H	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		1203-002512	IC-PWM CONTROLLER;KA5Q1565RF-YDTU,TO-3PF	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	IC805	AA96-00243K	ASSY H/S;-,REGULATOR,AA62-000450A,KA78R0	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-	S.N.A
....4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
...3	IC901	AA09-00041A	IC MICOM;,SDA555X-0TP,3.3V,-,128K,SDIP,-	S.N.A
...3	JA701	3722-001884	JACK-SCART;42P,-,SNPB,BLK,-	
...3	JA702	3722-001767	JACK-PIN;2P(9P),-,NI,WHI/RED,-	
⚠ ...3	LR402S	AA27-10004F	COIL CHOKE;-,56uH,K,-,2.5A,BK,-,DR12x15,	
⚠ ...3	LR403S	AA27-00251A	COIL LINEARITY;10UH,10UH,YL81 DR1518,11M	
⚠ ...3	LR404S	AA27-40003P	COIL HORIZ. WIDTH;-,120uH/180uH,Th8x20,U	
...3	Q402	0505-001116	FET-SILICON;BUZ73A,N,200V,22A,0.6ohm,40W	
...3	Q804	BH99-00007S	ASSY HEAT/SINK;KSC2073,MICOM,HERCULES,BH	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	0502-001007	TR-POWER;KSC2073-H2,NPN,25W,TO-220,ST,6	
....4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
....4	CIS	BH62-00007A	HEAT SINK-TR;-,T1.0,L20*H30,CDA	S.N.A
⚠ ...3	RL801S	3501-001053	RELAY-POWER;5Vdc,530mW,10A,1FormA,15mS,5	
...3	T401	AA26-50001S	TRANS-HORIZ.DRIVE;-,-,-,6.0mH,-,-,44uH,-	

Level	Loc. No.	Code No.	Description ; Specification	Remark
⚠ ...3	T444S	AA26-00173A	TRANS FBT;FUJ34H001F(S),FUJ34H001F(S),1.	
⚠ ...3	T801S	AA26-00178A	TRANS SWITCHING;EER5345,K55A,PAL,CIS,160	
⚠ ...3	TU02S	AA40-00084A	TUNER;TCPS3000PC16B(S),PAL ,181CH,38.9MH	
...3	X601	2801-004020	CRYSTAL-UNIT;18.432MHz,30ppm,28-AAM,12pF	
...3		AA39-20536G	LEAD CONNECTOR-ASSY;,1P60MM,F,F,1617#22	
...3		AA95-03091A	ASSY SUB-PCB,FEATURE BOX;,K55A, ,PAL	
....4	BR01	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4	BR02	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4	CN01	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4	CN02	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4	CN03	3711-003601	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,ANGLE,	
....4	DC41	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
....4	DC51	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	DX01	2802-001177	RESONATOR-CERAMIC;2.696MHZ,0.4%,BK,10X4.	
....4	EC48	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	EC49	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	EX01	2801-004019	CRYSTAL-UNIT;20.25MHz,30ppm,28-AAM,13pF,	
....4	IC06	1203-002000	IC-VOL. DETECTOR;7027,TO-92,3P,-,PLASTIC	
....4		AA97-12148A	ASSY SMD;,K55A PAL	S.N.A
.....5	DC01	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5	DC02	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5	DC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC04	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC05	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC06	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....5	DC07	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5	DC08	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC09	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,	
.....5	DC10	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC12	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC13	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC14	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC17	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC19	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC20	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC21	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC22	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC23	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....5	DC24	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC25	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC26	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC27	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC28	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC29	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC30	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC31	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC32	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	DC33	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	DC34	2203-000896	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
.....5	DC35	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	DC36	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5	DC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC39	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	DC40	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5	DC43	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	DC45	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	DC49	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	DC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	DC52	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	DD01	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD02	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD03	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD04	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD05	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD06	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD07	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	DD08	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD09	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD10	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD11	0403-000746	DIODE-ZENER;RLZ3.9B,3.89-4.16V,500MW,LL-	
.....5	DD13	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD14	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD15	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD16	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD17	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD18	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD19	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5	DD20	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
.....5	DL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	DL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	DL03	2703-001070	INDUCTOR-SMD;100uH,10%,4.5x3.2x3.2mm	
.....5	DQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ02	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ03	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ04	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ05	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ07	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ08	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DQ09	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
.....5	DQ10	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5	DQ11	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	DR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR05	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR06	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR08	2007-000691	R-CHIP;3.3Mohm,5%,1/16W,DA,TP,1608	
.....5	DR09	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR10	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR13	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5	DR14	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5	DR15	2007-000869	R-CHIP;4.7Kohm,1%,1/16W,DA,TP,1608	
.....5	DR16	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR17	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR18	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR19	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR23	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP,1608	
.....5	DR24	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
.....5	DR25	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5	DR26	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR27	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....5	DR28	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....5	DR29	2007-000118	R-CHIP;390ohm,5%,1/16W,DA,TP,1608	
.....5	DR30	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR31	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR32	2007-000081	R-CHIP;2.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR33	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5	DR34	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR36	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR37	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR38	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR39	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR40	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....5	DR41	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....5	DR42	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR43	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR44	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR45	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR46	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR47	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR49	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR50	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR51	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR52	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR53	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR54	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR55	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR56	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR57	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5	DR58	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR59	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR60	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	DR61	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR62	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR63	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5	DR64	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR65	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	DR66	2007-000088	R-CHIP;7.5Kohm,5%,1/16W,DA,TP,1608	
.....5	DR68	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR69	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR70	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	DR80	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	DR81	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
.....5	DR82	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
.....5	DR86	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR87	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....5	DR88	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	EC01	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC02	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC04	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	EC08	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC09	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC10	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC12	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC13	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC14	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC15	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5	EC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC17	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC18	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC19	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC20	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC21	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC22	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC23	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5	EC24	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	EC29	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC30	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC31	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC32	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC33	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC34	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
.....5	EC35	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
.....5	EC36	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC39	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC40	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC41	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC42	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC43	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC44	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC45	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC46	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC47	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	EC51	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	EC52	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC53	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC54	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC55	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC56	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC57	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5	EC58	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	EC59	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	EC60	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	EC62	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC63	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC64	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EC65	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5	EL04	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5	EL05	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EL06	3301-001324	CORE-FERRITE BEAD;AB,15OHM,2X1.25X0.9MM,	
.....5	EL07	3301-001324	CORE-FERRITE BEAD;AB,15OHM,2X1.25X0.9MM,	
.....5	EL08	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EL09	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EL13	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	EQ04	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....5	EQ05	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....5	EQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	ER01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER02	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	ER06	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5	ER07	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5	ER09	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5	ER13	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER16	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER19	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	ER21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	ER22	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER24	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER25	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER26	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	ER29	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	ER30	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	ER31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	ER32	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	ER33	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	ER34	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	ER35	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	ER36	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
.....5	IC01	1204-001938	IC-DECODER;VSP9407B-B11,MQFP,80P,14X14MM	
.....5	IC04	1204-001989	IC-VIDEO PROCESS;CXA2165Q,QFP,64P,20X14M	
.....5	IC05	1203-002186	IC-POSI.FIXED REG.;18,DPAK,3P,240MIL,PLA	
.....5	IC10	1001-001177	IC-VIDEO SWITCH;TEA6425D,VIDEO SWITCH ,S	
.....5	IC11	0801-000662	IC-CMOS LOGIC;74HC123,MULTIVIBATOR,SOP,1	
.....5	PCB	AA41-00644B	PCB-PAL FERTURE BOX;CS29Z6,FR-4,4L,B,1.6	S.N.A
.....5	SC29	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SC31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SC33	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SC43	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	SC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	SC47	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5	SC48	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5	SC49	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	SL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	SR09	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	SR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	SR11	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	SR30	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR32	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR33	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR34	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5	SR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	SR36	2007-000259	R-CHIP;1.6Kohm,5%,1/16W,DA,TP,1608	
.....5	SR37	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5	TC01	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC02	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC03	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC04	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC05	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC06	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5	TC07	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5	TC08	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5	TD01	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5	TL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5	TQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	TQ02	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5	TR01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	TR03	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5	TR05	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR07	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5	TR08	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR09	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	TR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5	TR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3		AA97-13359B	ASSY ROBOT-MAIN;,K55A,RUSSIA	S.N.A
....4	C423	2301-001193	C-FILM,MPPF;1uF,5%,400V,TP,31x17x25,20	
....4	C803	2401-002227	C-AL;330uF,20%,450V,GP,BK,35x45,10	
....4	C815	2401-003024	C-AL;220uF,20%,200V,WT,TP,22x35,10	
....4	CN902	3711-003043	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
⚠ 4	CR405S	2301-001583	C-FILM,PPF;3NF,5%,2KV,TP,25X13X7MM,20	
⚠ 4	CR406S	2301-001583	C-FILM,PPF;3NF,5%,2KV,TP,25X13X7MM,20	
⚠ 4	CR407S	2301-001398	C-FILM,MPPF;3.3nF,5%,2kV,TP,29x8.5x1.5mm	
⚠ 4	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ 4	CX802S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ 4	CY802S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
⚠ 4	FP801S	3601-000297	FUSE-CARTRIDGE;250V,5A,TIME-LAG,GLASS,5.	
⚠ 4	IC401	1202-000103	IC-VOLTAGE COMP;,393,DIP8P,300MIL,DUAL,	
....4	IC601	1204-001971	IC-SOUND PROCESSOR;MSP3411G-P0-B11,DIP,5	
....4	IC803	1203-001225	IC-POSI.FIXED REG.;78R09,TO-220,4P,-,PLA	
....4	IC902	1103-001177	IC-EEPROM;24WC16,2048x8Bit,DIP,8P,-,-,2.	
....4	L808	AA27-00098A	COIL CHOKE;-,-,24uH,10%,-,0.1,3.0A,DR10X	
⚠ 4	LR405S	AA27-00057A	COIL HORIZ. WIDTH;-,10mH,YL-9N 15x27.5 C	
⚠ 4	LX801S	AA29-30002N	FILTER LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ 4	LX802S	AA29-30002N	FILTER LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ 4	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ 4	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
⚠ 4	PT801S	1404-001026	THERMISTOR-PTC;7ohm,20%,-,290V,25A,-,ST	
⚠ 4	TU01S	AA40-00083A	TUNER;TCLS3101PD16A(S),PAL B/G,D/K,I,M,1	
....4		AA97-13360B	ASSY AUTO-MAIN;,K55A,RUSSIA	S.N.A
.....5	C101	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C102	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C104	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
.....5	C105	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C106	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C107	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C108	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
.....5	C109	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
.....5	C110	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
.....5	C111	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C112	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C113	2202-000216	C-CERAMIC,MLC-AXIAL;0.027NF,5%,50V,SL,TP	
.....5	C116	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C201	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C202	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
.....5	C203	2202-000106	C-CERAMIC,MLC-AXIAL;1.5nF,20%,16V,Y5P,TP	
.....5	C204	2202-000106	C-CERAMIC,MLC-AXIAL;1.5nF,20%,16V,Y5P,TP	
.....5	C206	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C207	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C239	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C240	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C302	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
.....5	C303	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
.....5	C304	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
.....5	C305	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
.....5	C306	2301-000160	C-FILM,PEF;12nF,5%,50V,TP,11.0x6.0x9.0mm	
.....5	C307	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
.....5	C308	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
.....5	C401	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
.....5	C402	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
.....5	C403	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
.....5	C404	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
.....5	C408	2301-001143	C-FILM,PPF;56nF,5%,400V,TP,20x10x17,7.5	
.....5	C409	2303-001001	C-FILM,PPF;22nF,5%,630V,TP,18x14.5x8.5mm	
.....5	C411	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
.....5	C412	2301-000310	C-FILM,PEF;68nF,5%,50V,TP,8.0X8.5X4.0X5,	
.....5	C413	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
.....5	C414	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
.....5	C415	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,	
.....5	C416	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
.....5	C417	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C418	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
.....5	C420	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
.....5	C421	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
.....5	C422	2401-001527	C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
.....5	C424	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
.....5	C432	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C601	2201-000558	C-CERAMIC,DISC;0.47NF,10%,50V,Y5P,TP,5X3	
.....5	C602	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
.....5	C603	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C604	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
.....5	C605	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C606	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C607	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C608	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C610	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C611	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C612	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
.....5	C613	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
.....5	C614	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C615	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C619	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C620	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C621	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C622	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C623	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....5	C624	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....5	C625	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C626	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C627	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....5	C628	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C629	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....5	C630	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C631	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C632	2201-000370	C-CERAMIC,DISC;0.22NF,10%,50V,Y5P,TP,4X3	
.....5	C633	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....5	C634	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
.....5	C635	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C636	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....5	C637	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....5	C638	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....5	C639	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....5	C640	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C641	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C642	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
.....5	C643	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C644	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
.....5	C645	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C646	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C647	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
.....5	C648	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
.....5	C649	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm	
.....5	C650	2401-001176	C-AL;33uF,20%,25V,GP,TP,5x11,5	
.....5	C651	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C652	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C653	2401-002216	C-AL;2200uF,20%,35V,GP,TP,16x25,7.5	
.....5	C654	2201-000611	C-CERAMIC,DISC;0.056NF,5%,50V,C0G,TP,7X3	
.....5	C655	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
.....5	C656	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
.....5	C657	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
.....5	C658	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C659	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C660	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C701	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
.....5	C801	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
.....5	C802	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
.....5	C804	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
.....5	C805	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
.....5	C807	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.	
.....5	C808	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
.....5	C809	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
.....5	C810	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
.....5	C811	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
.....5	C812	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C813	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.	
.....5	C814	2201-002028	C-CERAMIC,DISC;0.47NF,10%,2KV,Y5P,TP,7.5	
.....5	C816	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
.....5	C817	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
.....5	C818	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
.....5	C819	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
.....5	C821	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
.....5	C822	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
.....5	C823	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
.....5	C824	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
.....5	C825	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C826	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	C827	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
.....5	C828	2201-000374	C-CERAMIC,DISC;0.22NF,5%,50V,C0G,TP,10.5	
.....5	C830	2201-000984	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
.....5	C831	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C832	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
.....5	C833	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
.....5	C834	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
.....5	C835	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
.....5	C836	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C837	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C838	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
.....5	C840	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
.....5	C841	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
.....5	C843	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C844	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C901	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C902	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C903	2202-000719	C-CERAMIC,MLC-AXIAL;6.8nF,20%,16V,Y5R,TP	
.....5	C904	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C905	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C906	2202-000791	C-CERAMIC,MLC-AXIAL;150pF,10%,50V,Y5P,TP	
.....5	C907	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
.....5	C909	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
.....5	C910	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
.....5	C911	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
.....5	C912	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C913	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C914	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C915	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C916	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C917	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C918	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
.....5	C919	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C920	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C921	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5	C922	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C923	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C924	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
.....5	C925	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C927	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
.....5	CN302	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
.....5	CN601	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
.....5	CN901	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
.....5	CW901	2503-000156	C-NETWORK;100pFx4,20%,50V	
.....5	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D202	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D207	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 5	D401	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 5	D402	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 5	D403	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 5	D404	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 5	D405	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D406	0404-001056	DIODE-SCHOTTKY;RK16,60V,1.5A,DO-204AC,TP	
⚠ 5	D408	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 5	D409	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
⚠ 5	D410	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D411	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
.....5	D603	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D607	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 5	D801	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 5	D802	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 5	D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 5	D804	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 5	D805	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D808	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 5	D812	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D816	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
.....5	D901	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D902	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D903	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D904	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
.....5	D907	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
.....5	DZ302	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
.....5	DZ303	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
.....5	DZ304	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
.....5	DZ305	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
.....5	DZ306	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
.....5	DZ307	0403-001118	DIODE-ZENER;MTZ30A,32V,26.99-28.39V,500m	
.....5	DZ401	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
.....5	DZ402	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	DZ404	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ601	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ602	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
.....5	DZ603	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ604	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ605	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ606	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ607	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
.....5	DZ608	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
.....5	DZ801	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
.....5	DZ802	0403-000716	DIODE-ZENER;MTZJ4.7B,4.7V,4.55-4.8V,500m	
.....5	DZ803	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
.....5	DZ804	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
.....5	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
.....5	DZ807	0403-001330	DIODE-ZENER;MTZJ30A,26.99-28.39V,500mW,D	
.....5	DZ808	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ902	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ906	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ907	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ908	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ909	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ910	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ911	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ912	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	EL201	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL202	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL203	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL204	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL401	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL402	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL407	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL408	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL805	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL806	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL807	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EL808	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY302	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY303	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY403	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY404	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY405	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY406	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY407	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY408	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY409	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY410	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY411	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY412	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY413	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY414	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY415	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY417	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY418	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY419	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY420	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY421	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY422	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY423	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY424	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY425	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY426	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY429	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY430	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY431	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY432	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY433	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	EY434	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY435	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY436	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY437	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY439	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY441	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY446	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY447	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY603	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY604	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY701	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY702	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY703	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY704	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY705	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY706	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY801	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY802	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY803	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY804	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY805	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY806	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY809	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY810	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY811	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY812	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY813	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY814	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY815	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY816	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY817	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY820	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY824	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY825	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY828	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY829	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY830	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY831	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY832	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY833	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY835	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY836	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY837	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY838	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY839	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY840	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY841	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY842	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY844	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY845	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY846	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY848	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY850	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY851	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY853	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY854	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY855	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY856	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY857	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY858	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY859	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY860	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY861	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY862	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY864	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY865	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY871	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	EY872	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
.....5	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
.....5	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
⚠ 5	FA801S	3601-000120	FUSE-AXIAL LEAD;125V,2.5A,FAST-ACTING,GL	
⚠ 5	FA802S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
⚠ 5	FA803S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
.....5	GT102	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT301	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT302	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT401	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	GT402	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT404	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT405	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT406	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT409	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT410	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT411	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT412	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	GT807	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
.....5	HIC401	AA13-00094A	IC HYBRID;-,DDRI001A,SIP,5P,-,TP	
.....5	IC202	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
⚠ 5	IC402	1203-000243	IC-POSI.FIXED REG.;7812A,TO-220,3P,-,PLA	
.....5	IC804	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
.....5	IC903	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
.....5	IC904	1203-001943	IC-VOL. DETECTOR;7025,TO-92,3P,-,PLASTIC	
.....5	J709	2001-000376	R-CARBON;150HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	L101	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
.....5	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
.....5	L103	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
.....5	L104	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
.....5	L106	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
.....5	L201	2701-000200	INDUCTOR-AXIAL;5.6uH,10%,4.2x9.8mm	
.....5	L203	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L402	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
⚠ 5	L403	2701-001040	INDUCTOR-AXIAL;10uH,10%,4.5x14mm	
.....5	L404	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L407	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L409	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L410	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
.....5	L601	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
.....5	L602	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
.....5	L603	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L604	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L605	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L606	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L607	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L608	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L609	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
.....5	L610	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L612	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L613	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L614	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L615	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L703	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L704	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L705	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L706	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
.....5	L801	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L802	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L803	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L804	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L805	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L806	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L807	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
.....5	L809	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L811	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
.....5	L901	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
.....5	L902	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
.....5	L903	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
.....5	L904	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
.....5	L906	2701-000215	INDUCTOR-AXIAL;8.2uH,10%,2.5x3.4mm	
.....5	L907	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L908	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
.....5	L909	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
.....5	PCB	AA41-00707B	PCB-MAIN;CS29Z6HP,FR-1,1L,B,1.6T,330X245	S.N.A
.....5	Q404	0505-000156	FET-SILICON;IRF620,N,200V,5A,0.8ohm,50W,	
.....5	Q601	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q603	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	Q801	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q802	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
.....5	Q803	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q901	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q906	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q907	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q908	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q909	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
.....5	Q910	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
.....5	Q912	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q913	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q914	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	R101	2001-000938	R-CARBON;680HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R102	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R103	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R104	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R105	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R106	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R107	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R108	2001-000969	R-CARBON;750HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R203	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R204	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R301	2001-001163	R-CARBON(S);5600HM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R302	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5	R303	2001-000016	R-CARBON(S);10HM,5%,1/2W,AA,TP,2.4X6.4MM	
.....5	R304	2008-001108	R-FUSIBLE(S);1.2ohm,5%,2W,AG,TP,3.9x12mm	
.....5	R305	2003-002205	R-METAL OXIDE(S);330ohm,5%,2W,AG,TP,3.9X	
.....5	R306	2003-002205	R-METAL OXIDE(S);330ohm,5%,2W,AG,TP,3.9X	
.....5	R307	2008-001114	R-FUSIBLE(S);1.5ohm,5%,2W,AG,TP,3.9x12mm	
.....5	R308	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5	R309	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R310	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R314	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R315	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R316	2001-001129	R-CARBON(S);330KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R317	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R401	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
.....5	R402	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
.....5	R403	2003-000532	R-METAL OXIDE(S);18ohm,5%,2W,AF,TP,4x12m	
.....5	R405	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
.....5	R409	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
.....5	R410	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
.....5	R411	2001-000028	R-CARBON(S);1000HM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R412	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
.....5	R413	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
.....5	R414	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
.....5	R415	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
.....5	R416	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
.....5	R418	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R419	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R420	2004-001987	R-METAL(S);4.3Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5	R421	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R422	2008-001149	R-FUSIBLE(S);0.22OHM,5%,2W,AF,TP,3.8X11M	
.....5	R423	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
.....5	R424	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
.....5	R425	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
.....5	R426	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
.....5	R428	2004-000698	R-METAL;3.3Kohm,1%,1/4W,AA,TP,2.4x6.4m	
.....5	R430	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
.....5	R431	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
.....5	R432	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R433	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
.....5	R434	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	R435	2003-000784	R-METAL OXIDE(S);7.5Kohm,5%,2W,AF,TP,4x1	
.....5	R440	2004-002019	R-METAL(S);33Kohm,1%,1/2W,AA,TP,2.5x6.5m	
.....5	R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R602	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R603	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R604	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R605	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R606	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R607	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R608	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R609	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R610	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R611	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R612	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R613	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R614	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R615	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R616	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R617	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R618	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R623	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R624	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R626	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R627	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R628	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R629	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R630	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R631	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R632	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R633	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R634	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R635	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R636	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R637	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R638	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R639	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R704	2001-000969	R-CARBON;750HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R710	2001-000376	R-CARBON;150HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R715	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R716	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R717	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R718	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R723	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R801	2001-000019	R-CARBON(S);100HM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R802	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
.....5	R803	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
.....5	R804	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
.....5	R805	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R806	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R807	2001-001103	R-CARBON(S);20KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R808	2001-001197	R-CARBON(S);910OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R809	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R810	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R811	2001-001155	R-CARBON(S);5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R812	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R813	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R815	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
.....5	R816	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R817	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R818	2001-001131	R-CARBON(S);33KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R819	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
.....5	R820	2001-001096	R-CARBON(S);2.2OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R821	2004-002015	R-METAL(S);140Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5	R822	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R823	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R824	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R827	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
.....5	R828	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm	
.....5	R829	2008-001148	R-FUSIBLE;3.3OHM,5%,1W,AG,TP,3.9X12MM	
.....5	R830	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
.....5	R833	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R835	2003-002181	R-METAL OXIDE(S);68Kohm,5%,2W,AG,TP,3.9x	
.....5	R838	2001-001050	R-CARBON(S);1.5KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R840	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R841	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R842	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R901	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R902	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R903	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R904	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R905	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R906	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R907	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R908	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R909	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R910	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R911	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R912	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R913	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	R914	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R915	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R916	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R917	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R919	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R920	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R921	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R922	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R923	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R924	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R925	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R926	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R927	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R928	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R935	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R936	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R937	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R938	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R940	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R941	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R942	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R945	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R946	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R947	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R948	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R951	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R952	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R953	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R954	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R955	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R958	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R960	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R961	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R962	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R963	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R965	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R966	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R967	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R968	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R972	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R973	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R974	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R981	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R982	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R983	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R984	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R988	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 5	RR430S	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
⚠ 5	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 5	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 5	VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ 5	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
.....5	X901	2801-003728	CRYSTAL-UNIT;6MHz,30ppm,28-AAM,20pF,40oh	
...3		AA61-00707B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
..2		AA96-00908E	ASSY COVER P-TERMINAL BOARD;29Z6,CIS,HIP	
...3		AA64-02823A	INLAY-T/BOARD;Z7,PS SHEET,T0.5,PAL	S.N.A
...3		AA65-00025A	TERMINAL-BOARD,ANT;,HIPS V0,BLK	S.N.A
⚠ ..2		AA96-20130H	ASSY POWER CORD;-,CP2/NO(4.0R),H/S 500MM	S.N.A
...3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3		AA39-10003B	CBF POWER CORD;-,KJP-140,KLCE-2F,2.4m,HO	
...3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A
..2		AA65-00011B	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
..2		AA61-01190A	HOLDER-CHASSIS;Z7,HIPS V0,G4309	S.N.A
..2		AA94-07792A	ASSY PCB MISC-DYNAMIC FOCUS;CT-29Z7HR,K5	
...3	LH01	AA26-90002C	TRANS-DUMMY;-,-,-,-,-,-,-,-,-,-,-,EER2	
...3	LH02	AA27-40003L	COIL HORIZ. WIDTH;-,1.0mH,DR14x20,2UEW0.	
...3	RH28	2008-001113	R-FUSIBLE(S);0.22ohm,10%,2W,AG,TP,3.9x12	
...3	WIRE3	AA39-20061C	LEAD CONNECTOR-ASSY;,3P,200,YFH800-03,S,	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-07229L	ASSY AUTO-DYNAMIC FOCUS;CT-29Z7HR,K55A	S.N.A
....4	EY01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY03	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY04	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY05	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY06	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY07	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY08	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY09	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	GTH01	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTH02	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTH03	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	PCB	AA41-00152C	PCB-DOUBLE FOCUS;CW29A6VN8X/XEF,FR-1,1L,	S.N.A
..2		AA94-11730A	ASSY PCB MISC-MASTER;Z6,Z7Z9,K55A,S57A,P	
...3	GTAY01	AA39-20179C	LEAD CONNECTOR-ASSY;,3(2)P,600MM,YFH800-	
...3	HP+PCB	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
...3	MPP+LP	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
⚠ ...3	SW811S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
...3		AA97-05539A	ASSY AUTO-MASTER;WS36Z48D,KS4A,PAL	S.N.A
....4	EY01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY03	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	EY04	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
....4	GTY05	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY06	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY07	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY08	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY09	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GTY10	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	PCB	AA41-00521A	PCB-MASTER S/W;CS32Z4,FR-1,1L,A,1.6T,245	S.N.A
...3		AA61-00719B	HOLDER-MASTER;T6,W3,HIPS V0,BLK,J52A	S.N.A
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA94-11731A	ASSY PCB MISC-LED;CS29Z6HPJX/BWT,K55A	
...3	CN01	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,500,YBNH025-05,6	
...3	CY01	2401-002291	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	
...3	LD01	0601-001381	LED;ROUND,RED/GRN,5.0MM,650/563NM	
...3	RM01	AA32-00012A	MODULE REMOCON;ORC-50HF2,38KHZ,940NM,MES	
...3		AA97-12478A	ASSY AUTO-LED;CS29Z6,K55A	S.N.A
....4	DC01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DC02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	PCB	AA41-00702A	PCB-LED;WS32Z6HF,FR-1,1L,A,1.6T,245X245,	S.N.A
....4	RY01	2001-000020	R-CARBON(S);220HM,5%,1/2W,AA,TP,2.4X6.4M	
..2		AA94-11750B	ASSY PCB MISC-A/V SIDE;34Z6HP,K55A,PAL	
...3	AV+CV	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
...3	CN701	AA39-00317B	LEAD CONNECTOR-ASSY;K55A/WT-32Z4HD,UL100	
...3	CN703	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,500,YBNH025-05,6	
...3	CN704	AA39-00070B	LEAD CONNECTOR-ASSY;,4P,500MM,YBNH250-04	
...3	JA701	3722-001164	JACK-PIN;3P,3.4mm,SN,WH:YE:RE,#16-22	
...3	JK04	3722-000544	JACK-VHS;4P,11.5mm,AG,BLK,N	
...3	JKH701	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	
...3		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
...3		AA96-00940B	ASSY COVER P-COVER A/V;CS34Z6HP,HIPS HB,	
....4		AA63-60001R	SPACER-FELT;-,FELT,-,-,-,-,T0.35,-,200X1	S.N.A
....4		AA64-02667B	INLAY-AV;Z7,PS SHEET,T0.3,DGN-K189,K55A	S.N.A
....4		AA63-00572A	COVER-A/V;34Z6,HIPS,HB,G4309,DGN-1189	S.N.A
...3		AA97-12697A	ASSY AUTO-A/V SIDE;,K55A,PAL,29Z6	S.N.A
....4	C701	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C702	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C707	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C708	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	DZ701	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500m	
....4	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L705	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L706	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L707	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L708	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	PCB	AA41-00620B	PCB-A/V SIDE(Z7);CT-29Z7HR,FR-1,1L,B,1.6	S.N.A
....4	R701	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R702	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	

ASSY CPT

1		AA91-02964A	ASSY CPT;CS34Z4HF9X/BWT	S.N.A
..2		AA91-02176B	ASSY CPT;A80LTM350X98,34,+380MG,ITC,AA0	S.N.A
⚠ ...3		AA03-00232A	CRT COLOR;A80LTM350X98,+380MG,0.35MH,9.9	
..2		AA98-70011F	ASSY TBC WIRE(P);-,34inch,NTSC,2P-WH,KS4	S.N.A
..2		AA27-00060A	COIL DEGAUSSING;-,34,14ohm ,-,L3600,E	

Level	Loc. No.	Code No.	Description ; Specification	Remark

ASSY COVER REAR

1		AA90-03250B	ASSY COVER REAR;CS34Z6HPGX/BWT	S.N.A
..2		AA64-02749B	CABINET-BACK;34Z6,ABS,V0,G4309,SVM2012	
..2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A

ASSY COVER FRONT

1		AA90-03247B	ASSY COVER FRONT;CS34Z6HPGX/BWT	S.N.A
..2	CA+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	CB+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CB+TBA	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CC+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	CRT+CF	AA60-10050V	SCREW-ASSY;-,SWRCH18A,M6,L30,HH,+,WC,-,Z	S.N.A
..2	D-COIL	AA65-30017A	CLAMPER CORE-D,COIL;-,NYLON-66,V0,-,NTR,	S.N.A
..2	PP+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	SPK+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2	TBA+RJ	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2		AA96-00975D	ASSY COVER P-RACK;TR-34Z6,SVM2012,DIY, S	
..2		AA73-00017A	RUBBER-CAP;29Z7,SILICONE RUBBER,WHT	S.N.A
..2		AA73-00005B	RUBBER-CAP;FLAT,PRJ,SILICONE RUBBER,WHIT	
..2		AA96-00934B	ASSY COVER P-FRONT;CS34Z6HP,34Z6,ABS, HB	
...3	DP+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
...3	KNOPOW	AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A
...3		AA64-02753A	INDICATOR LED;29Z6,ACRYL,HB,CLEAR	S.N.A
...3		AA64-02752A	WINDOW-RMC;29Z6,PC,V0,VIOLET	S.N.A
...3		AA64-70124C	BADGE-BRAND;-,AL,-,-,L=70,SAMSUNG,SILVER	S.N.A
...3		AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA60-00091C	SPACER-FELT;-,FELT,230X10,-,-,BLK,T1.0,-	S.N.A
...3		AA60-00091J	SPACER-FELT;-,FELT,330X10,-,-,BLK,T0.5,-	S.N.A
...3		AA64-02748B	CABINET-FRONT;CS34Z6HP,ABS,HB0690M,G4309	S.N.A
...3		AA64-02750A	DECORATION-POWER;29Z6,ABS,HB,GRAY,AL	
...3		AA64-02751B	KNOB-POWER;29Z6,PC,VO,VIOLET,MASTER	
..2		AA91-00507A	ASSY HOLDER SPK;-,-,8OHM/15W,-,ASSY HOLD	
..2		AA63-60004K	SPACER-GUM,CRT;-,NTR RUBBER,-,-,-,BLK,T2	S.N.A
..2		AA65-00019A	CLAMPER CORE-D,COIL;25-34,NYLON 66,V2,N	S.N.A

ASSY ACCESSORY

1		AA92-06199A	ASSY ACCESSORY;29Z6,RUSSIA,K55A	S.N.A
..2	1	AA68-02479A	MANUAL USERS;CS29Z7HP,RUS,K55A,PIP,TTX	
..2		6801-001073	CARD-REGISTRATION;RUS,XEV,RUS,MOJO100,-,	S.N.A
..2		AA59-00266D	REMOCON;TM63,HERCULES,45,SAMSUNG,EX,RUSS	
...3		2802-000194	RESONATOR-CERAMIC;8MHz,1.0%,TP,8.5x4.5x5	
...3		AA09-00275A	IC MICOM;Z86L8808SSC-R51PX,SOP,ST,SZTM-8	
..2		AA68-00952A	CARD-COUPON;-,A/P100(G),AA68-00949A,-,-,	S.N.A
..2		AA69-00862A	BAG PE;-,HDPE PE FOAM,T0.03,W400,H240,-,	S.N.A
..2		AA68-01402A	MANUAL-GOOD WILL LETTER;,CIS,B5,1PAGE,A/	S.N.A
..2		AA68-01120A	MANUAL SERVICE;-,-,CIS,A4,6PAGE(FOLD),W/	S.N.A
..2		AA68-00816B	CARD WARRANTY-01;,RUSSINA,2,W/P 120G,BOT	S.N.A

ASSY P/MATERIAL

1		AA92-05373B	ASSY P/MATERIAL;CS34Z6HPGX/BWT	S.N.A
..2		AA69-00306A	BAG AIR;LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A
..2		AA69-00744F	BAG-SHEET;-,HDPE PE FOAM,T0.015,W1400,H1	S.N.A
..2		AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,	S.N.A
..2		AA63-10007C	BAND-PP;W18,CLEA,1G	S.N.A
..2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A